

LARGEST CIRCULATION OF ANY MECHANICAL PUBLICATION IN THE WORLD

127 Articles

105 Illustrations

OCTOBER, 1905


VOL. VII. NO. 10

Price
10 cts.

POPULAR MECHANICS

WRITTEN SO YOU CAN UNDERSTAND IT

BURNING CARTRIDGES ARE NOT DANGEROUS
LOCOMOTIVE LOST IN JUNGLE TURBINE SHIP 800 FEET LONG
HOW AN AUTOMATIC SPRINKLER WORKS
RECOVERING A SUBMERGED ISLAND
FAN-DRIVEN ICE BOAT CANAL BOATS LIFTED 75 FEET
CAPPED PROJECTILES PIERCE HEAVY ARMOR



ELECTRIC VIOLIN--MOST WONDERFUL OF ALL MUSICAL INSTRUMENTS

Machinery and Supplies from the St. Louis World's Fair

The Chicago House Wrecking Company bought the complete LOUISIANA PURCHASE EXPOSITION, which cost over Fifty Million Dollars to construct. Here is an opportunity for you to purchase supplies of every kind at extremely low prices.

We are the largest Machinery Dealers on earth. Our plant covers 25 acres, and we are in a position at all times to supply anything needed in the Machinery or General Supply line.

ELECTRICAL APPARATUS

A Million Dollars' worth of material, good as new.

Rubber Covered Wire in sizes from No. 14 to 500,000 C. M.

Weatherproof Wire, sizes No. 14 to No. 2-0.

Slow Burning Weatherproof Wire, 16 to 600,000 C. M.

Lead Covered Cables, all voltages and sizes.

100,000 used Incandescent Lamps, practical for further service, each 5 cts.

200,000 new Incandescent Lamps, 104 Voltage, 8 candle power in natural colors, Amber, Green, Opal and Ruby.

200,000 No. 9171 Receptacles.

Weatherproof Sockets, Knobs, Cleats and thousands of other items. Write for our complete list.

MOTORS

50 Motors, ranging from 1 to 45 H. P. These Motors were used only during the Exposition and are practically new; Voltages 110 to 500.

PIPE

10,000,000 feet of Standard Black and Galvanized Wrought Iron Pipe; also Hydraulic Pipe, extra heavy pipe, steel riveted pipe, spiral riveted pipe, converse joint pipe, cast iron pipe, tile pipe and pipe of every kind.

VALVES AND FITTINGS

Thousands of them for sale, good as new. Also fittings of every kind.

BOLTS, RODS, LAG SCREWS ETC.

1,000 tons Bolts, Rods, Lag Screws, Turnbuckles and Washers.

150 Track and Lever Jacks.

LUMBER AND BUILDING MATERIAL

100,000,000 feet of highly seasoned Lumber from the Exposition. Also Sash, Doors, and Building Material of every kind. Send us your bills for our estimate. We will save you big money.

CONTRACTORS' SUPPLIES

4,000 Steel Shovels.

500 Steel Picks.


600 Mattocks, Lanterns, Axes, etc.

500 Wheelbarrows.

Thousands of other items: Furniture and Office Equipment, Household Goods, Settees, Fire Extinguishers, Tanks, Safes, Flags and Flag Poles, Roofing Material, and in fact anything manufactured.

WRITE FOR OUR SPECIAL CATALOGUE NO. 539

CHICAGO HOUSE WRECKING CO.. West 35th and Iron Sts., Chicago



WEBER GAS POWER

Would you be interested if we could prove to you that our **Suction Gas Producer** and **Producer Gas Engine** would pay first cost in the saving in less than one year?

COMPLETE PRODUCER PLANT

1 Pound
H. P.
Hour

Charcoal.
Anthracite
Pea Coal,
Coke,
Lignite

Read the names of Wise Power Users (partial list only) using Gas Producer Power Plants, and saving \$

Write to
all of
them

Brooks Elevator Co., Minneapolis, Minn., 125 H. P.
Hermosillo Electric Light Co., Hermosillo, Mex., 225 H. P.
Pierce Electric Light Co., Pierce, Neb., 60 H. P.
Regent Shoe Co., Omaha, Neb., 50 H. P.
Purdy Roller Mills, Purdy, Mo., 50 H. P.
Gilliam Electric Light Co., Gilliam, Mo., 50 H. P.
Hunkins-Willis Lime & Cement Co., St. Louis, Mo., 60 H. P.
Lustre Mining Co., El Oro, Mex., two 100 H. P.
Pablo Gaudin, Parral, Mex., 125 H. P.
C. E. Hertline, New York, N. Y., 125 H. P.
The Gamer Co., Ft. Worth, Texas, 60 H. P.
Archbishop's Palace, Oaxaca, Mex., 16 H. P.
Sonora Mining & Development Co., Nacozari, Mex., 30 H. P.
Caesar Marburg, Hermosillo, Mex., 16 H. P.

7 H. P. up--Suitable for all Power Purposes

WEBER GAS AND GASOLINE ENGINE COMPANY
BOX 358, KANSAS CITY, MO.

Please mention Popular Mechanics when writing Advertisers.

OCTOBER, 1905

Popular Mechanics

160 WASHINGTON STREET

JOURNAL BUILDING, CHICAGO, U. S. A.

H. H. WINDSOR.....EDITOR

SUBSCRIPTION, \$1.00 PER YEAR

MAILED POSTAGE FULLY PREPAID TO ANY
ADDRESS IN THE WORLD

All subscriptions are discontinued at expiration
Please examine the date printed on your wrapper

Published Monthly by POPULAR MECHANICS COMPANY
Entered as mail matter of the second class at the postoffice at Chicago, Ill.

Eastern Advertising Office: 116 Nassau St., New York

CONTENTS.

BURNING CARTRIDGES NOT DANGEROUS	1003
Auto Track Racing to Cease.....	1004
Automobile Combination Chemical Fire Engine and Hose Wagon	1005
FREIGHT AND PASSENGER COLLISION	1006
Transportation of Bananas.....	1006
Secret Telephone Exchange.....	1006
FAN-DRIVEN ICE VEHICLE	1007
Superintendents Should Superintend.....	1007
GRANITE COLUMNS WITH STEEL CENTERS	1008
Army Motor Wagons with Wooden Wheels.....	1008
Zirconium, New Filament.....	1009
Maps of River Beds.....	1009
CEMENT BLOCK CIRCULAR SILO	1009
CANAL BOATS WITH LOADS ELEVATED 75 FEET	1010
RAILROAD TRACK OF THE FUTURE	1011
THREE ACRES OF ROCK BLOWN UP	1012
HOW AN AUTOMATIC SPRINKLER WORKS	1013
Pompeii's Waterworks	1014
A Lampless Lighthouse.....	1014
Observation Street Car.....	1014
LARGEST MARINE BOILERS EVER BUILT FOR GREAT LAKES	1015
English Opinion of American Boiler Inspection.....	1015
LOCOMOTIVE LOST IN A JUNGLE	1016
How Varnish is Made.....	1016
RECOVERING A SUBMERGED ISLAND	1017
Cause of "Bennington" Accident.....	1019
STEAMER WRECKS STREET CAR	1019
Reinforced Concrete Sewer Pipe.....	1019
NOTABLE WHARF IN MEXICO	1020
Smallest Navies in the World.....	1020
1906 Style Auto.....	1020
THE ARMOR-PIERCING POWER OF THE CAPPED PROJECTILE	1021
Air Cushion Absorbs Shock in Auto Travel.....	1023
Clock Shows Time in Thirteen Cities.....	1023
Street Car Passengers Draw Prizes.....	1023

New Type Balloon "Swanske".....	1024
How Togo Fooled the Russians.....	1024
Turntable for Automobiles.....	1024
MAY RAISE THE "MAINE"	1025
CANADA REVIVES GEORGIAN BAY CANAL PROJECT	1025
HOW TO MAKE AN ADJUSTABLE SHAV- ING MIRROR	1026
"Pop" Wise as His Ancestors.....	1026
TURBINE SHIPS 800 FEET LONG	1027
Unique Marine Pulpit.....	1028
THE ELECTRIC VIOLIN A SUCCESS	1028
The Handleless Hand Car.....	1030
Municipal Telephony a Failure in England.....	1030
CHEMISTRY FOR MECHANICS—PART II	1040
French Flag-Ship "Jauréguiberry".....	1051
MECHANICS FOR YOUNG AMERICA— How to Build an Electric Engine.....	1052
Novel Electric Motor.....	1052
How to Make a Sailomobile.....	1053
Novel Burglar Alarm	1054
Simple X-Ray Experiment.....	1054
To Build a Merry-Go-Round.....	1054

SHOP NOTES.

A Pipe Hacksaw Frame.....	1031
Home-Made Water Heater.....	1031
Battery Economizer for Telephones.....	1031
Varnish Precepts	1031
Drawing Five-Pointed Stars.....	1032
Home-Made Level	1032
Straightening Wire in the Lathe.....	1032
Waterproof Electric Light Sockets.....	1032
Babbitting Ladle Made of Pipe.....	1033
To Cut Thin Steel Without Tempering.....	1033
Cleaning Smoked Ceilings.....	1033
Home-Made Post Auger.....	1033
Chemical Formula Table for Painters.....	1034
Thawing Frozen Ground with Lime.....	1034
Automatic Cut-Off for Electric Lights.....	1034
To Make a Steam Gauge Alarm.....	1035
How to Paint Iron, Zinc and Galvanized Iron.....	1035
Putting a New Base Under a Boiler.....	1035
How to Make Celluloid Incombustible.....	1035
Sled for Moving Lawn Sprinkler.....	1036
Rack for Kitchen Utensil Covers.....	1036
Easy Method of Burning 50 Bushels of Charcoal.....	1036
How to Make a Pneumatic Paint Mixer.....	1037
Acid-Proof Ink for Zinc.....	1037
Mending Porcelain and Granite Ware.....	1037
Simple Tap Wrench.....	1037
Home-Made Blueprint Frame.....	1038
Press-Stopping Device	1039
How to Make an S-Wrench.....	1040
Making a Spring Head.....	1040
Boring on the Turret Lathe.....	1040
How to Burn Sawdust.....	1041
Another Safe Rail Grip.....	1042
Repairing Cracked Water Jackets.....	1042
Some Electric Plant Troubles and What Cured Them	1042
How to Make and Use a Cylindrical Square.....	1043
Weight of Lead Pipe.....	1043
How to Build a Cheap Water Wheel.....	1044
Cement Required for Surfacing.....	1044
Make the Saw Fit the Work.....	1044
To Keep Show Windows from Sweating.....	1045
Improved Emergency Boiler Feed.....	1045
Heating Iron in Cold Water.....	1045
Simple Method of Drawing an Ellipse.....	1046
Flexible Varnish	1046
Method of Protecting Water Pipes from Freez- ing	1046
Simple High and Low Water Alarm.....	1047
How to Wind a Single Cylinder Motor.....	1047
Matches for Cutting Gauge Glasses.....	1047
Grade the Steam Pipe.....	1047
Substitute for Auto Starter.....	1048
Simple Babbitt Ladle.....	1048
Heating System	1048

FREE! To Those Accepting Our Proposition


**DRAUGHTSMEN! TOOL MAKERS! MACHINISTS!
ELECTRICIANS! PATTERN MAKERS! EVERYBODY!**

A New, Handy and Convenient Device for Taking Measurements is the

Wiet-Goethe Combination Gauge

Now Offered
for the
first time
to
those
Interested

Full Size



The Scale is graduated to 64ths of an inch.
The Protractor in degrees and numbered.

Did it ever occur to you when called upon to perform some mechanical work to be confronted by almost insurmountable difficulties because you did not have handy the right kind of a tool to take measurements?

Is it practical for any man to carry a cumbersome tool chest to take measurements?

Suppose you could carry in your vest pocket all in one instrument

An Outside Caliper An Inside Caliper A Divider A Straight Edge An Angle Edge
A Depth Gauge A Try Square A Center Square An Angle Protractor A Center Gauge
and many other combinations too numerous to mention, but understood and appreciated at once by all having to deal with any kind of measurements.

We now present a tool which will enable you to fill all these requirements and take all measurements, within its scope, accurately and quickly.

It is made of superior steel, carefully and thoroughly tested as to its accuracy.

It will be found to be a novel and valuable addition to the tool chest of any mechanic.

The practical men will find constant and novel uses for it under any and all circumstances.

It will enable one to solve all the different and difficult problems which arise in the shop or elsewhere.

It is so portable and convenient—being small enough for the pocket—that it can always be at hand.

The gauge is made by first-class mechanics and no expense is spared to insure accuracy. We commend it as a finished and perfect tool for the various uses to which it can be put.

The combination gauge is enclosed in a neat leatherette case with metal trimmings, so as to be conveniently carried in the pocket.

HERE IS A SPECIAL OFFER. READ IT.

We want to increase the Subscription List to our Monthly Journal

MODERN MACHINERY The foundation of civilization rests on inventions of new machinery. To keep abreast of mechanical progress should be the aim of every intelligent man. Our publication keeps you informed, and it is written so all can understand it, and the best illustrated of its class. **MODERN MACHINERY costs \$1.00 a year.** We want to get you started reading this paper regularly, and therefore make you this offer.

Send us your subscription, at once, enclosing \$1.00, and we will mail you **MODERN MACHINERY** every month for one year and a **WIET-GOETHE COMBINATION GAUGE FREE** at once. If not just as represented, send the gauge right back and we will refund your money. Don't delay accepting this proposition; write to-day. Remember, money back to-morrow if dissatisfied. If you are at present a subscriber to **MODERN MACHINERY** you may take advantage of our offer, and we will extend your subscription one year ahead from present date of expiration.

Modern Machinery Publishing Co., Security Bldg., Chicago, Ill.

COUPON

MODERN MACHINERY PUBLISHING CO., 13 Security Building, Chicago


Date _____

Gentlemen:—Enclosed find \$1.00 for which please send me **MODERN MACHINERY** for one year, and also send me one **WIET-GOETHE COMBINATION GAUGE FREE** as advertised in your Journal. It is understood that if I am dissatisfied that I may return the gauge and my money will be refunded.

ALL STEEL TRY SQUARES

TEMPERED BLADES

The Goodell-Pratt Try Squares were made to meet the demand for a better grade than has heretofore been used by carpenters and wood workers. They meet it at every point. ❀ ❀ ❀




Made with graduated blades. The graduations are put on with dividing engines, ensuring absolute accuracy.

The beams have a patent rest, so that the tool will lie flat on the work and stay there without being held in position.

Handle is nickel-plated. Blade is highly polished.

- No. 906. Length of blade, 6 inches.
- No. 908. Length of blade, 8 inches.
- No. 910. Length of blade, 10 inches.



This tool is of the same high quality, and in all respects is the same as the above, except that it has no graduations.

- No. 806. Length of blade, 6 inches.
- No. 808. Length of blade, 8 inches.
- No. 810. Length of blade, 10 inches.

THESE TRY SQUARES ARE PACKED
ONE IN A BOX.

Write to-day for Catalogue No. 7, which tells all about them, and about many other new tools.

GOODELL-PRATT COMPANY, Greenfield, Mass.

This One



88FJ-RC4-GDCN

Mechanical Engineering Technical

BOOKS

You can get any book published on Mechanics, Engineering, Electricity, Steam, Fuels, Metal or Woodworking, and all the Individual Trades and Professions, in fact any book on any subject, published in this country or Europe, that is obtainable, through the

Popular Mechanics Book Dept.

In every case we prepay in full all mailing or express charges.

Any book desired can be earned by securing one or more subscribers to Popular Mechanics. State book wanted and we will advise you how many subscribers will secure it. This is a very easy way to get the best books.

ENGINEERING

GAS ENGINES. With Instructions for Care and Working of the Same. By G. Lieckfield; translated by Geo. Richmond. 120 pages; illustrated; 12mo.; cloth. Price, \$1. To which has been added full directions for the management of oil engines.

TRACTION ENGINE ITS USE AND ABUSE. By James H. Maggard. Small 12mo.; cloth; illustrated. Price, \$1. Revised and enlarged by an expert engineer. Deals in detail with the principles and parts of a traction engine; directions for starting an engine; use of gauge, try cocks, pumps, governor, slide valve, etc.; water supply; the boiler, its care and management; methods of a good fireman; the engine; handling a traction engine. The book is teeming with practical points and suggestions put in very simple language and very effective manner. It should be in the hands of every man who runs a traction engine. The farmer and creamery operator, especially, should not be without it.

HANDBOOK OF MODERN STEAM FIRE-ENGINES. (Roper's Engineers' Handy Book series.) Price, \$3.50. The only book of the kind ever published in this country. Contains descriptions and illustrations of all the best types of steam fire-engines, and fire pumps, injectors, pulsometers, inspirators, hydraulic rams, etc.; and treats more extensively of Hydraulics than any other book on the market.

SIMPLE PROCESS FOR ESTIMATING THE HORSE POWER OF STEAM ENGINES. By Edwin R. Keller, M. E. New edition. Price, 50c. Contains various methods of estimating and calculating the horse power of boilers and engines and ascertaining the power required to run line shafts, individual machines, etc., etc.

MODERN MACHINE SHOP TOOLS. By W. H. Vandervoort. Large 8vo. 555 pages; 673 illustrations; cloth. Price, \$4. Just out, this "masterpiece of the machine shop," no machinist can afford to be without it. Treats the subject of Modern Machine Shop Tools in a concise and comprehensive manner. Each tool is considered from the following points: First—its construction with hints as to its manufacture; second—its operation, proper manipulation and care; third—numerous examples of the work performed. A book in which the apprentice will find a thorough course of instruction, the mechanic a valuable manual of practice and the superintendent and foreman many valuable suggestions. In fact, it is in all respects the most complete, concise and useful work ever published on the subject. Of incalculable value as a work of reference. In 34 chapters.

PRACTICAL GAS ENGINEER. What It Is and How To Do It. Cloth. Price, \$1.

RECORD BOOK—VALVE SETTING. By A. B. Low. 120 pages; quarto; stiff covers. Price, 60c. For the use of marine engineers.


WATER WHEELS. By A. B. Cullen. 63 pages; 12 plates; quarto; cloth. Price, \$2. Of all the books on Pumps and Hydraulic Motors this is one of the

most practical. Treats of the construction of horizontal and vertical water wheels.

COMPRESSED AIR: ITS PRODUCTION, USES AND APPLICATIONS. By Gardner D. Hiscox, M. E. 4th edition, revised and enlarged; 820 pages; 545 illustrations; cloth. Price, \$5. The most thorough and comprehensive treatise on the subject of compressed air that has ever been published. Well printed and substantial. No phase of the subject is omitted. Is a complete compendium in 36 chapters, valuable for reference and for study. Contents: The physical and operative properties of air from a vacuum to its liquid state; its thermo-dynamics; compression, transmission and uses as a motive power in operation of stationary and portable machinery in engineering, mining and manufacturing work; air tools; air lifts; pumping of water, acids and oils; the air blast for cleaning and painting; the sand blast and its work; and the numerous appliances in which compressed air is a most convenient and economical transmitter of power for mechanical work, railway propulsion, refrigeration and the various uses to which compressed air has been applied. Contains a list of patents on compressed air from 1875 to date, and 40 tables of the physical properties of air, its compression, expansion and the volumes required for various kinds of work.

ELECTRICAL ENGINEERING FOR ELECTRIC LIGHT ARTISANS AND STUDENTS. By Slingo and Brooker. 346 illustrations; 12mo. Price, \$3.50. This new and revised edition contains all data and formulae relating to this branch of electrical application.

ENGINEERS' PRACTICAL TEST. Actual size, 6x4½ inches; stiff silk cloth. Price, \$1. A guide for all men in or about power plants. Indispensable to engineers, mechanics, machinists, firemen, etc. Tells how boilers and engines should be managed. All about gas engines, engineers' license examination questions and answers.



MECHANICAL ARTS SIMPLIFIED. By D. B. Dixon, comp. 497 pages; actual size, 8¼x5½ inches; illustrations. Price, \$1.50. With an appendix containing a thorough electrical department, an exhaustive treatise on ice making and a large collection of miscellaneous practical examples. A thorough and original reference book for architects, iron workers, boiler-makers, contractors, civil and mechanical engineers, firemen and ice machine men.

VAN NOSTRAND SCIENCE SERIES. 16mo. Boards. 50c. each. Ample illustrated when the subject demands. Put up in a uniform, neat and attractive manner. Subjects are of an eminently scientific character and embrace a wide range of topics. The following citations may be noted as types of this notable set:

CHIMNEYS FOR FURNACES AND STEAM BOILERS. R. Armstrong, C. E. 3rd American edition. Revised and partly re-written, with an appendix on "Theory of Chimney Draught," by F. Idell, M. E.

STEAM BOILER EXPLOSIONS. By Zerah Colburn. New edition. Revised by Prof. R. H. Thurston. Price, 50c.

FATIGUE OF METALS UNDER REPEATED STRAINS. Price, 50c. With Various Tables of Results and Experiments. From the German of Prof. Ludwig Spangenberg, with a preface by S. T. Shreve, A. M.

TRANSMISSION OF POWER BY WIRE ROPES. Price, 50c. By Albert W. Stahl, U. S. N. Second edition. Revised.

TRANSMISSION OF POWER BY COMPRESSED AIR. Price, 50c. By Albert Zahner, M. E. New edition in press.

GAS-LIGHTING AND GAS-FITTING. Specifications and Rules for Gas-Piping. Price, 50c. Notes on the Advantages of Gas for Cooking and Heating, and Useful Hints to Gas Consumers. 2nd edition. Re-written and enlarged. By Wm. Paul Gerhard, C. E.

TWENTY-FIVE CENT SERIES

STUDY OF ELECTRICITY FOR BEGINNERS. Comprising the Elements of Electricity and Magnetism as applied to Dynamos, Motors, Wiring, and to all Branches of Electrical Work. By Norman Schneider. 54 illustrations and 6 tables. Price, 25c.

DRY BATTERIES. Especially adapted for Automobile, Launch and Gas Engine Work; Medical Coils, Bells, Annunciators, Burglar Alarms, Telephones, Electrical Experiments, and all purposes requiring a good battery. 30 illustrations. Price, 25c.

SMALL ELECTRIC MOTORS. How to make and use them, including design, examples of small motors and their applications, speed controllers, starters, fuses, etc. 48 illustrations. Price, 25c.

SIMPLE SCIENTIFIC EXPERIMENTS. How to perform entertaining and instructive experiments with simple home-made apparatus. 59 illustrations.

MODEL BOILER MAKING. Contains full instructions for designing and making Model Stationary, Marine and Locomotive Boilers. Fully illustrated. Price, 25c.

METAL WORKING TOOLS AND THEIR USES. A Handbook for Young Engineers and Apprentices. Shows how to use simple tools required in Metal Working and Model Making. Illustrated. 25c.

THE LOCOMOTIVE, SIMPLY EXPLAINED. A first introduction to the study of the Locomotive Engine, their Design, Construction and Erection, with a short catechism. 26 illustrations. Price, 25c.

ACETYLENE GAS, HOW TO MAKE AND USE IT. A practical handbook on the uses of Acetylene Gas, suitable apparatus for its generation, hints on fitting up, etc. 34 illustrations. Price, 25c.

JOINT WIPING. Practical hints on, for beginners in plumbing, describing in detail the various operations and fully illustrating them from actual work. Price, 25c.

WOODWORK JOINTS. How to make and where to use them. Mortise and tenon joints, lap joints, dovetail joints, glue joints, scarfing joints, circular work, with 137 illustrations. Price, 25c.

DIAGRAM OF THE CORLISS ENGINE. A large engraving giving full particulars. Explanation of figures. 13x19 in. Price, 25c.

ELECTRICAL CIRCUITS AND DIAGRAMS. Illustrated and explained. New and original drawings comprising Alarms, Annunciators, Automobiles, Bells, Dynamos, Gas Lighting, Motors, Storage Batteries, Street Railways, Telephone, Telegraph, Wireless Telegraphy. By Norman Schneider. 25c.

HOW TO INSTALL ELECTRIC BELLS, ANNUNCIATORS AND ALARMS, including Batteries, Wires and Wiring, Circuits, Bushes, Bells, Burglar Alarms, Fire Alarms, Thermostats, Annunciators, and the Location and Remedying of Troubles. By Norman Schneider. Price, 25c.

MISCELLANEOUS

ELEMENTARY FORGE PRACTICE. By John Lord Bacon, Instructor in Forge Work, Lewis Institute, Chicago. 262 pages. Cloth. Price, \$1.50. Contents: General description of forge and tools; welding, calculation of stock for bent shapes; upsetting, drawing out and bending; simple forged work; calculation of stock and making of general forging; steam hammer work; duplicate work; manufacture of iron and steel; tool-steel work; tool forging and tempering; miscellaneous work; tables.

LOCOMOTIVE OPERATION. By G. A. Henderson. 536 pages; illustrations. Cloth. Price, \$3.50. The object of this work is to give a complete and systematic discussion of the theory and practice of locomotive operation with the results accomplished and the effect of the action upon the various parts, as well as the amount of fuel and water needed to perform such needed work, rather than an exclusive treatise upon the mere manipulation of the machine. The order of contents is: Inertia, steam action, resistance, slipping, braking, steam capacity, hauling capacity, water consumption, fuel consumption.

TEXT BOOK ON ROOFS. By Mansfield Merriam. Part I. Sixth edition rewritten and enlarged. 326 pages; illustrations. Cloth. Price, \$2.50. The contents include treatises on stresses in roof trusses, highway bridge trusses, railroad bridge trusses, miscellaneous trusses, deflection and internal work, historical and critical notes.

WIRELESS TELEGRAPHY. By A. Frederick Collins. 500 pages; illustrations. Cloth. Price, \$3. Describes the history, theory and practice of wireless telegraphy in a way to rouse the enthusiasm of the layman, as well as the professional. A happy regard for details and minor points makes the whole a remarkably clear and interesting account of the Science.

MODERN ELECTRICITY. By Henry and Hora. 355 pages; 150 illustrations. Cloth. Price, \$1. Thoroughly accurate and scientific in its explanation of X-rays, wireless telegraphy, radium, transmission and distribution, power stations, wiring, and written in plain English. An essentially practical handbook for students, apprentices and electrical engineers.

ARITHMETIC SELF TAUGHT. By Spangenberg. 228 pages. Price, 55c. Undoubtedly the best book published for students of arithmetic. Do not despair because through neglect you have forgotten what you once knew about this branch of mathematics. This new method requires no teacher.

YOUNG ENGINEER'S GUIDE. New edition revised and enlarged. 254 pages; illustrations. Price, \$1. Covers the entire subject of care, management, operation, repairing, engineer's license and various points of equal importance, and is endorsed by leading engineers in all parts of the country.

HOW TO RUN ENGINES AND BOILERS. By E. P. Watson; illustrated. Price, \$1. Written in plain language and well adapted for use as a textbook by the engineer and boiler maker.

MODERN COTTAGE ARCHITECTURE. By M. B. Adams. Large quarto; 79 pages; illustrated. Cloth. Price, \$4.50. Contains an introductory essay on cottage building and notes on the subjects, illustrated from works of well known architects.

UNTECHNICAL ADDRESS ON TECHNICAL SUBJECTS. By James Douglas. 90 pages. Cloth. Price, \$1. Contents: The characteristics and conditions of the technical progress of the nineteenth century; the development of American mining and metallurgy and the equipments of a training school; wastes in mining and metallurgy.

STARRETT TOOLS



are the recognized standard for accuracy, workmanship, design and finish. Whether you use tools to earn your daily bread or for amusement and relaxation from a different vocation, it pays to use GOOD tools. You get a better quality of bread and a good deal more pleasure.



L. S. STARRETT

USE STARRETT TOOLS

We make hundreds of different tools. Ours is the largest plant in the world where nothing but fine mechanical tools are made. All these tools are fully described and illustrated in our Catalogue No. 17AP, which you may have by sending us your address. There is a good deal of valuable information in its 176 pages which it will pay anyone who uses tools to have.

THE L. S. STARRETT COMPANY
ATHOL, MASS., U. S. A.

RUBBER AS AN INVESTMENT

is sure to yield large returns. The owner of a bearing rubber orchard recently refused \$1,250.00 per acre for it. Had you been in his place you would have done the same, for it is worth more.

WE ARE PLANTING RUBBER

which in a few years will be worth the price above quoted, but which you can now purchase for less than one-fifth that amount, per acre. Is not such an investment worth while?

Meanwhile your money is not idle, but earning a larger rate of interest than your savings account. We have just paid

DIVIDENDS OF 8 %

to our investors, earned from side crops. Besides rubber, we are planting and raising sugar-cane, cassava, oranges, hogs and cattle.

Our dividends will become larger annually until rubber comes into bearing, when they will amount to 50 per cent or over.

To plant the remainder of our 5,000 acres we are offering Plantation Certificates on terms within reach of all. The proposition is absolutely safe. It is being managed by men of experience and ability. Remember, we don't want your money until you are satisfied that our proposition is genuine. Don't fail to **WRITE NOW** for our illustrated literature. It costs you nothing.

PAN-AMERICAN PLANTERS CO., 159 LaSalle St., Chicago

Ridpath's History of the World

"THE WORK OF THE CENTURY."

EVERY AMERICAN CITIZEN SHOULD KNOW HISTORY, not only the history of our own country, but the history of the whole world. In these history making days it is a positive misfortune not to have this knowledge. In no other way can we intelligently judge the events of the present except by some knowledge of the past.



President Roosevelt in his recent speech in Chicago, referred to the many republics of the past, all of which save our own have gone down on the rocks of disaster. Do you know what those rocks of disaster were? Do you know the causes of the downfall of Greece and Rome and all the other nations of the past? Can you intelligently discuss the great historical happenings of the present? In one way and in one way only can you understand the events of the past or present—by knowing history. There is one satisfying history of the whole world, just one, Ridpath's is the only one.

The Failure of Merrill & Baker, Publishers

finds us with a few sets on hand of this, their greatest publication, which we must sell to pay advertising bills, and for these few sets the **PRICE FITS YOUR PURSE**, and our terms are so easy as to bring this monumental work within the reach of all. The sets are their latest edition, down to the fall of Port Arthur, new, just from the bindery, beautifully bound in half morocco. We will sell them at

A VERY GREAT BARGAIN

Hundreds who read this have decided to buy Ridpath some day; now is the time. No need for us to tell you about Ridpath. The English-speaking world has pronounced this the only history of the world worth having.



President McKinley said, "I am familiar with the merits of Ridpath's History of the World and cordially recommend it to the scholar as well as the plain people generally." Ridpath is generally conceded to be the greatest history ever written. It is truly "the work of the century."

A RECENT SUBSCRIBER writes: "Ridpath's History received and found entirely as represented. Have read the work through twice in the past. It has a charm and interest found in no other history. I love Ridpath and consider this the most valuable set of books in my library."

Signed, H. LEE FORDING, Buffalo, N. Y.

RIDPATH is complete in nine large Royal Octavo volumes, each volume is 11 inches tall, 8 inches wide and 2 inches thick; the complete set boxed weighs 65 pounds. It contains 4000 large double column pages and 2000 splendid illustrations of the most important events in the world's history.

YOU SHOULD BUY RIDPATH NOW

- BECAUSE** it is generally conceded the Greatest History Ever Written.
- BECAUSE** it is the Only General History recognized as an authority.
- BECAUSE** you should know history in these history making days.
- BECAUSE** it is so beautifully written your children will learn to love it.
- BECAUSE** this is your chance to buy it much less than ever before.
- BECAUSE** you may pay in small sums monthly, if you prefer.

SEND COUPON for Sample Pages and we will write you fully.



Mail
Coupon
To-day.

**WESTERN
NEWSPAPER
ASSOCIATION,
204 Dearborn St.
Chicago.**

Please send me Ridpath
Sample Pages and full par-
ticulars offered in Popular
Mechanics, October.

NAME.....

ADDRESS

THIS WRENCH IS MADE
OF 50-POINT OPEN
HEARTH DROP FORGED
CARBON STEEL. JAWS
WILL TAKE 1-4 TO 3-4
INCH PIPE.

PATENTED IN UNITED STATES, CANADA, FRANCE,
GERMANY AND GREAT BRITAIN. PATENTS PENDING




No. 200 Regular
No. 400 same as No. 200 only full
Nickel Plated
The dies in wrench for English
and foreign trade, furnished with
Withworth style of thread, if
wanted.

Best Wrench Made
For Automobiles
Has More Uses Than
Any Wrench Made

This wrench should be in the tool box of every mechanic. Will be mailed on
receipt of \$1.00. Better order one today.

Manufactured by
The Hawkeye Wrench Co., Marshalltown, Ia.



ELECTRIC LIGHT Outfits

STANDARD EQUIPMENTS FOR
Residences, Yachts, Launches, Etc.
Best Material, Thoroughly Practical,
Over 130 in our 60-page catalogue.

Address ELECTRIC LIGHT DEPT.,
Richardson Engineering Co.,
HARTFORD, Conn.

If You Like "Pop." Why Not Send it to a Friend FOR ONE YEAR?

Cannot fail to please any man and
will please him for twelve months

Fill in address and mail
with One Dollar at our risk.

POPULAR MECHANICS, Journal Building, Chicago

Send your Magazine one year, commencing with the month of _____

NAME _____

STREET _____

CITY _____ STATE _____

and notify party named above that the subscription has been paid for, and is sent with the compli-
ments of _____

Please mention Popular Mechanics when writing advertisers.

The Question Is

Will You? Not Can You!

Every man can, if he will, increase his knowledge, and thereby his salary, by improving his spare time. Your pay depends on your knowledge; therefore you control your own salary. If you are getting small pay it is because you are doing a grade of work that hundreds of others can do equally well. Our instruction will fit you for a higher grade in your present line, or in an entirely different line. Big firms are eagerly searching for engineers capable of directing their vast enterprises, to whom they can pay salaries as great as \$10,000 a year. The Engineer is not the man in overalls with the oil can and waste in his hand. He is the man who designs the engine which the other man runs. He is the master mind who conceives, plans, and directs the work of hundreds of other men.

ENGINEERING

TAUGHT BY MAIL

If you cannot go to a technical school it can be brought to your door by the postman. Our students study under the direction of the same teachers who have charge of the laboratories and classes of Armour Institute of Technology, thus bringing for the first time to engineering correspondence students the standards and thoroughness of resident school instruction. *Students desiring to continue their studies and take a degree in residence will be given proper credit by Armour Institute of Technology.*

You are no different from the thousands of others who have succeeded by this means, and you can, if you will. If you will, you will write to-day for full information regarding the course needed to fit you for a position in the course marked "X." This costs you nothing; *neither will it bring an agent to annoy you for all time to come. We employ no agents. All money paid by the student is used in instructing the student.*

Tuition fees are moderate—from \$10 up—and may be paid in small monthly payments.

COUPON — CUT OUT AND MAIL TO-DAY

Please send me 200-page handbook. I am interested in the course marked "X"

- | | |
|--|---|
| Mechanical Drawing | Municipal Engineering |
| Electrical Engineering | Railroad Engineering |
| Central Station Work | Surveying |
| Electric Lighting | Hydraulics |
| Electric Railways | Structural Drafting |
| Telephone Practice | Complete Architecture |
| Mechanical Engineering | Architectural Engineering |
| Telegraphy | Contractors' and Builders' Course |
| Sheet Metal Pattern Drafting | Cotton Course |
| Machine-Shop Practice | Woolen and Worsted Goods Course |
| Heating, Ventilation, and Plumbing | Knit Goods Course |
| Stationary Engineering | College Preparatory Course |
| Marine Engineering | (fitting for entrance to engineering schools) |
| Locomotive Engineering | |
| Structural Engineering | |

Name..... Age.....

Address.....

Occupation.....

Popular Mechanics Oct. '05.

AMERICAN SCHOOL OF CORRESPONDENCE

at

Armour Institute of Technology

CHICAGO, ILL., U.S.A

MAIN BUILDING
ARMOUR INSTITUTE OF TECHNOLOGY

A STRONG ARGUMENT BUT NO PICTURES—READ IT

The Phillips Seven Powers in One

—DUPLEX GASOLINE FARM MOTOR—

Can be used on the farm for any work a farmer has to do

He doesn't have to call in his neighbors to grind his feed, cut his ensilage or fodder, neither does he have to run a **GREAT BIG 8 H. P. ENGINE** to pump water and run his cream separator that only takes $1\frac{1}{2}$ H. P.; he can't afford to do this; it takes too much gasoline.

Every farmer needs an 8 horse power engine at oftentimes and only about 2 horse power most of the time. Most farmers can't afford to put so much money in a big engine, and so limp along with a 2 or 3 horse power engine when they would really like an 8 horse power, and if they could get

A First-Class 8 H. P. That Does Not Cost Any More Than the Common 4 H. P Engine to Buy


and one that would **RUN ON AS LITTLE GASOLINE AS ANY SMALL ENGINE** when doing a small engine's work; one that the farmer could use anywhere and any place that any 2, 3, 4, 5, 6, 7 or 8 horse power engine could be used, either as a mounted engine or as a semi-portable, or a stationary, on a foundation, or as a marine engine, if desired—I say, if the farmer could get **ALL THIS IN ONE**, providing the engine was as simple and durable as the old fashioned kind, that he would then have **Just the Ideal farm power.** The **WONDERFUL PHILLIPS FARM MOTOR** is all this and more.

Let Us Tell You More About It. Write for Circular No. 23

PHILLIPS MOTOR WORKS, 415 Tacoma Bldg., CHICAGO, ILL.

Correspondence solicited regarding complete marine motor outfits; also automobile motors, transmissions, etc.

MYERS CONVERTIBLE MACHINE TOOLS



Height, over all, 14 inches; Length, exclusive of handles, 18 inches; Weight, boxed, 100 lbs.

A newly invented machine that enables a carpenter, machinist, blacksmith or any "handy man" to do, at home, practically all kinds of work that can be done in regular shops. With its numerous attachments it may be used in Forging, Drilling, Boring, Grinding, Sawing (wood or metal), Grooving, Buffing, Sand-papering, Thread-cutting and in many other ways. A tool-steel handle goes with the anvil. Has vise with 4-inch face, pipe-vise, saw-table and gauge adjusted to mitering. Our smallest size circular saw (6-inch) saws inch lumber.

Has cut gears, and may be operated by hand, foot or motor power. The 9-pound fly-wheel imparts wonderful speed and momentum. Not an ordinary, cheap "repair kit," but a real machine, made from the best of materials, and does absolutely true work. All of our attachments such as saws, emery-wheels and drills are the best standard makes. Our Machine-Tools are guaranteed both as to materials and workmanship. Big demand for them in towns and cities as well as in the country. Sold direct by the manufacturers to users at reasonable prices with liberal discounts to Manual Training Schools. Write for descriptive circular.

MYERS MANUFACTURING CO., 65 Wabash Avenue, CHICAGO

Please mention Popular Mechanics when writing Advertisers.

POPULAR MECHANICS

Vol. 7. No. 10.

CHICAGO, OCTOBER, 1905.

10 Cents a copy.
\$1.00 a year.

BURNING CARTRIDGES NOT DANGEROUS

Startling Demonstration--The Men Who Make Ammunition Fearlessly Stand Near While 68,000 Rounds Are Consumed in Fierce Fire

To prove their assertion that cartridges and shells may be consumed in roaring flames without danger to bystanders, a committee of ammunition makers stood within 20 ft. of a roaring fire in the midst of which were 68,000 rounds of the explosives. The tests lasted 30 minutes and no one was hurt.

This startling exhibition was made before the convention of the International Association of Fire Engineers, at Duluth, to prove the claim that firemen need not hesitate to come within working distance of a burning building containing cartridges and shells.

The demonstration was on account of the contemplated increase in insurance rates on buildings containing ammunition, such as

hardware stores, etc. Previous to the fire, the following statement was made:

"Ammunition in a fire does not explode simultaneously. We make this statement advisedly and emphatically after many years' experience. Gunpowder in bulk, that is to say, in kegs, will explode with force. One keg exploding may tear open the adjacent kegs and the flash of fire from the first communicate to the second, and that in turn to the next, with such rapidity that the explosion is practically simultaneous. At first thought there would appear to be no reason why ammunition should not act in the same way, but as a matter of fact, it does not. An exploding cartridge has not sufficient force to tear open the adjacent



Firemen Extinguishing the Fire at a Distance of 20 Feet During Rapid Discharge of Cartridges

cartridge and therefore cannot communicate fire to the powder charge of its neighbor. Each cartridge in the fire explodes individually, and explodes when its particular primer is heated to the flashing point, but the flash from this cartridge cannot set off the adjacent cartridge. Consequently, instead of having a simultaneous explosion, we have a series of explosions of the individual cartridges, and when there is a large quantity of ammunition burning these explosions follow in rapid succession, sounding like rapid musketry fire.

"The danger from flying fragments of exploding cartridges is by no means a serious matter. The cartridge shell unsupported by the gun chamber readily bursts at the first indication of pressure, and this allows the gases to escape at a low pressure. The escaping gas expends its energy in tearing open the shell rather than in throwing the bullet, and as there is nothing to restrict the escaping gas, it has but little propulsive force. Frequently the heads of the cartridges are torn off and thrown some little distance, but the bullets scarcely ever fly. In other words, the heavier parts of the cartridge remain behind and only the lighter parts are thrown out, and they are thrown with no force or velocity; in fact, a fireman may keep well beyond the range of fragments thrown from the fire and still be easily within working distance and as close as the heat of the fire would permit."

The Western Fireman, whose editor was a close witness, states that for the test a frame building was constructed, in which was placed 68,000 rounds of ammunition. The cartridges ranged from 22 calibre to 50-110 high velocity kind. Also shot shells loaded with black and smokeless powder, and rifle and pistol cartridges of various kinds. The house was made as combustible as possible with a chimney on the roof extending 6 ft. above. The building was then filled with excelsior and fine dry wood and set on fire, and to insure a hot, rapid fire, 5 gallons of kerosene was poured on the mass. The ammunition had been unpacked from the wooden shipping cases and remained in pasteboard boxes, just as it is displayed in a store.

At the end of twenty minutes half the ammunition was destroyed, and the firemen tore some boards from the side of the house and put out the fire. The test proved all the ammunition makers claimed. Several persons who approached within twenty feet of the fire were struck by flying fragments of cartridges, but in no case was the velocity

of the pieces sufficient to cause discomfort. In other words the bursting of the cartridges was not unlike the popping open of corn or chestnuts when heated.

The exhibition was conducted by the Winchester Repeating Arms Company, the Union Metallic Cartridge Company, the United States Cartridge Company, and the Peters Cartridge Company.

AUTO TRACK RACING TO CEASE

Indications are that the auto track racing will be abandoned, in this country at least, so far as the better class of people are concerned. One fatality after another of enthusiastic auto men has brought about the result.

Ex-Chairman Temple, of the American Automobile Association, states the case concisely as follows: "I don't believe in the racing game anyway. I can see no utility in it. It does not demonstrate anything of value to the true automobile sport



Motor Age

"Toying With Death"

or to the industry. The mere matter of speed does not need demonstration in that way. Every one knows that automobiles can be built to run faster than they can be driven with safety, so what is the use of such contests."

This sentiment finds echo from prominent auto club men all over the country and will doubtless result in action.


AUTOMOBILE COMBINATION CHEMICAL FIRE ENGINE AND HOSE WAGON

A new invention in the line of fire protection apparatus is a combination chemical fire engine and hose wagon using steam for its motive power and always ready to start at the sound of the alarm, merely upon the motorman mounting to his seat and opening first the fuel valve and then the steam throttle.

The combination wagon is built with an

diameter with 4 in. solid rubber tires, provided with bolt head and protecting flanges.

The machine is very strong, capable of maintaining uniform speed on long runs, can be stopped quickly and is declared to be cheaper, all items considered, than the horse-drawn combinations. New London, Conn., is the first city to install one of these machines.



"Always Ready to Start"

iron body on a channel steel frame and the body is mounted on four elliptic springs. The wheels are small and rubber-tired. The machine has capacity for 1,000 ft. of $2\frac{1}{2}$ in. cotton rubber-lined hose, has a 35-gal. chemical cylinder on each side fully fitted up, and the equipment throughout is large and complete.

The fire-tube design of boiler is used, because of its great reserve power, useful in climbing hills or traveling over rough roads. When the apparatus is in motion on the street, gasoline is the fuel used, and at the engine house steam pressure is maintained by a gas burner. The gasoline burner is built entirely of steel and is controlled by regulators. Two engines, working independently, are connected, one to each rear wheel, for driving the machine. These engines are of the double-cylinder type, high-speed and double-acting.

The running gear has an 8-ft. base and 56-in. tread. The wheels are 36 in. in

CLAY PRODUCTS A GREAT INDUSTRY

There are in this country 6,069 concerns engaged in converting clay into manufactured products; the average output for a year being \$21,589; the total value amounting to \$131,000,000 for twelve months. Of this the greater part was brick and tile, valued at \$195,000,000. The leading producing states in their order are, Ohio, Pennsylvania, New Jersey, Illinois and New York. Ohio shows a record of over \$25,000,000.

The average price throughout all the states was for common brick, of which 8,665,000 thousands were made, \$5.97 per M.; paving brick sold for an average of \$10.28.

Sand-lime bricks now seem to be considered a success; 57 plants earned \$463,000. The rapid increase in the use of cement blocks is likely to reduce the volume of clay products, or at least to curtail their previous yearly increase.

FREIGHT AND PASSENGER COLLISION

The effect of a head-on collision which recently occurred on the Nickel Plate road, near Cleveland, is vividly portrayed in the illustrations. Twelve persons were killed and many more injured; the greatest harm



Telescoped

was done to those in the smoker which was telescoped. A fast passenger train running 50 miles an hour ran into a freight train which was standing still. Failure of the freight crew to obey orders and further neglect in flagging the flier caused the accident. Engineer Poole of the passenger re-


fused to jump, was caught in the wreck and slowly scalded to death before the eyes of a helpless crowd.

TRANSPORTATION OF BANANAS

One company alone imported 26,000,000 bunches of bananas in a single year, requiring 72 steamers. The transportation of the fruit is peculiar; it must not get too warm or it decays, nor too cold or it will never ripen, it being always shipped green. The latest improvement is the erection of cooling sheds, into which an entire train is run at one time, and cold air is pumped into the tops of the cars, thus reducing the temperature to exactly the degree desired. In winter warm air will be used. The blower has a capacity of 50,000 cu. ft. per minute, and an electric alarm in each car rings a gong when the proper temperature is reached.—Condensed from Ice and Refrigeration, Chicago.


SECRET TELEPHONE EXCHANGE

An electrical expert has invented and put in practical operation, a telephone exchange in which the hello girl cannot listen to the conversation. The next encroachment on official perquisites will be a postal card which cannot be read en route. The system of switchboard wiring by which this is accomplished is said not to be specially complicated.



"The Passenger Train Was Running 50 Miles An Hour"

FAN-DRIVEN ICE VEHICLE



The "Aëro-Motor"—An English Ice Craft that Will be Tested During the Coming Winter

Motor ice yachts and ice vehicles of all types will, beyond doubt, create great interest during the coming winter. Among the many machines which will be tested is an English device called an "aëro-motor," and will utilize an idea tried in this country several years ago—that of propelling the sledge by means of a revolving fan or screw.

The fan used in the English machine is four-bladed, is driven by a gasoline engine and may be attached to either a motor-car or to a sled. The inventor, J. Bruce MacDuff, expects great things of his machine and suggests that the aëro-motor sleigh may supplant dogs for use in Arctic and Antarctic explorations.

SUPERINTENDENTS SHOULD SUPERINTEND

It is of the highest value to have a superintendent who possesses the practical knowledge and experience to do any piece of work which comes into his shop. To have him take off his coat and do the work except in the case of some unusual thing where he does so to show his men how, is not considered advisable.

In a paper read before an association of foremen the superintendent of motive power of the C. & N. W. Ry. says:

"You men have no business to have your coats off when on duty in your shops unless you are warm. You have no business to take the tools out of a workman's hands

to do his work. Your business is to secure results from the other men's work. If I find that a foreman boiler maker on my road is doing the work that his men ought to do I begin to think that he had better keep using the hammer and chisel."

Ability to do things is all right; the doing of them is another matter. Proprietors make a mistake when they allow or expect a superintendent to work with his hands when he ought to be working with his head. It's an extraordinary man who can do both successfully at the same time, and such men do not remain superintendents very long.

GRANITE COLUMNS WITH STEEL CENTERS

Unique Combination of a San Francisco Architect

The Merchants Exchange new building in San Francisco possesses a remarkable feature, which so far as we can learn is the first of its kind. The massive granite pillars which support the great building are hollow and contain solid steel columns.



Steel-Centered Granite Columns 40 Feet High

This building is fourteen stories high; the two lower stories are of granite and the other twelve of very handsome pressed brick. On each side of the main entrance are two enormous fluted granite pillars. At the base each pillar is 6 ft. in diameter; they taper slightly and are 5 ft. across at the top; each being 40 ft. high.

Before the massive and shapely columns were put in position, when the great building had reached the first story, both the contractors and architect concluded that they should be strengthened in some manner. Massive though the granite pillars would be, yet the weight they were required to support was enormous.

To increase the strength it was determined to build the pillars in short sections and to bore out a hole in each section 16 in. in diameter. This long hole of 40 ft. was to contain a solid steel column 16 in. in diameter. It proved a slow, tedious, and painstaking task to cut a hole through the blocks of granite. This was accomplished

by means of a circular saw, the core being "trepanned."

The cutting was done with the utmost precision; so very accurate that the sections fitted together with the utmost nicety, the flutings being perfect. As each section was bored out it was lifted by a derrick and fitted over the steel column. Whatever little space was left between the steel pillar and its granite casement was filled with liquid cement. This, hardening, made one solid mass.

The two columns were then placed in position, and the building proceeded. Each pillar contains 13 sections, the joints being united with cement.

That the building has sufficient support is not denied, though some architects question the utility of the plan, claiming that it is extremely difficult to divide the load between steel and granite, the resistance of the two not being equal. "One or the other is really carrying the load," says a prominent Chicago architect, "although the steel center undeniably holds the circular stone sections that compose the pillar in place."

ARMY MOTOR WAGONS WITH WOODEN WHEELS

Built strictly for business and with no consideration for the comfort of the passengers is true of the new army motor wagons built for France. However, they carry great loads at a speed of 15 miles an hour on good roads, and are guaranteed not to stampede under fire. The latest type have wooden



Army Motor Wagon

wheels with immense spokes and wide steel tires, which meet the approval of military men as safer than any form of rubber tires. The Motor Age says the steel tired wheels proved good hill climbers even in the mud.

ZIRCONIUM, NEW FILAMENT

A new filament for incandescent lamps is produced by submitting oxides of a material called zirconium and magnesium at a high temperature to the action of hydrogen, then pulverizing the resultant alloy and adding a cellulose solution which transforms it into a plastic and homogeneous mass. From this mass the filaments are drawn, 50,000 to the pound of raw material. The zirconium lamps require current of only 37 volts and three lamps can be placed in series across the usual 110-volt circuit. Several filaments in one bulb are used for high candle power lamps.

MAPS OF RIVER BEDS

The foundations for a great bridge or dam are important essentials, which, like the engineers and firemen on a ship are not seen and seldom appreciated. Before the stately structure can span the chasm or stream the foundations must be laid deep,



Boats for Drilling

and sure, and lasting. There's a lesson here for every young man, but we are writing about dams and things—not preaching.


Weeks and months, sometimes even years, must be spent in studying the sand or rock beneath the water. Recently the government had occasion to learn the exact condition of the river bed of the Ohio for a mile and a half, near Parkersburg, W. Va. Scores of borings were made, each one furnishing its "core" from which exact maps were made showing exactly the character of the river bottom, and of the rock beneath to a considerable depth.

The illustration, from the Gas Engineer, shows the boats used in the sounding, the drills being let down into the water from the sides of the boats, and operated by gas engines.

CEMENT BLOCK CIRCULAR SILO

The latest in the silo line is the handsome structure shown in the illustration. The following details are condensed from Hoard's Dairyman:


The silo is 29 ft. in height and 16 ft. in



Cement Silo

diameter and is figured to hold 115 tons. Its cost is \$360. It is constructed of hollow cement blocks molded to the desired curve. The form and method of tying the blocks together so as to resist the lateral pressure, is shown in another cut.


So far as we can judge, this is, in many respects, a model silo. If it proves to be all the designer and owner of it anticipate, under the test of time, it solves the problem of a cheap, safe and indestructible silo. The cost per ton of storage capacity is certainly reasonable. The device for strengthening the blocks appears to be sufficient. When laid up the notches in the ends of the blocks are filled with soft cement, which helps materially to make the wall strong.




End View of Cement Blocks, Showing the Curve and Method of Applying the Iron Fasteners

CANAL BOATS WITH LOADS ELEVATED 75 FEET

Unique English Elevator Saves 12 Locks--
Very Cheap to Operate



Power House



Lower Level Canal, Showing Lifting Cradles

An apparatus has been constructed at Foxton, England, which transports boats of all sorts from one canal to another seventy-five feet higher, without the use of locks, twelve of which would be required to raise a boat that distance.

Two docks with reservoirs of water are placed at the edge of the canals, one at the foot and the other at the top of an incline. Upon this slope are laid two tracks, each track composed of four rails. On these travel two cars for transporting the boats, one mounting while the other descends, being drawn by steel cables which run in conduits. The cars are, in fact, immense movable tubs formed of steel plates, well braced, and mounted upon sixteen pairs of strong wheels each. At either end of these traveling docks are sluice gates moved by hydraulic pressure. The power plant is installed at the top of the incline which is built of solid masonry.

When a boat is ready to be transferred the car is submerged, one of the sluice gates at its end is opened and the boat sails into the metal dock with all its freight and

appurtenances just as it floated in the canal. The gates are then closed and the boat is ready for its journey on the rails. When the other movable dock has been loaded in the same way one huge tub with its floating load is drawn up while the other carrying the second boat descends, thus, the weights being equalized, the cost of transferring the two boats is no more than to handle one alone. In order to launch the boats it is only necessary to open the sluice gates after the car has been again submerged, when they float out into the canal and resume their voyage. The whole operation, as previously mentioned, takes only 15 minutes.

The cost of operating this plant is quite insignificant. The boats are small, but the traffic has averaged a total of 6,000 tons handled each 12 hours; this cost only \$6.40 for labor, fuel, oil and repairs. These traveling docks will accommodate canal boats up to 53 tons.


From 190 to 200 boats of that class was a fair average number during 12 hours without crowding, not counting canoes.

motor-yachts and pleasure boats of all sorts which were transported during the same period.

To what extent it might be possible or practicable to enlarge the Foxton method is not yet known. If it could be adapted to large work such as the transport of great ocean vessels or a battleship, it would mean the saving of several years in time and a great many million dollars in money in the

concerned, in a few minutes more than eleven hours, and it is not beyond possibilities that 100 miles an hour may be achieved. When this is done a man could leave New York at 9 o'clock in the morning, go to Chicago, spend an hour there, and be back in New York at 6 o'clock the next morning.

Many experts anticipate a return to the longitudinal system of track support, which will doubtless be in the form of a great



Upper Level Canal--Boats Proceeding on Journey

completion of the Panama canal. The question of levels and locks would then cut no particular figure, as there could be several levels, thus saving a vast amount of cutting and excavating.

RAILROAD TRACK OF THE FUTURE

Increase of speed in the movement of passenger and freight trains seems to come in cycles of a few years each. It is not so many years ago that 29 hours were required to cover the 1,000 miles between Chicago and New York. Then the time was reduced to 24 hours, next to 20 hours and finally to 18 hours. When the electric motor replaces the steam locomotive for passenger trains this time will again be considerably reduced, but in all probability not until a radical change is made in track construction.

The high speed track of the future will be laid on longitudinal supports, instead of cross ties, and the foundation will be much deeper and more solid than is possible with wooden cross ties.

The New York Central is to have an electric locomotive of 2,200 h. p. which will be capable of hauling a heavy passenger train at 90 miles an hour. As it would have no occasion to stop for fuel or water, and seldom for other reasons, it will be seen that a road electrically equipped between Chicago and New York could make the run, so far as motive power is

beam of concrete which in turn will rest upon a support more solid than dirt.

In the early days of railroads in England, Germany, and even this country, the longitudinal system was employed, though by no means as substantial as is required with the mammoth locomotives and heavy sleeping cars of today. The increasing scarcity of wood for ties will also contribute toward a radical change in track construction.

The Engineering News, a railroad authority, says: "An engineer would never design an important building and support it on wooden blocks bedded a few inches below the ground surface; and he would not consider the case much better if stone or concrete blocks were substituted for wooden. To make a permanent support for railway track we must carry our foundation course down deeper, just as we would a building foundation. But it is practically impossible with the cross-tie system to make the foundation much deeper than the thickness of the present wooden ties, for the trackmen could not reach under the ties to tamp them if the ties were, say, 12 to 16 inches in depth. There is not room enough between the ties to permit this; and it is, of course, out of the question to space the ties farther apart. All this points directly to the replacement of cross-ties with longitudinals whenever a really permanent system of track foundations replaces the present 'mud-sill' system."

THREE ACRES OF ROCK BLOWN UP

**Henderson's Point, Piscataqua River, Demolished by Forty Tons of Dynamite--
Clearing the Channel to the Portsmouth Navy Yard**

A short time ago Henderson's Point was a big ledge of rock jutting out into the Piscataqua river and forming a sharp turn in the swift current, so that none of the larger warships could pass up the channel to the new dry-dock at Kittery, Maine. Today Henderson's Point lies a great mass of loose debris, which is being rapidly removed by powerful dredges. Forty tons of 75 per cent dynamite were used to reduce the 35,000 cubic yards of rock forming Hender-

below the Point a submarine drilling boat was used for drilling holes where the shallow water began. The rock was blasted off into deep water and left for the time being. After three months' work, scows were substituted for the boat, and in all 800 cubic yards of rock were removed in this way.

The center of the Point removed, the work of putting in long holes for the big charge was begun. These holes were run from the edge of the "rim" at intervals of



Battery of Air Drills Inside Cofferdam

son's Point to this condition and the entire project will cost the United States government \$750,000. Since, in 1885, Hell Gate channel, East river, New York, was cleared of its dangerous rocks, there has been no blast to compare with this one. The Hell Gate blast, however, extended over an area of nine acres, and to break up the 270,000 cubic yards of rocks, 120 tons of "rend-rock" powder and 20 tons of dynamite were used.

The difficulties attending the destruction of Henderson's Point were great. The use of a coffer-dam had been intended, most of the work to be in the open and proceeding from the channel toward the shore, but the swift current wrecked the strong coffer-dam constructed and then one was built on top of the "rim."

The core was first excavated and just

6 to 10 ft. and at a dip from horizontal of $1\frac{1}{4}$ in. to the foot. The holes were from 50 to 80 ft. deep. Eight drills, having cylinders $5\frac{1}{2}$ in. in diameter by 8-in. stroke, were used. The use of tripods or columns for mounting them was impossible under the conditions. Instead they were bolted to a heavy timber framework which was loaded down with stone. A series of holes were bored and the framework moved along. The holes at the start were 5 in. in diameter and tapered to 2 in., and the shortest time required for drilling one of them was 12 hours. The drills were operated by compressed air.

The great explosion caused no injury to persons or damage to property, beyond a few broken window panes, though water and debris were thrown to a height of 100 ft.

HOW AN AUTOMATIC SPRINKLER WORKS

Inactive for Years, Perhaps, It Springs Into Action When Needed

We have had several requests for a description of the automatic sprinkler—a device which will remain inactive for months and years at a time, and then in an instant when fire breaks out in some remote room, drenches the compartment with water and subdues, even if it may not entirely extinguish the fire. Many a time a fire has been extinguished at the start, which if unchecked for a few minutes would have grown into a terrible conflagration.

The system is in reality a very simple affair, consisting of a big tank of water placed higher than the building, connected to parallel pipes extending along the ceiling of each room. These pipes are ordinarily 8 or 10 ft. apart, while at intervals of 10 ft. a sprinkler is attached to the pipe. By this arrangement at least one sprinkler is placed over each floor space of 8 x 10 ft.

The sprinkler itself consists of a metal frame with two bronze levers holding a bronze cap over the opening in the pipe. These levers are connected by a small link of solder, designed to melt at a temperature of 165 deg. As soon as a fire starts the hot gases and smoke rise to the ceiling, melt the solder, the levers are released and drop, there is no longer anything to hold the cap in place, it flies out, forced by the pressure of the water, and the sprinkler is busy. In order to spread the stream in all directions and divide it into large drops, a deflector is provided at the top of the frame. All these working parts will be clearly understood from the illustration (Fig. 1). The water will continue to run until some one shuts off the supply or the tank runs dry.

There are two sprinkler systems—the wet, in which the pipes are constantly filled with water; and the dry, in which there is no water in the pipes except when one or more sprinklers open. In the dry system





Fig. 1--Sprinkler Head


the pipes are filled with air compressed to about 30 lbs., which holds back a valve placed in the large water main leading from the tank.

Sprinklers are made to act at different temperatures as desired, from 165 deg. up to



Other Types of Sprinkler Heads

360 deg. This is accomplished by using links of various degrees of hardness. Each fuse link bears the date when it was put in, and its melting temperature.



Sprinkler in Action

Modifications of the above system include underground cisterns, instead of elevated tanks, or connection to city mains, in which case automatic pumps are required which start pumping the instant a sprinkler opens. A sprinkler system is quite expensive to install, but secures reduced insurance charges.

POMPEII'S WATERWORKS

A most complete system of water works, says Professor Kelsey, Ann Arbor, Mich., has recently been unearthed in Pompeii. This system has been so well preserved that even at the present day it is possible to turn water on and it will flow through the pipes as freely as when that city was in the height of its prosperity over 1,800 years ago.

A LAMPLESS LIGHTHOUSE


A lighthouse that has neither lamp nor keeper, yet throws out a light at night that may be seen far and wide upon the surrounding water, is located at Arnish Rock, Stornoway Bay, in the Hebrides, Scotland.

It is a conical beacon with a lantern, which has a mirror and an arrangement of prisms, fixed at its summit. Across the channel, 500 ft. away, on Lewis island, stands a lighthouse which throws a stream of light on the mirror in the lantern, which in turn reflects it on the prisms. The rays of light are converged to a focus outside the lantern and then diverge in every direction, making a serviceable lighthouse, fully adapted to the requirements of its locality.

OBSERVATION STREET CAR

What is doubtless the finest observation street car in the world has just been built for the Montreal street railway. It makes daily trips, taking visitors over all the car lines in that extremely interesting city.

The car is 46 ft. long, 8 ft. wide, and the seats, which will accommodate 50 passengers, are in tiers one above another, hence every seat commands an equally good view. The car is open, with nothing to obstruct the view. At night it is brilliantly illuminated. The conductor acts as guide, pointing out and describing the points of interest. The car has a speed of 40 miles an hour, is driven by four large motors and is equipped with air brakes. The trolley pole is carried by a post at the rear of the car.



Observation Street Car, Montreal

LARGEST MARINE BOILERS EVER BUILT FOR GREAT LAKES

Special Track Built for Loading them on Vessel for Shipment



Courtesy Marine Boiler Works

"The Boilers are Each 15 Ft. in Diameter"

The largest marine boilers ever built for use on the Great Lakes were recently shipped from Toledo, Ohio, to Detroit, Mich., where they will be installed on a new vessel being built there. To facilitate loading the big boilers on the boat for shipment necessitated building a special track out along the pier.

The boilers are each 15 ft. in diameter by 12 ft. long and contain three corrugated furnaces 44 in. interior diameter by 9 ft. 4 in. long and contain 368 three-inch tubes 8 ft. 9 in. long. They have 32 through bolts ($2\frac{7}{8}$ in.) with nuts inside and outside. The shells of the boilers are $1\frac{3}{8}$ in. thick (the

heaviest ever put in marine boilers, it is said), and are riveted with $1\frac{3}{8}$ -in. rivets, driven with 150 tons hydraulic pressure. The tube sheet is $\frac{3}{4}$ in. thick, the external parts $\frac{3}{8}$ in. and the furnaces 23-32 in. thick. The flanges for steam pipe and safety valve are of cast steel; the butt straps are 1 in. thick. The rolling of the steel plates for the shell was a great undertaking and it was necessary to substitute steel gears for the ordinary cast iron gear wheels on the machine.

The boilers were tested to 315 lb. hydrostatic pressure, which gives them a safe working pressure of 210 lb. of steam.

ENGLISH OPINION OF AMERICAN BOILER INSPECTION

After referring to the widely differing and somewhat conflicting laws of the several states in the matter of boiler inspection, the Electrical Review, London, says:

"In the city of New York the police do the boiler inspection. A few helmeted desperadoes drive up in a van with a force pump, seize an unfortunate boiler, put a trifle more water into it than it will fairly hold, and leave it stretched and weakened with a quite unwarranted certificate that,


being reduced in strength by the test put upon it, it is now safe to work until next assault and battery. No one but a born fool would put a boiler to such a casually applied hydraulic test with any expectation of securing safety or proving a fault, though such casual tests do greatly help incipient faults to develop and prove themselves afterwards under steam pressure half that used in the hydraulic test."

Conditions are different in England.

LOCOMOTIVE LOST IN A JUNGLE

One would naturally think a locomotive was the last thing in the world to be discovered lost and abandoned in a tropical jungle. But such is the fact, and at this moment what was once a fine machine in

has cooled a little, the oil, in suitable quantity for the kind of varnish being made, is added gradually to the gum, stirring constantly. The mass is then cooked, the grade and character required in the product determining the degree of heat and the time of boiling. Much cooking makes a dark var-



"How it Came to Be There is a Mystery"

its day, is rusting away far from the habitation of any human being. It was recently discovered in the woods in Columbia, South America. How it came to be there is a mystery; no tracks lead to its present location; it's a railroad derelict. Tropical vines creep through the spokes of the driving wheels and twine around the throttle lever. Its headlight has vanished, and forsaken and deserted it is a monument to its own death. The Boiler Maker says the name plate shows the engine was built in the United States in 1878.

HOW VARNISH IS MADE

In brief, the making of varnish seems like a simple matter indeed, yet it takes one of experience to obtain always the exact results and a dependable product.

A brass kettle having capacity for 125 lb. of gum and provided with a cover having a hole through which a stirring rod is operated, is filled and put in the fire for the gum to melt, which requires about one-half hour. From 10 to 25 per cent of the gum is lost in the escaping vapors.

In another copper kettle linseed oil is heated in the meantime, and when the gum

nish and less a paler varnish, generally preferred. However a dark varnish made of the best gum, but not darkened by overcooking, wears better than the paler product, says the Master Painter.

A ton of gum must be sorted over to obtain enough light gum for a 125-lb. melting, where light-colored varnish is desired. This makes it very expensive. When the mass has cooled after cooking, it is thinned with turpentine, great precautions against fire being necessary. The varnish is graded according to the amount of oil added to it, which ranges from one to sixty gallons per 100 lb. of gum.

Westrumite, a German product named for a Herr Westrum who invented it, is being tested in this country as a dust eradicator. It is said that a road thoroughly saturated with Westrumite will not require sprinkling for eight or nine days thereafter. The fluid is as cheap as water, and when first tried in Germany, a year ago, consular reports spoke highly of it.


Congress will be asked to change the plans of two new battleships from 16,000 to 18,000-ton ships.

RECOVERING A SUBMERGED ISLAND

**18 Billion Gallons Pumped from an Area of 7,000 Acres--Average Depth 6 Ft.--
Steamboat Furnishes Part of the Power**

One of the most stupendous pieces of pumping ever undertaken in the United States was very recently accomplished in California. This work was done in San Joaquin county, on Bouldin island. The island in question is formed by the junction of the San Joaquin and Mokelumne rivers, and contains an area of more than 7,000 acres. A large extent of this island is under cultivation, being used for raising asparagus. In fact, this island contains what is undoubtedly the largest asparagus farm in the world.


Bouldin Island is of irregular shape, and at a mean stage of water lies about 8 ft. below the level of the streams surrounding it. Many years ago a huge dike was built, following all around the zig-zaggy shoreline of the island, some 30 miles long. During a heavy freshet a break occurred in this



Closing the Break


dike, small at first, but rapidly enlarging. In a very short time the break increased until 1,500 ft. of embankment was swept away.

Through this great breach the floods poured furiously and in a short time submerged the entire island. On an average the water stood 7 ft. deep all over the 7,000



Pumping Plant--Submerged Land Beginning to Appear

acres. After the subsidence of the floods the first work to do was the repair of the breach. This proved a very difficult and



A 44-in. Pump

expensive task. Finally, after months of work, it was closed up and the inrush of waters shut out. To accomplish this it was necessary to sink the condemned hulk of a sailing vessel 250 ft. long, then piling and vast masses of rock were added. When this heavy work was done, the company owning the island was confronted with the colossal task of pumping out a great lake.

A large pumping plant was installed at the point where the break occurred. The boiler capacity of 1,000 hp. was found to be insufficient, and was supplemented by 500 hp. additional in the steamer "City of Stockton," shown in the illustration. She was made fast to the dike and steam pipe lines with ball joints run ashore from her four 54 in. x 18 ft. boilers.

The capacity of the four pumps was 165,000 gal. per min., equivalent to 10,000,000 gal. per hour. During the time of pumping no less than 6 in. of rain fell on the island,


which increased the duty to be performed about 1,200,000,000 gal. additional, making the total water pumped 18,200,000,000 gal.

Two 44-in. and two 36-in. centrifugal pumps were installed. The capacity of each of the 44-in. pumps was 60,000 gal. per minute; of the 36-in., 35,000 gal. per minute. These pumps were installed upon the syphon plan, being the first attempt at this class of installation on such large pumps ever attempted upon the coast. The plant was a success in every particular and the water was entirely removed from the island within a period of five months. All four pumps were operated continuously for about 60 days, after which time the pumps operated intermittently, as best served the owners. The oil consumption ranged from 60 to 100 barrels per day of 24 hours, and 2,500 barrels of oil were used in draining the island. Every 24 hours 240,000,000 gallons were thrown out. The pumping was started March 8 of the present year and completed in August.

Now that the pumping is over, it is estimated that the cost of putting the ground again into suitable condition for asparagus will reach another \$200,000. It is very probable that the total direct cost of the submergence of Bouldin island will approximate \$500,000.

At the present time there are 20,000 sheep on the island and 3,000 Japanese gardeners. A full crop of asparagus is expected next season.

It is said it will require 1,500,000 freight cars, or a train 12,286 miles long, to haul the grain crop to market this year.



Steamboat Supplying 500 Boiler Horsepower

CAUSE OF "BENNINGTON" ACCIDENT

The naval investigation of the "Bennington" accident finds it was caused by a careless fireman shutting off the steam gauge connection instead of an air cock as he supposed. The boilers were freely fired, but no pressure showed on the gauge. The safety valves stuck. Any 12-year-old boy who has read Popular Mechanics six months should have shown more discretion than the men who blew up the "Bennington."

STEAMER WRECKS STREET CAR

A peculiar street car accident occurred in Milwaukee not long since when a steamer collided with the north end of a bridge, just as the car was leaving the south end. When the steamer struck the bridge, it tore it open at that end, making a corresponding gap of 35 ft. at the other end, across which hung the street car with its load of terrified passengers. All escaped unhurt, however. Two of the huge bridge spans were wrenched loose and fell on the car. The bridge was damaged considerably and it required several hours to clear away the debris and rescue the car from its precarious position. A scow piled high with railroad ties was backed under the bridge and a cribwork of ties built up to raise that end of the car, which was then hauled off.

REINFORCED CONCRETE SEWER PIPE

Reinforced concrete sewer pipe can now be made in diameter from 15 in. to 10 ft. Not only that, but they possess a remarkable strength. The illustration, from Municipal Engineering, shows a section 3 ft. in diameter supporting a load of 20,000 lbs.,



and the pipe 90 days old. Railroads are now using these pipes for waterways under tracks in place of the more expensive iron pipes. Joints are made with iron bands drawn tight, the coupling filled with cement.



Unusual Accident--Ship Wrecks Street Car


NOTABLE WHARF IN MEXICO

A notable example of wharf engineering has been completed after several years construction at Tampico, Mexico. The structure is near the bank near the mouth of the Panuco river, the water being 30 ft. deep on the river side. The construction had to be not only fire proof above the water line, but calculated to resist the equally destructive ravages of the warm salt water below.

The entire wharf is 2,600 ft. long with

SMALLEST NAVIES IN THE WORLD

Several recognized nations have "navies" which are simply ridiculous. For instance, Panama has one converted yacht; Belgium has one training ship; Peru has a weather-beaten tramp steamer of 600 tons; and Roumania's navy consists of a 1,300-ton cruiser, a small training ship and 8 torpedo boats. In comparison with our "big stick" the above would rate as little more than slivers.



Courtesy Ry. Review

Constructing the Piers, Tampico, Mexico

tracks of the Mexican Central extending the entire length. One-half inch steel cylinders 6 ft. diameter and 55 ft. long, placed about 20 ft. apart, support the wharf. The cylinders were sunk to the sand which is covered by 30 ft. of mud. Creosoted piles of long leaf yellow pine were driven inside the cylinders and the remaining space filled with concrete.

Extensive freight houses were erected on the wharf with electrical machinery for exchanging freight between the cars and ocean-going vessels. The above facts are condensed from a detailed description in the Railway Review.

An International Fire Congress to which fire and insurance men are invited will be held in Milan, Italy, in May, 1906. In Europe as much attention is given to preventing fires, as Americans display in extinguishing them.

The largest public bath in Europe is located at Vienna. It is 587 ft. long, 156 ft. wide and accommodates 1,500 people. It is patronized by thousands of the poor.

1906 STYLE AUTO

Some of the new styles of autos which will be brought out next year will lose much of the accustomed resemblance to a motor car and will easily pass for a horse-drawn vehicle. The running side board is omitted and the rear seat is higher than the



Phaeton Auto for 1906

other. The room required for machinery is greatly reduced and the lines throughout are much more graceful. The style illustrated will be known as the phaeton auto.

THE ARMOR-PIERCING POWER OF THE CAPPED PROJECTILE

The strongest, hardest armor plate manufactured today, the product of long years of experiment, study and experience devoted to the question at such steel works as the Krupp, Harvey and Creusot, is not proof against that marvel of penetrative ability—the capped projectile. In 1854 the French sent floating batteries sheathed with $4\frac{3}{4}$ in. laminated iron to the Black Sea and these were able to resist the fire of the 68-pounders in use at that time; a few years later the "Merrimac," newly clad in iron, sailed out

to fit it to the projectile is by metallic soldering and with this method, caps can be fitted to old projectiles on hand. Another method, used only with new projectiles, is to screw the cap on the head. Whichever the case, the cap must be securely attached.

Why this mass of material at its head should give to the projectile the extraordinary efficiency that it does is a subject of much theorizing. Certain it is, however, that in tests, a capped ball, moving at a velocity of 2,500 ft. per second, pierced an 8-in.



Armour-Piercing Shot
(6-in) After Pen-
etrating Plate



Capped 6-in. Shot



Penetrated 9-in. Plate
Twice and was not
Injured

of the Mississippi to uphold the Confederate cause, and to demonstrate the use of the armor-protected war vessel to be practical. Then, indeed, began the competition for supremacy between armor plate and armor-piercing shell, now one, now the other claiming the advantage; striving onward through a period of 40 years unto the present day in which the capped projectile holds the point. Supremacy in this age, however, is as transitory as life, for now, more than ever before, in a material sense, man is "restrained from no thing that he hath imagined," and the great steel manufacturers are still imagining plates that no shell can pierce.

The cap which is used on the projectile is made of soft steel filled with graphite (though there is a freedom of choice in the matter) is of various shapes and for a 4.7 in. shell weighs about 3.3 lb. The best way

Krupp plate that had successfully resisted an uncapped shell striking it with a velocity of 2,300 ft.; that $15\frac{1}{2}$ -in plate was pierced by a 10-in shell with a clean round perforation, only made ragged by flowing metal at its edges; and that other tests beyond number have proved it.

Eugen Kodar v. Thurnwerth in an article in the *Marine-Artillerie-Ingenieur* (translated for the *Journal of the United States Artillery* by Captain George Blakely) summarizes the noteworthy theories in regard to the action of the capped projectile and refutes a number of them, adducing his own.

Some claim that the cap melts and forms a lubricant for the projectile in its passage through the plate and so reduces the amount of friction resulting. But this could only be true in soft plates where the head and body of the projectile come in sliding contact with the plate, whereas the superiority


of the capped projectile over the uncapped only obtains in the case of hard plates. Also the amount of energy required to heat and



Effect of 4.7-in. Capped Cast Projectile on Nickel Steel Plate Inclined 20 Degrees

melt the cap would decrease the energy available for penetrative purposes.


Another theory is that on the impact the cap takes up that amount of energy which would cause the destruction of the projectile and sets free only that part required to penetrate the plate. The cap is neither of sufficient size nor suitable material to take up so large a store of energy without destroying its molecular structure. The cap cannot act as a guide to the projectile, because it has become deformed when the projectile is most in need of guidance, thus another theory comes to naught. The most likely theory, declares Herr Kodar von Thurnwerth is that the uppermost layer of the armor is softened and the plate so transformed into a homogeneous steel plate.



Action of Uncapped Projectile on Striking Krupp Steel Plate

In striking the best Krupp cemented and hardened nichel-chrome steel plate a projectile is arrested in motion almost immediately and a pressure of from 220 to 440 lb. occurs on its head. At that instant the head of the projectile is deformed and its then broad rounded surface cannot pierce the plate, but seeks to compress it; this results in the front surface of the plate bulging in, and the rear side bulging out. Meanwhile, the cylindrical body of the projectile moves forward, until, arrested by the deformed head and the plate, the low tenacity of the tempered material is overcome and the projectile breaks up. Its head is broken loose by the resistance and is practically welded to the plate. This is the unsatisfactory effect of the uncapped projectile against hard plate.

The superior action of the capped projectile, it is declared, rests on the fact that, at the first instant of impact with the plate, the head is not deformed. The cap causes the pressure to be distributed over a fairly large cross-section instead of confining it to the point, and so the point pierces the hard



Action of Capped Projectile on Striking Krupp Steel Plate

steel like a chisel. The cap has no further work to do; the projectile passes on through the plate alone and uninjured; its point, once entered into the hard steel, forms a path for itself, its head ever-widening, and forces out at the rear of the plate a cylindrical section of the softer material it there encounters. This section breaks up into several pieces. The shell goes through the plate whole, more often than it breaks, and with increased bursting effect from this reason.


The capped projectile, however has its limitations. Its superiority to the ordinary shell obtains only with hard plates and with high striking velocities; thus at long ranges it is not more effective. The limiting

velocity is stated to be 1,650 ft. sec. This velocity is attained with 4.7 in. forty calibre guns at 2,200 to 2,625 yd. and with modern 9.5-in. guns at 7,650 yd. These are close ranges and leave recourse to longer fighting ranges and increase in thickness of armor plate as the means at present available for protection against the capped projectile.

AIR CUSHION ABSORBS SHOCK IN AUTO TRAVEL

The question of springs for automobiles is a perplexing one to the manufacturer, as the light, flexible springs which make such comfortable riding at slow speeds on ordinary roads, play so freely on bad roads and at high speeds that bumping on the axles results when the springs are compressed, and often in the rebound the springs break.

A new device intended to absorb the shock of spring play and make the flexible springs practical and comfortable on any road is in



Shock Absorber Attached to Auto

the shape of a cylinder in which works an airtight piston. The cylinder is attached to the axle and the piston to the car frame, by means of suitable brackets, while freedom of movement in all directions is secured by universal joints at the points of attachment. A cap or casing on the plunger fits closely over the cylinder and excludes the dust. The cylinder contains sufficient lubricant for 10,000 miles running and on ordinarily uneven roads the air cushion allows the springs to move freely with comfort to the passengers, while at too great speed over rough places the cushion absorbs the shock, sparing the injurious effect on the springs and

gradually brings the car to a stop. Wear on machinery is thus greatly reduced, as well as the comfort of the occupants of the vehicle being promoted.

CLOCK SHOWS TIME IN THIRTEEN CITIES

A clock recently made by an English firm for an eastern potentate has thirteen dials and shows the correct time for as many of



Clock With Thirteen Dials

the largest cities of the world, viz: Washington, Yokahama, Berlin, Teheran, Bombay, Samarkand, Rome, St. Petersburg, London, Paris, Vienna, Constantinople and Peking.

Each dial is mounted in a handsome ormolu frame, richly engraved and bears the name of its city in native characters, as are also the figures. Similar clocks have been made in this country.


STREET CAR PASSENGERS DRAW PRIZES

In the city of Mexico each passenger who pays fare on a street car is supposed to receive a receipt from the conductor. As the company knows how many receipts are furnished each conductor, it expects a fare turned in for a like number. In order to encourage the passengers to insist upon the receipts, each receipt is made a lottery ticket with a chance to draw one of the 209 cash prizes offered by the company. The prizes range from \$1,000 down to a small amount. The scheme has the approval of the authorities and not only increases travel but furnishes an excellent check upon any dishonest employees.

Shop Notes for 1905 contains 200 pages, 385 illustrations. Price, 50 cents.

NEW TYPE BALLOON "SWANSKE"

A new type of balloon has been built by Capt. Unge, a Swede, and named by him the "Swanske." It is a gas inflated vessel of



The "Swanske"

such shape that in case of an accident and a too sudden descent it becomes a parachute.

HOW TOGO FOOLED THE RUSSIANS

An interesting side light on the battle of the Sea of Japan appears in the Singapore Press in an interview with Capt. Pernitz of the salvage ship "Russ," lost in the battle. The captain was on his way home and said:

"Engagement?—from the Russian point of view it wasn't worthy of the name. Call it a wild scramble for safety—shelter anywhere. Rojestvensky was taken by surprise, completely surrounded, bewildered. The devilish cunning of the Japanese! They had a huge dummy fleet—wooden ships, marvelous imitations of the real article, guns, fighting-tops and all, lying off the Pescadores. Of this supposed squadron our admiral had information, and passing the Pescadores without hurt, we


imagined there was not sufficient weight behind the remainder of Togo's fleet to prevent the greater portion of our armada making for Vladivostok. And then we were trapped, surrounded, and in reality, defeated before the fight began!"

Admiral Rojestvensky, according to the captain, was the only fighting man of any value among the leaders of Russia's forlorn hope. Nebogatoff and the others, by the feeble fight they made of it, were little better than traitors. They were disgraced for ever. Scarcely one of the Russian warships gave battle in the true sense of the word. The whole navy seems to have been dazed by the suddenness of the attack and the overwhelming force of the enemy. There seems to have been no proper understanding between the various commanders as to whether they were all to cut and run, or stand and fight to a finish. Some did the one, a few adopted the latter policy. The result was demoralization, complete, pitiable. Captain Pernitz narrowly escaped with his life.

The marine board at Trieste, Austria, is offering premiums for killing sharks. For specimens of sharks up to 5 ft. long (any species save eatable ones), \$2.30 is paid. Larger sharks bring \$4.60; very large ones, of two particular species, \$11.50; and man-eating sharks bring from \$9.20 to \$230 premium.

TURNTABLE FOR AUTOMOBILES


A turntable for automobiles, built somewhat on the plan of a locomotive table, is now available. Where the owner houses his machine in a small shed it is convenient, as



Turntable

it enables him to always run the machine out going ahead instead of backing. For garages, factories and repair shops its advantages are evident.

MAY RAISE THE MAINE



Plan Proposed for Raising the Maine

An effort is again being made to organize a company to raise the Maine, which is an obstruction to navigation in the harbor of Havana. It is now more than seven years since the wreck occurred and during this time the hull with its heavy load has been constantly sinking in the soft muddy bottom of the bay. The only possible way to raise the vessel would be to inclose it in a cofferdam, and pump the water out.

Whether it could then be patched and floated would depend upon how badly the hull is shattered.

The proposed dam would be about 400 ft. in diameter and 100 ft. deep. The prospect of recovery grows less each year as the machinery, guns and other valuable salvage is being rapidly corroded in the warm salt water. The authorities claim that the wreck is a menace to navigation.

CANADA REVIVES GEORGIAN BAY CANAL PROJECT

The Canadian government has revived the old project of a deep-sea ship canal connecting the Georgian bay with the Ottawa and St. Lawrence rivers, thus creating an all-water route from Chicago to the Atlantic and diverting to Canadian channels the mighty stream of commerce that now flows through Buffalo and New York on its way to Europe. Canada would reap an immense profit in tolls.

The annual export of grain from the United States amounts to 2,223,000,000 bushels

and of meat 1,000,000,000 pounds, three-fourths of which moves to New York by rail and less than one-fourth from Chicago to Buffalo by boat. The cost of carrying from Buffalo to New York is stated as greater than the cost from New York to Liverpool. The distance from Chicago to Buffalo via the great lakes is 900 miles and from Chicago to Montreal by way of the Michigan, Huron and Georgian bay canal, 905 miles. The Georgian bay canal would undoubtedly afford a cheaper and



Map Showing Route of New Canal

shorter road to the foreign market, and though New York would inevitably lose, Chicago and Duluth would gain.

"In all 32 miles of canal with a depth of 20 ft. of water on the sill and 22 in the reaches would have to be built," remarked James J. Hill. The Ottawa river would require some dredging and for the rest, nature has prepared the way. The cost of building the canal would approximate \$70,000,000.


HOW TO MAKE AN ADJUSTABLE SHAVING MIRROR

By C. P. Mitchell

Get about two ft. of $\frac{1}{4}$ -in. brass rod and bend one end in half circle as in Fig. 1. This can be done by holding loosely in the jaws of small vise and bending a little at a time until the half circle is made. The other end should then be screwed tightly in vise and bent up in same plane $1\frac{1}{4}$ in. from end to a sharp right angle as in Fig. 1.

bolt about $\frac{3}{8}$ in. from bend; then place in vise to the depth of 1 in. and bend the two ends apart at right angles as in Fig. 3. The extremities of each end should then be bent around two pieces of stout wire curved away from each other, the ends of which are bent over the edge of a round mirror, as in Fig. 6. If the ends of the wires are pinched together, the mirror can be slipped in and out at will. Now put the $2\frac{1}{2}$ -in. piece of brass band in vise to the depth of $\frac{3}{4}$ -in. and bend at right angle; then bend it back over and around end of rod. Now bore a hole near the edge to correspond to the hole in the $4\frac{1}{2}$ -in. piece and insert a half inch bolt through both holes as in Fig. 5, using two nuts, one to act as a lock nut.

The door stop can then be screwed to the wood frame of any window (two screws will be sufficient to hold it, using the two upper screw holes). If the curved end of the rod is then inserted and the mirror placed on the other end of rod and the nuts



Get a folding door stop at any hardware store (those used in connection with doors which run on rails) and drill with a $\frac{3}{8}$ -in. drill, a hole in the middle of the center projection, as in Fig. 2, but when the point of the drill begins to show on the other side be careful to stop when the hole is large enough to admit, easily, the curved end of the $\frac{1}{4}$ -in. rod. In other words, instead of drilling all the way through, stop when the opening is a fraction over $\frac{1}{4}$ in., making the opening at one end $\frac{3}{8}$ in. and at the other $\frac{1}{4}$ in.

Get about 7 in. of 1-in. wide and $1/32$ -in. thick brass band and cut with shears in two pieces of $4\frac{1}{2}$ in. and $2\frac{1}{2}$ in. respectively. Bend the $4\frac{1}{2}$ -in. piece in half and hammer flat together, then drill a hole for a half inch

tightened so that it will turn stiffly, it will be found that the mirror can be placed in any position desired and can be put out of the way when not in use. Other door stops can be screwed to other windows in any part of the house and the mirror and rod moved from one to another.

"POP" WISE AS HIS ANCESTORS

I have been a reader of "Pop" about 6 months, and find it the best mechanical publication I have ever had hands on. I am a marine gaso-engineer and find the Shop Notes a great help. "Pop" may be young, but a Great-Grand-Pop could not be any wiser.—E. S. Stout, San Pedro, Cal.


TURBINE SHIPS 800 FEET LONG

Horsepower, 75,000--Displacement, 43,000 Tons--A Floating City

In whatever respect any big ocean liner in existence has excelled in the past, be it dimensions, capacity, accommodations or speed, the eclipse of her pride is presaged in the construction in England of two monster turbine Cunarders. In such degree will these mammoth vessels surpass all their elder sisters of the deep, competition between them will scarcely be worth while—

the twins will have to race with each other to create an interest.

The dimensions of these new vessels are as follows: Length over all, 800 ft.; beam, 88 ft.; depth, 60 ft.; displacement, 43,000 tons. The horsepower of each will be 75,000 and the contract speed is placed at 25 knots. Comparing them with other big steamships of the world, we find that in length the



Courtesy Scientific American.

"Eight-Story" Ship With Elevators

"Baltic" is exceeded by 75 ft. and in displacement 3,000 tons; that the beam of the "Great Eastern," for years the accepted standard for modern steamships, is 5 ft. less than that of the Cunarders, and her depth 2½ ft. less; length, 108 ft. less. And that the speed of the "Deutschland" and the "Kaiser Wilhelm II," for years the fastest ships crossing the Atlantic, is 1.5 knots too slow to keep up with even the contract pace of the Cunarders, which, it is tacitly agreed, will not be their best, as turbine vessels nearly always exceed the contract speed.

The steel plating of the turbine twins is 1½ in. thick, bringing it on the lap to a total of 3 in. on each side. Their extreme draft is 36 ft., but not until the new Ambrose channel into New York harbor is completed will they be able to load to that draft.

The vessels have double bottoms 5 ft. 6 in. in depth between the inner and outer shell. The Scotch boilers are placed four abreast and the large coal bunkers are located in the wings. There are in all eight decks.

The third-class passenger accommodations are the best ever afforded; the space is divided into separate state rooms, and the rooms are lighted with port holes. There is a great dining saloon on the upper deck, 80 by 125 ft., and capable of seating over 500 people. In the center will be a large overhead well, extending through two decks, and crowned with a dome of cathedral glass. The first-class state rooms will be 50 per cent larger than the usual size.

The vessels in height compare well with an eight-story building, and in many respects resemble one. They are equipped with elevators, an innovation that will be greatly appreciated.

Four turbines of a designed indicated horsepower of 18,000 supply the motive power. These will all be placed on the same platform. The stride in size and construction is indeed a long one, but it is hardly to be expected that other large steamship companies will let it rest here—it is merely an impetus to competition.

UNIQUE MARINE PULPIT

Where the "Sky Pilot" Preaches From the "Wheel"

What is doubtless the most unique and appropriate pulpit in the world may be seen in the mariner's church, San Francisco. As its name implies, it is devoted exclusively



The Marine Pulpit

to the welfare of the sailors who visit that port from all parts of the world.


The pulpit platform is in the form of the stern of a ship, modeled after the graceful lines of the "Young America," of San Francisco, a very handsome craft.

THE ELECTRIC VIOLIN A SUCCESS

The Most Difficult of All Instruments Now Played By Machinery

All kinds of violin music ranging from the classical production of world-wide artists down to the old time "money musk" of the husking bee, can now be rendered without the touch of a human hand. An ordinary ½ hp. electric motor furnishes the power and other electrical machinery does the rest. While pianos, guitars, cornets, banjos and scores of other instruments have been reduced to mechanical operation, the violin has persistently baffled the hundreds of earnest inventors who have been working for years to perfect a purely automatic mechanical instrument. It is only within the past few weeks that success has been achieved, and a mechanism perfected little short of human in its operation.

The violin itself, which requires no explanation, is firmly anchored on a handsome cabinet. Instead of a bow there are four revolving discs, composed of celluloid and rosin, called sounding brushes,—one for each string. These discs are constantly revolving while the machine is running, and one or more of them press against the strings at the proper moment, by means of electro magnets. At the instant the disc touches its string an electric finger, also



The Electric Violin

operated by a magnet, presses the same string at the proper place, just as a musician would do with his own fingers. There are 58 of these electric fingers arranged in rows, as will be seen in the illustration. Connecting with the revolving discs and the electric fingers are wires, not shown, which pass into the lower part of the case containing the violin. These wires each end in a small brass strip, or contact point, which rests upon a perforated strip of paper, which is the score. This paper strip passes over a brass cylinder, and when one of the perforations in the paper reaches a contact point, the perforation allows the brass point to touch the brass cylinder thus completing the electric circuit and operating the proper magnets which control the movements of the discs and fingers. A long perforation therefore produces a long note, and a short perforation a correspondingly short note. The machine can do what no human performer can do, viz., produce a sound on any two or more strings at the same instant, thus securing an orchestral effect.

One would naturally expect a machine could produce nothing but "brassy" or metallic music, but quite the opposite is the fact. The transferring of a piece of music, as actually played by a performer, onto a record from which the perforated strips are

made, is a difficult operation, which the inventor guards as a state secret.

The electric virtuoso is designed for use in the home, but will doubtless be first seen on the stage as a musical novelty, and in other places of amusement. It can be adjusted to four times the volume of the hand played instrument, or graduated to suit the faintest, most delicate strains desired. The tuning would naturally seem to be a difficult undertaking, but this is also done mechanically; in fact one who is not himself a musician, can accurately tune the instrument by means of a special roll of the perforated paper, and the use of certain thumb screws. In short, the electric violin is said to be capable of performing any action of the hand-played instrument, and much more.


Lightning killed one man and injured two others in a mine 1,008 ft. in the ground in Michigan recently. The bolt struck a cable and ran down into the mine, prematurely setting off two charges of dynamite.

"If explosions occur in the muffler of the gasoline engine, add more battery," advises a contemporary. It may be a case of weak mixture, when the user will have to add more gasoline.—The Gas Engine.

THE HANDLELESS HAND CAR

From Boston to San Francisco, and as far back as the oldest settler can remember the sight of the section gang pumping their hand car is a familiar one. Thousands upon thousands of these useful but unsightly vehicles travel over 6,000,000 miles each year on the steam railways of this country.

The auto craze seems destined to reach even "Pat," and he is due to ride in ease in the near future when he goes down the line



"Pat's" Automobile

to take out a broken tie or raise a low joint. His auto rejoices in the impressive name of section motor work car, and will carry his crew merrily along at 15 miles an hour, while the boys rest and pack their pipes. The motive power is a two-cylinder, 8 h. p., gasoline engine, with simple gearing and calculated to operate with little experience. The car is made for any gauge from 24 in. up, will run in either direction, and is


quickly stopped by means of a double hub brake. The framework is of steel tubing, combining necessary strength with minimum weight.

MUNICIPAL TELEPHONY A FAILURE IN ENGLAND

For years the government has operated the telegraph in England, giving an excellent service at very low charges. Six years ago a bill was passed allowing cities to go into the telephone business. This act was repealed on August 9 last. The plan was a failure. During the six years only 13 cities out of a possible 1,334 took out a license, and of the 13 only 6 put in telephones. On August 9, when the act was repealed, only 5 municipal exchanges were in operation, and all of these were in a sorry plight, financially. In order to protect the public the government has offered to take over and operate the five exchanges, which are situated in Glasgow, Hull, Brighton, Portsmouth and Swansea, and which cost a total of \$2,500,000.

The lesson is obvious. Something more than a merely honest administration is required, for there is no suspicion of the grafting prevailing in this country, in connection with the failure.

Just try to imagine the Czar taking chances on a trip in a submarine!



Courtesy Ry. Review

Motor "Hand Car"--Carries 15 Men 15 Miles an Hour


All the articles appearing in this department are reprinted in book form at the end of each year.

SHOP NOTES

Contributions to this department are invited. If you have worked out a good idea or know of one, please send it in.

A PIPE HACKSAW FRAME

To make this frame, three $\frac{1}{4}$ -in. ells, two pieces of $\frac{1}{4}$ -in. pipe, 3 in. long (B B), one piece of $\frac{1}{4}$ -in. pipe, 15 in. long (A), and one




Pipe Hacksaw Frame

$\frac{1}{4}$ -in. tee will be required. C is a piece of bolt iron, pipe-threaded and screwed into the ell; D is a piece of the same metal, 4 in. long, which is bolt-threaded and passed through the reamed tee with about 4 in. of thread on the handle side of which is a nut by which the tension of the blade may be adjusted. Parts C and D both have slits sawed in them parallel with the blade, into which the blades are fastened by means of pins passing through holes drilled for the purpose. Fittings without bosses on them make a neater appearance, and all brass pipe for the frame looks better, also.—Contributed by Apprentice.

HOME-MADE WATER HEATER

A water heater to have steam and drip connection hitched into steam heating system, the same as a radiator, water entering lower tee and being discharged from the upper tee, is shown in the illustration.

The heater may be used either vertical or horizontal, though it should be pitched toward the drip end, and may be used with or without tank. It consists of outer pipe



Home-Made Water Heater


or shell, through the center of which passes smaller pipe for steam, the water being around this smaller pipe; heads or bushings

in the end make the shell watertight where the steam pipe enters with a long thread at both ends.

A $1\frac{1}{2}$ -in. outside pipe with tees $1\frac{1}{2}$ in. x $\frac{1}{2}$ in. or equivalent; with bushings $1\frac{1}{2}$ in. x $\frac{3}{4}$ in. for the end and bushings $\frac{3}{4}$ in. x $\frac{1}{2}$ in. for connecting and making watertight joints with $\frac{1}{2}$ in. steam pipe at the ends, will heat a volume of water 6 or 8 ft. long.—Contributed by W. J. Barber, North Adams, Mass.

BATTERY ECONOMIZER FOR TELEPHONES

By the use of a switch (3) placed on the telephone box or on the wall and wired up with the batteries (1 and 2) as shown in the diagram, a great deal of wear on the batteries can be saved and they will last a long while. — Contributed by Geo. R. Bowers, Shelbyville, Mo.



VARNISH PRECEPTS

One coat of varnish never cracks.
Two coats of varnish seldom crack.
Three coats of varnish often crack.
Four coats of varnish always crack.

—Master Painter.

Shop Notes for 1905 contains 200 pages; 385 illustrations. Price, 50 cents. Write for a copy to-day.

DRAWING FIVE-POINTED STARS

One of the easiest methods of making a five-pointed star by the use of the steel square is to describe a circle of a given diameter, then divide up the circumference by indicating chords equal to seven-twelfths of the diameter. The five points where the chords intersect the circumference will be the points of the star, says the Metal Worker.




Fig. 1.




Fig. 2.

Another good way is to divide 360 by the number of points the star is to have, which will give the distance between points in degrees. Then get the angle on the bevel square with the protractor, and using any diameter as the base line, the points may soon be obtained. This operation is illustrated in Fig. 1, while Fig. 2 shows the star with points joined.

HOME-MADE LEVEL

A home-made level which suffices for all ordinary purposes is shown in the diagram. The level is made of a $1\frac{1}{2}$ in. x 3 in. x 36 in. piece of wood, two plastering laths, a string and a plumb bob.




Home-Made Level

2 ft. long, a string and a plumb bob. The illustration explains the construction. The laths may be nailed to the bottom piece with shingle nails.—Contributed by Jas. Morton, Jr., Dunn, Tenn.


STRAIGHTENING WIRE IN THE LATHE

Short lengths of thick wire are very hard to straighten with the mallet, but the work can be done in the lathe, quickly and easily, says the Model Engineer, London.

Grip the wire in the chuck, and roughly straighten it with the hand, so that it clears the bed. Now get two pieces of hardwood about 1 ft. by 2 in. by $\frac{1}{2}$ in., and bore a hole in each about 2 in. from one end to fit the wire. Slip them on the wire close up to chuck, and start the lathe. Grip the pieces of wood in the position shown in the sketch, keeping the ends farthest away pressed close together and twisting the pieces of wood in opposite directions. Move slowly along the wire, keeping in the same position. If necessary, repeat the operation. New holes



Section



Straightening Wire

can be bored in the wood at a short distance from the old ones when these become too large.


WATERPROOF ELECTRIC LIGHT SOCKETS

Electric lights so located that they are exposed to water may be made waterproof by the following described means:

Before putting the lamp into the socket fill the receptacle with a lump of soft putty, then screw the lamp in. This will force the putty into every crevice and make it absolutely tight. Unscrew the lamp again, clean the putty from the threads so that it will not stick there as it hardens, then screw up again. A correspondent of Power says this works exceedingly well.

BABBITTING LADLE MADE OF PIPE

Into a $1\frac{1}{4}$ -in. pipe cap screw a $1\frac{1}{4} \times 1\frac{1}{4}$ in. nipple, threaded on one end only. On the inside of the nipple file a mouth or lip (A) for pouring a small stream. Make a handle of $1\frac{1}{4}$ -in. or $\frac{3}{8}$ -in. pipe of whatever length is




Babbitting Ladle

most convenient for your use. Screw the handle into the nipple about $\frac{1}{4}$ in. to brace it and plug it at that end with a pipe plug, or an old bolt threaded in. On the other end of the handle screw a tee, making it convenient to hold. Have all the threads neat and tight, so the ladle will not be unsightly.—Contributed by Apprentice.

TO CUT THIN STEEL WITHOUT TEMPERING

A simple method of cutting a thin piece of steel as from a saw blade, without drawing the temper, is shown in the illustration.



Cutting Thin Steel

A correspondent of the Blacksmith and Wheelwright recommends this method.


CLEANING SMOKED CEILINGS

A smoke-blackened ceiling may be cleaned by coating with a mixture of starch and water, allowing this to dry, and then brushing off lightly with a soft brush.

HOME-MADE POST AUGER

Any circular disk that is wide enough and not too thick—as, for instance, the broken blade of a disk harrow or a circular saw blade—may be used for the auger blade. Center punch the plate, mark the size required with a compass and cut in circular shape.

At the center of the disk punch or drill a $\frac{3}{4}$ -in. hole, then split the disk from the center to the outer edge and cut out a small strip as at X in the sketch, so as to leave a better opening, says the American Blacksmith. Sharpen both sides of this split and turn one down and the other slightly upward. Forge a piece like B and rivet it on the blade as at A. Forge a lip, C, from a



Home-Made Post Auger

piece of spring steel and rivet it to the blade on the edge opposite the split part. This lip is intended to cut the soil on the outside, while at the split the cutting is directly down into the soil. The whole blade should be concaved on the outside edges—turned upwards.

Make the stem D, of $\frac{3}{4}$ -in. round iron, 4 ft. in length, with an eye for a cross handle and with its point extending 6 in. below the blade and twisted like a twist drill. Cut a thread on the stem and screw into plate B.

This auger is particularly useful in boring holes in stiff clay soil. It makes a clean hole and can be used without water. The boring can be fast or slow, according to the downward bend given the cutting lip of the disk.

CHEMICAL FORMULA TABLE FOR PAINTERS THAWING FROZEN GROUND WITH LIME

The painter who has some knowledge of chemistry will find it greatly to his advantage in the preparation of his colors. For those who cannot take such a course the following table compiled by the Master Painter will be found useful and worth memorizing.

Lime may be successfully used in thawing frozen ground where excavating must be done to gain access to frozen pipes. Apply one barrel over night, covering well, for thawing out frost 1 ft. deep, in a trench 2 ft. wide and 8 ft. long. Hot water may be used with the lime to good advantage.


Common Name	Chemical Name.	Formula
Barytes, Blanc Fixe,	Sulphate of Barium,	BaSO_4
Gypsum, Terra Alba, Plaster of Paris,	Sulphate of Calcium,	$\text{CaSO}_4 \cdot 2\text{H}_2\text{O}$
De-Hydrated Plaster of Paris,	Sulphate of Calcium,	$\text{CaSO}_4 \cdot 2\text{H}_2\text{O}$
Whiting, Lime Carbonate, Lime, Paris		
White, Spanish White, English White,		
Marble Dust,	Carbonate of Calcium,	CaCO_3
Sublimed Lead, "White Lead,"	Sulphate of Lead,	PbSO_4
White Lead, Corroded Lead,	Basic Carbonate of Lead,	$2\text{PbCO}_3 \cdot \text{PbH}_2\text{O}$
Silex, Silver White, Infusorial Earth, Wood		
Filler, Ground Quartz,	Silica,	SiO_2
Zinc White, Zinc Oxide,	Oxide of Zinc,	ZnO
China Clay, Clay,	Hydrated Silicate of Alumina,	$2\text{SiO}_2 \cdot \text{Al}_2\text{O}_3 \cdot 2\text{H}_2\text{O}$
Litharge, Lead Oxide, Massicot,	Lead Monoxide,	PbO
Red Lead, Orange Red,	Lead Oxide,	Pb_3O_4
Chinese Vermilion and Mercury Vermilion,	Sulphide of Mercury,	HgS
Venetian Red, Indian Reds, Mineral Brown,		
Etc.		
Chrome Yellows, M and L,	Oxide of Iron,	Fe_2O_3
Chrome Yellow, O,	Chromate of Lead,	$\text{PbCrO}_4 + \text{PbSO}_4$
Lamp and Gas Black,	Chromate of Lead,	PbCrO_4
Ivory, Bone, and Drop Black,	Carbon,	C
Graphite,	Carbon, etc.,	C
	Graphite,	C

AUTOMATIC CUT-OFF FOR ELECTRIC LIGHTS

Fasten an alarm clock on a shelf, and about 10 in. away place a switch. Make a trigger as shown in the sketch and mount it on an axle, so it will move backward and forward. At a point on the wall above this arrangement, fasten a spiral spring at such a height that when the switch is closed and then let go, it will stretch the spring. Fasten the spring to the switch with a screw eye.

Attach a stout cord to the alarm key of the clock and run the cord to the trigger. Put a hook on the string, so that it may be hooked to the trigger, showing that the alarm is wound up. Wind and set the alarm; pull the switch down and put the handle in the trigger, then fasten the string on the trigger.

When the alarm goes off, the key will



Automatic Cut-Off for Electric Lights

wind up the string, thus pulling the trigger out and releasing the switch handle, which is pulled up by the spring and so cuts out the lights. This device is convenient for store keepers who wish to keep lights burning in show windows until a late hour.—Contributed by W. J. Slattery, Emsworth, Pennsylvania.

TO MAKE A STEAM GAUGE ALARM

A steam gauge alarm that will sound whenever the steam pressure falls to a predetermined point is described by a correspondent of the National Engineer.

Connect up an ordinary annunciator bell with the gauge, running one wire to the post of the pointer and the other to a piece of copper fastened to the face of the dial, but insulated from it. The wire to the gauge pointer will make contact with the piece of copper on the dial face whenever the steam pressure drops to the predetermined point, thus closing the circuit and ringing the bell. The alarm may be thrown out of service at any time by a switch placed in the circuit.

HOW TO PAINT IRON, ZINC AND GALVANIZED IRON

The best time for painting new iron is at the foundry as soon after casting, or being wrought or rolled, as possible, says the Master Painter. Paint it when a dry wind or warm sun will act upon it; do not paint it in the early morning or damp evening. First see that the iron is thoroughly dry and free from rust, and then coat with red lead and linseed oil, a thin coat, just enough to penetrate the pores of the iron. The first coat must dry hard. Follow up with three other coats containing red or white lead in as great proportion as possible.

To paint old iron, burn off all rust and scale, brush with turpentine or paraffin and proceed precisely as with new iron.


For zinc, the first coat should consist of white lead, red lead and turpentine, tempered with varnish. Wash new rolled sheet zinc with a solution of a tablespoonful of hydrochloric or nitric acid to a gallon of water, or scratch the surface with No. 2 glass-paper before painting.

Treat galvanized iron the same as zinc, but do not use the acid preparation, nor scratch. Very smooth, bright tin plate must be first dulled or scratched and the first coat should be oilless.

PUTTING A NEW BASE UNDER A BOILER

In substituting a new base under a boiler for a broken one, a correspondent of the Metal Worker tells how the job can be done quickly and without disturbing any of the connections.

Saw out two hardwood wedges and drive them under the two return pipes in position as shown at A in the sketch. These should be of proper height to lift the boiler off the base just far enough to allow the broken base and grates to be slipped out and the new base slipped in. Brace the boiler from the walls to keep it from slipping



Putting a New Base Under a Boiler

sideways, and before removing the old base score a deep mark with a cold chisel on the brick foundation, so that the new one may be put in on exactly the same spot.

HOW TO MAKE CELLULOID INCOMBUSTIBLE

Make an ether-alcohol solution of celluloid and an ether-alcohol solution of ferric perchloride, then mix the two solutions. This will give a clear, syrupy liquid, yellow in color and yielding no precipitates. Pour it into a suitable vessel and leave for spontaneous evaporation. A shell-colored substance will be produced, which after washing and drying, gives the result desired, says the Model Engineer, London.

Celluloid so treated will be pliant, transparent, unflammable and incombustible.

SLED MOVING LAWN SPRINKLER

In watering a lawn in the old-fashioned way one has to do much walking in moving the sprinkler from place to place, shutting off the water and turning it on again, and is certain to get his feet wet in the opera-



Sled for Moving Lawn Sprinkler

tion. To avoid all this trouble, make a little sled of 1x4 in. pine, 24 in. long, with $\frac{1}{2}$ -in. board nailed across the runners, which should be about 20 in. apart.

Then fasten the sprinkler on the sled, well toward the front, attach about 8 ft. of rope to the sled to draw it by, and arrange the hose so it will run out back of the sled to prevent its tipping over. The sprinkler can then be moved to any point on the lawn without one's running back and forth through the wet grass to turn the water on and off.—Contributed by J. S. Wallace, San Jose, Cal.

RACK FOR KITCHEN UTENSIL COVERS

Tin covers for stew pans and kettles are a nuisance when not in use, as they are apt to slip off the shelf, if piled upon it, and are sure to get out of order so that one must search for one of the right size. To make a convenient rack for these covers get some strips of $\frac{1}{2}$ -in. boards, half of them 1 in. wide and the other half 3 in. wide and all as long as the shelf is wide. Have as many of each width strips as you have covers, or more. Fasten these strips with shingle nails to the bottom of a shelf that is about 5 ft. from the floor as



Rack for Kettle Covers

shown in the sketch. The strips should be fastened at various distances apart in order to accommodate the several sizes of covers. Place the covers with knobs or handles downward.—Contributed by J. S. Wallace, San Jose, Cal.

EASY METHOD OF BURNING 50 BUSHEL OF CHARCOAL

In our February number instructions for burning 100 bushels of charcoal were given; the accompanying directions are for a smaller quantity—say, forty or fifty bushels.

Pick out a spot where rocks are not too plentiful and where perpendicular walls of ground will not crumble too easily and dig a hole 6 ft. long, 4 ft. wide and 6 ft. deep. Cut into lengths of about 4 ft. 7 in. enough of sound dry wood to fill the hole. Pile the wood alongside the hole where it will be within easy reach. Get an armful of dry kindling, split lengthwise, and a couple of armfuls of green evergreen brush or green hay (wet gunny sacks will do as well).

Put the kindling at the bottom of the hole and set it on fire; next pile in the wood on top of it, packing it close together. For the first 2 ft. work rapidly. Proceed with the filling until the hole is full and round it up a little, making it highest in the center. Then lay on the covering material—green grass, wet sacks or whatever it may be. Spread this material along the center, leaving a 6-in. space at the edges of the pit uncovered, then throw dirt on the covered portion. The 6-in. space left is for ventilation and escape of smoke.


The pit will not require much tending. When the flames break through, close it a little at that place, but not more than is necessary. By starting the burning at six o'clock in the morning, the material will be burned to coal by nine o'clock in the evening—fifteen hours. Along in the afternoon the fire will be getting pretty well to the top. Tramp on the pit, and if any holes in it can be felt, remove the covering at those places and trample in some short pieces of wood about a foot long until the hole is filled up even with the top, then replace the covering. Toward the last it must be watched closely, as the flames are apt to break out.

If for fifteen hours a thick cloud of smoke has rolled above the pit, at the end of that period it should be burned to coal. Put damp covering over the 6-in. marginal space, pile on dirt to a depth of 8 or 10 in., wet it and trample down till solid. In the morning wet the dirt again, thoroughly. In two days the coal may be dug out.

Choose a still day without wind for burning; foggy or rainy weather will not affect the burning.—Contributed by John H. Evans, Dewey, Montana.

HOW TO MAKE A PNEUMATIC PAINT MIXER

A pneumatic paint mixer may be made of $\frac{1}{2}$ -in. iron pipe, with an air hose coupling attached to the upper end and the lower portion of the pipe bent into a circle slightly



Mixes Paint Pneumatically

smaller in diameter than the inside of the bottom of the barrel. In the circular portion, drill a number of $\frac{1}{8}$ -in. holes spaced 2-in. centers. Air escaping through these holes, agitates the paint in the barrel and mixes it thoroughly. The end of the pipe in the circular portion may be merely plugged up, but is apt to clog in the section indicated at A, because the force of the air expends itself before this point is reached. Probably a better way would be to connect B to the ring by a T, as shown at C, so that the air will circulate from both directions, says the Canadian Machine Shop.

The mixer may be connected to an old air hose and this, in turn, connected to the main line with an air hose coupling.

Contributions to our Shop Notes department are invited. Brief, clear descriptions and rough sketches are acceptable.

Life subscription to Popular Mechanics, \$10; five years, \$3.

ACID-PROOF INK FOR ZINC

An acid-proof ink which may be used with a drawing pen on zinc, says the Draftsman, consists of 1 dram verdigris, 1 dram sal-ammoniac powder and $\frac{1}{2}$ dram lamp-black mixed with 10 drams of water.


MENDING PORCELAIN AND GRANITE WARE

Porcelain and granite ware, which cannot be soldered, may be mended satisfactorily in the following way:

Mix together litharge and glycerine to about the consistency of putty and then apply to part to be mended. Apply it at each side of the hole and press it through, then finish off smooth and let dry. When dry it will be as hard as the porcelain and will withstand any heat that porcelain will.—Contributed by W. C. Telford, Santa Barbara, Cal.

SIMPLE TAP WRENCH

A simple tap wrench is made of $\frac{1}{8}$ -in. steel rod in two parts each 4 in. long. One end of each part is treated as shown in Fig. 1. Fig. 2 shows the two parts joined to form the wrench.—Contributed by M. Frank Jordan, 45 Jackson Pl., Chicago.




Handy Tap Wrench

HOME-MADE BLUEPRINT FRAME

The frame itself is made of pine wood, bound on the corners with iron corner bands. The sides should be at least $1\frac{1}{4}$ in. thick by 3 in. wide, and the front piece which is planted on the edges of the sides, should be $1\frac{1}{4}$ in. by $1\frac{1}{4}$ in. and screwed on very securely; they must lap over about $\frac{1}{2}$ in. on the inside of the frame to make a rest for the glass. The back should be made in three pieces, held together by hinges, and should be $\frac{5}{8}$ in. to $\frac{7}{8}$ in. in thickness, according to the size of the frame.

In the building of this frame, the most time should be given to the spring levers, which must be accurate and have close contact. The levers are hinged to the side and are pressed down on the back, forcing the

back of the frame tightly against the glass by the three brass springs and being held in place when down by three cupboard door snap locks. The three levers should be held together and in line by the iron or wood brace across their backs, this brace is very essential and should be securely attached. A thick piece of felt should always be laid on top of the paper so that the back may bear evenly on the print and make close contact between the blueprint paper and the tracings, which fact is absolutely necessary. The iron frame as shown, is ordinary black iron pipe, $\frac{1}{2}$ in. to $\frac{3}{4}$ in., according to size of frame, and the stand, which is fastened to the window trim, is heavier weight, $1\frac{1}{2}$ in. to $1\frac{3}{4}$ in. The collar must fit snugly around the nipple, and a drop of oil once in a while is necessary. After the iron frame



Home-Made Blueprint Frame


is built, it is a good plan to set-screw the connection between the frame and arm, as this joint would have a tendency to drop down on the treads. The frame can then be revolved on the arm treads, to put in the drawings and then turned glass side up and swung out the window to print. I have made and set up one of these frames in our drafting room, and it has given universal satisfaction.—Contributed by Prentice P. Avery, 39 Woodside Av., Ridgewood, N. J.

PRESS STOPPING DEVICE

The accompanying illustration shows an arrangement installed by W. Schafer of San Francisco, Cal., on a press used for baling dry goods, to stop the press in case of a careless packer letting it run up too far. As the movable platform rises, weight B, which is a little heavier than weight A on the other side, is pushed up and so lowers weight A (securely fastened to the cord so that it cannot move along it) and the lowering of weight A throws the circuit breaker, C. In case the man making a bale should neglect to stop the press when his bale is made, the circuit breaker will throw in the usual manner, so that it is not necessary to have any arrangement for stopping on the descent. The pulleys must be good ones and so arranged that the cord, when loose, will not work out of the groove. Mr. Schafer has used this device for about three years and states that it has never given trouble of any kind. This stop could be adapted to other purposes, for stopping elevators, for instance.

HOW TO MAKE AN S-WRENCH

From the scrap heap select a piece of good cast steel, $\frac{1}{2} \times 1$ in. by 3 in. long (Fig. 1). Draw down the center and round the ends. At SS (Fig. 2) fuller to $\frac{1}{4}$ in. thick, and leave the middle a little thicker. Make holes




in the ends as shown by the dotted lines, Fig. 2, using a square punch. Put a flatter on and smooth up side nicely.

Cut out AA on both sides with a sharp thin chisel, which will spread the jaws. Round up again and shape like Fig. 3 to suit your taste. Heat to a cherry red and lay in some unslaked lime which will soften. Let it cool and then dress. Make one end for, say, $\frac{3}{8}$, and the other for $\frac{1}{8}$, or any




size you want. Now heat to a very low red. Lay it between two green pine boards or drop in linseed oil, says a correspondent of the Blacksmith and Wheelwright, and you will get a good color and a good temper.



Automatic Stopping Device for Presses

MAKING A SPRING HEAD

There are many smiths who do not know how to put a head on the upper main leaf of an ordinary elliptic spring, says a correspondent of the American Blacksmith. The following is an excellent method:



Making a Spring Head

Cut off steel the length wanted, less $\frac{1}{2}$ in. for each end. The instructions are for only one end, but apply to both. Take 3 in. of $\frac{5}{8}$ -in. square Norway iron. Split through from one side as at A, and have the split the width of the steel to be used. Now fuller as at B, insert steel as at C and weld. Then trim as shown by the dotted lines at D. The ears can be bent in the vise, without danger of injury from cold, shut and should be bent as at E. Now dress up thread in the tool F, after fulling between the ears. Fulling will bring the ears parallel and after dressing them, the holes are drilled.

Mechanics for Young America, an illustrated book for boys. Price, 25 cents.

BORING ON THE TURRET LATHE

Boring to Size vs. Boring Undersize and Re-reaming by Hand

At one time I worked in a large manufacturing concern where all gears, sprockets, pulleys, collars, etc., were bored in the turret lathe by a system that, I admit, was new to me. I had worked in different shops, had seen many turret lathe fixtures and systems, but never before had I heard of boring articles undersize and reaming them to size by hand with an expansion reamer. The system I refer to could be bettered, in my estimation, by the suggestions offered below. Their boring was done by first running a drill, slightly smaller than the reamer, through, then reaming.

By use of a little oil and a new reamer a good fit could be secured, but it would not be advisable to keep buying new reamers; consequently when the reamer becomes slightly worn (which will happen in a very short time by continuous use) the bore will be small. If reamed dry, the bore will be too large, even with a worn reamer. The firm in question used oil on the reamer, which made the hole as small as possible, with the result that every piece had to be reamed by hand with an expansion reamer to obtain a good fit. In a large plant this labor of re-reaming will amount to a large sum in the course of a year.

I have often wondered why a system as explained below would not be satisfactory to others. I have rigged up turret lathes in this way, and it gave satisfaction in every respect. Furthermore work can be done more quickly, besides, no reamer is used.




Fig. 1




Fig. 2




Fig. 3

Referring to the diagrams, Fig. 1 shows a view of the boring bar in position for boring. Fig. 2 is a sectional view of bar, bushing for same and lathe spindle. Fig. 3 shows the cutter in the bar and the method of holding it. In Fig. 1 and Fig. 2, A is the boring bar turned on end B, so as to pass through the core and enter the bushing C in the lathe spindle, which steadies the end of the boring bar. D is turned to fit in spindle with shoulder at E for bearing against the end of the spindle and is bored out at F, to receive different sized bushings, which are fastened in by a feather key and can readily be changed. The bushings could be placed directly in the spindle without the use of D, but D is used to keep the bore of the spindle from wearing; by frequent changing of bushings, etc.

The bar is fitted with cutters the same as a facing tool, but these are not held by a key, as they have to be centered exactly, because both sides cut and with a key too


HOW TO BURN SAWDUST

A furnace and boiler setting like the one shown in the diagram is an excellent arrangement for burning sawdust, says a correspondent of Power.

The boiler setting itself is like that usually used in a horizontal boiler, but the grates are in an oven or projection built in front of the boiler instead of being under it. The oven is about 10 ft. long and should be full width of the boiler, or if convenient, 2 ft. wider than the boiler is preferable. The grates should have $\frac{1}{4}$ -in. openings.

The sawdust, brought by a mechanical carrier of some kind is dropped through two chutes on to the grates and lies in two cone-shaped piles that cover the entire grate surface.

The fire should be started with shavings or other dry material and will burn principally around the edges where the draft will force itself up through the fuel. When well



Arrangement for Burning Sawdust

much time is lost in setting. The cutters are fastened as shown at A, Fig. 3. The cutter is countersunk to receive cone head set screw and it is turned to size while so fastened. It is obvious that when replaced, it will always be central and different sized cutters can be used by turning them to size in the same bar they are to be used in.

With the end of the bar supported in the bushing, all material can be removed in one cut and as the cutter is turned to size, and being straight from cutting edge, no reamer is necessary. One cutter can be ground an hundred times without changing the size of the bore.

While this method is very old to some, it will no doubt help someone who is still toiling away with a monkey wrench and an expansion reamer.—Contributed by Norman Baker, Hoopeston, Ill.

ignited the surface of the cones will be covered with flames and the sawdust will burn furiously.


The supply of sawdust may be regulated by slides in the chutes. It is not necessary to use a firebar, simply fill up with the fuel and let it burn. To bank the fire at night fill the furnace well up to the top with the sawdust and level it off, close all doors and the damper and let it alone.

A threshing outfit equipped with a system of electric lights enables an Ohio thresherman to work till 10 p. m. during the busy season. The engine supplies the power for the dynamo and the lamps are attached to the separator.

If you want any machine or device and do not know where to get it, write us. Information free.

ANOTHER SAFE RAIL GRIP

The illustration shows a rail grab made by F. A. Crans of 207 Williams St., Waverly, N. Y., and used by Mr. Foley, wrecking foreman of the Lehigh Valley R. R. tool train located at Sayre, Pa. Mr. Foley says of this grip:



Rail Grip

"We are using the rail grab or grip in our wrecking equipment and it is a first-class grip, as it can be used in any place, and will fit any rail from 58 lbs. to 90 lbs. We have two of these grips and we use them very often for a stop to put ahead of our steam crane on the rail at the end of the track to keep the crane from moving when we have a hard end pull."

Anyone wishing details of construction of this grip may secure them by writing Mr. Crans.

REPAIRING A CRACKED WATER JACKET

A cracked water jacket in a gas engine is a common trouble. Often cylinders and cylinder heads that could easily have been repaired are consigned to the scrap pile on this account.

In repairing, when the crack is rather open, it is best to use a piece of sheet copper for the patch, as it can be hammered into almost any shape easily. The edges should be caulked to make them watertight, though sheet asbestos may be used as packing. The patch is best fastened on with small screws along the edges and not over an inch apart.

Small cracks may be repaired by forcing in solder with a blowpipe, or by driving a sharp-cornered cold chisel along the crack, making it wider and deeper near the outside, then pounding in a piece of lead wire or a narrow strip of lead and the job is done.—Contributed by Royal Wolfe, 915 S. Broadway, Lancaster, O.

We are always glad to receive contributions to this department from our readers. Make your story concise but plain.

SOME ELECTRIC PLANT TROUBLES AND WHAT CURED THEM

In an extremely interesting series of articles on "Experience on the Road," H. L. Stephenson, an electrical expert, tells in the Electric Journal some of the things he saw, from which the following are selected:

A RUNAWAY ENGINE.

A recent case of trouble with an engine will serve to illustrate the point. This particular engine was a small, high speed, piston-valve type, direct connected to a 75 kw. lighting machine to be driven at 270 r. p. m. When this outfit was started and the engine given full steam pressure, the first speed would probably be 276, and as quickly as another could be taken, 281, then 287, 293, 297, 301, 310, continuing to creep up slowly. With any load from ten kw. up, the speed regulation was very good, but whenever the load was thrown off, the speed would begin to creep. We ran it throttled until all of its parts had reached an even temperature, but with no better results. The engine-man then took out the valve to look for steam leaks but it seemed to be in good condition and a trial showed that we had not improved it. An improvised device showed that the governor did its work so that it looked reasonable to believe, despite our indicator cards, that there must be some error in the valve setting. This was checked over, and the piston was taken out and examined. We took cards until there was no more paper to fit the indicator. And so it went for three or four days, until we got hold of the theoretical curve such as engine builders send out as a sort of an advertisement.

In comparing the card with one of our no-load curves the trouble was as apparent as though it had been printed in words across the paper. The valve leaked steam. Taking the valve out for the second time, we peined the inside of the rings to spread them out thereby increasing their pressure against the walls of the steam chest. We had solved the problem, for engines are not made that run better than this one now does.

A TRANSFORMER FIRE.

A telegraphic request, "Trouble with new transformer, send man at once," took the writer off once on an eighteen-hour trip. The customer had installed this unit and on putting it into service it gave entire satisfaction, but in two or three hours some one noticed smoke pouring from the transformer

house in such volumes that it was thought the whole building was on fire. An investigation showed that it was only the new transformer and a careful examination revealed nothing further than that the smoke came from the grease and dirt burning on two of its low tension terminals, which from all appearances had reached a temperature far above 100 degrees centigrade. The attendants were at a loss to account for this as these terminals were joined together by a short copper strap and were therefore necessarily at the same voltage and, of course, there could be no heating on account of a slight leakage of current jumping from one to the other. This transformer was of that type designed to give either 110 or 220 volts on the low tension side, and as it was operated on the latter voltage, this copper strap put the two windings in series. The reader can imagine the chagrin of the attendants when the trouble was remedied by sand papering this strap and the terminals and screwing up the bolts tight enough to make a good contact for carrying the current. As this transformer was run with a load very close to its rated capacity, we afterwards took the precaution to insert an additional jumper.

A TIME-HONORED TROUBLE.

A paper of this kind would not be complete without mentioning some experience with the series fields of compound machines. Tell a roadman that a motor's speed is not right or that a generator will not hold up its voltage and the first thing that comes to his mind is the series field. This seems a simple thing, but any one with road experience can cite a number of cases where trouble was due to wrong connections on this part of the machine. It is not at all uncommon to find machines that have been run so long at an excessive speed to keep up the voltage at full-load, that the proper pulleys have been lost and when the trouble is discovered it takes a month or two before the change can be made and the generator belted properly.


Alternating-current apparatus is not altogether free from this same trouble. A good example comes to mind in the case of a composite wound generator which had been in service for two years, but only at the end of that time did it begin to receive anywhere near its rated load. A complaint was made that this machine would not hold up its voltage with the separately excited field having a drop of 110 volts direct current. As the reported full-load voltage was not excessively low we concluded that a bad

power-factor was responsible for some of it and with that end in view an elaborate test was arranged to be taken in the presence of the officials of the power company. The engineer who went to the plant discovered that in all probability during the two years they had been running, the self-excited coils had been bucking against the separately excited winding and reversing this—well, the truth is, we do not care to hurt the feelings of any one by commenting on things of this sort. Reversing this cured the trouble.

HOW TO MAKE AND USE A CYLINDRICAL SQUARE

In sawing off square a piece of metal tube or rod in the vice a round-square is needed, and the box square can be converted into one in the following way:

A thin flexible steel blade and a small cheese-headed screw will be required. Referring to the left-hand sketch, the blade A must be parallel its whole length. Cut slots BB directly in line with each other and at



A CYLINDRICAL SQUARE.

right angles to either edge of the square. In the right-hand sketch at C it will be observed that this slot tapers towards the edge. This is to bring the blade close to the work being marked off, says the Model Engineer, London. The marking is accomplished by drawing the blade around the work into the slot in the opposite side and scribing off.


WEIGHT OF LEAD PIPE

The weight of lead pipe of any thickness and diameter may be determined by subtracting the square of the internal diameter of the pipe from the square of the external diameter (both in inches) and multiplying the remainder by 3.86. The result will be the weight in pounds per running foot.

HOW TO BUILD A CHEAP WATER WHEEL

The wheel should be made of good hard pine and the dimensions given are for a wheel 10 ft. in diameter and 4 ft. wide, but a wheel of any size can be made in the same way and in proportion, says a correspondent of the Blacksmith and Wheelwright.

Gain eight pieces of joist 2 x 6 in. by 8 ft. long as shown at G, Fig. 1, and put them together in pairs (A A and B B, Fig. 2). Bolt the two pairs together, making eight spokes or arms, and forming one side of the wheel. Against the offset or depression of 2 in. at the end of every second spoke on each side, fit a piece 2 x 6 x 42 in. long, made




as shown in Fig. 4. This will make the spokes 4 x 6 in. Between each piece and its spoke, near the ends, gain in as at C, Fig. 2, for the standards for the buckets. E, Fig. 3, indicates the standards for the buckets. They should be 2 x 4 x 16 in., tapered, and bolted clear through as shown. The faces of the spokes at this stage will all be level. To the outside as at E, Fig. 3, bolt a cast-iron plate 18 in. in diameter. This plate should have a hub H, of about 4 in. on the outside for set screws or keyway for fastening it to the shaft, and a short hub on the inside to go into the wood. Have the shaft about 3 in. in diameter and the buckets about 10 in. deep, 10 in. on the bottom and 4 ft. long.

The other side of the bucket is made in exactly the same way and the parts then put together.

CEMENT REQUIRED FOR SURFACING

The following table gives the amount of cement and sand required in several instances. From this table one can readily estimate other areas as may be required.

Bbbs. of Cement.	Bbbs. of Sand.	Thickness of Coating.	Area Covered in Sq. Ft.
1	1	1 inch	67
1	1	$\frac{3}{4}$ inch	90
1	1	$\frac{1}{2}$ inch	134
1	2	1 inch	104
1	2	$\frac{3}{4}$ inch	139
1	2	$\frac{1}{2}$ inch	208
1	3	1 inch	140
1	3	$\frac{3}{4}$ inch	187
1	3	$\frac{1}{2}$ inch	280



MAKE THE SAW FIT THE WORK

"The right thing to do with any sawing machine is to use the smallest saw possible for the work." This is the deduction made by J. Crow Taylor in the Wood-Worker, after recounting how a man running a saw mill, thinking that there was no use in running a 16-in. saw for cutting a 1-in. board, cut down a number of thin and unsatisfactory 16-in. edger saws to 12 in. and secured excellent results, as well as saving power. By reducing the diameter of the saws, they were stiffened, and the volume of saw blade in the cut being reduced, a thinner saw could be run, with the same results produced with a bigger and thicker saw, requiring more power. Large collars are recommended for all kinds of circular sawing machines, also.

TO KEEP SHOW WINDOWS FROM SWEATING

If the window has no partition between it and the store room, make one of ceiling boards or of glass. Glass is preferable. (See





Fig. 1, plan view.) In a window of ordinary size make three openings 4 or 5 by 12 in. Case these up tightly with galvanized iron or wood. A good way, says a correspondent of the Metal Worker, is to put in galvanized iron, then on top of the floor on the inside over the whole tack a piece of $\frac{1}{4}$ -in. mesh wire screen, using small staples to




fasten it with. Fig. 2 is a sectional elevation. If this method is followed there will be no further trouble from sweating.

In lacing belts the pointed ends of the laces may be stiffened and made easier to insert by burning them.

IMPROVED EMERGENCY BOILER FEED

In regard to the emergency boiler feed described in our July number, A. G. Knight, of La Salle, Ill., writes as follows:

"I understand the emergency boiler feed was like the accompanying sketch. In place of the funnel on top of the pipe, the party could have run a pipe, as shown by dotted line and supplied with a valve; he could have poured the water into the tub on the floor. When the two valves connecting his apparatus to the boiler were closed the steam in the big pipe would condense, causing a partial vacuum. Then on opening the



valve to the tub the water would be forced up into the large pipe by atmospheric pressure."


HEATING IRON IN COLD WATER

A lead-lined glass or porcelain vase or cupola filled with acidified water, to which is connected a strong positive conductor and a pair of tongs with insulated handles attached to a flexible negative conductor will constitute the forge and furnace of the future, declares Science and Art of Mining. Into the sour water the smith plunges his piece of iron, manipulating it with a pair of insulated tongs. The water is agitated with a boiling motion immediately, and the great resistance created brings the iron first to red, then to white heat and so quickly that that portion of the iron not immersed is but slightly warmed.

Is there anything you want but don't know where to get it? Write Popular Mechanics. Information free.

SIMPLE METHOD OF DRAWING AN ELLIPSE

An ellipse is a figure that is incorrectly drawn more often than any other geometrical design. A simple way of developing and laying out an ellipse is shown in the illustration. As all ellipses have two diameters, viz: major and minor, it is necessary to know these two points before one can be drawn.



To Draw an Ellipse

Describe a circle with the length of the major axes A B of the ellipse for its diameter; then describe another circle, using the same center as the first circle and having for its diameter the length of the minor axes C D.

Divide the circle in any number of equal parts—the more, the easier to draw and the more perfect the figure will be. The figure in the illustration is divided by twelve lines passing through the center. Draw lightly the perpendiculars, using the points of intersection on the outer circle marked "e," then the horizontal lines indicated "f." By then connecting the first points of intersection, e and f, as shown in the sketch, a perfect ellipse will result.

Any ellipse may be drawn in this way and it saves the trouble of making the tram-mel and guider that are so commonly used.—Contributed by Jos. E. Stanton, Los Angeles, Cal.

FLEXIBLE VARNISH


This varnish is sometimes called "balloon varnish." Boil together 2 gal. linseed oil, 6 oz. copperas, 6 oz. sugar of lead and 1 lb. litharge, stirring constantly. When it strings well, remove from fire and when cold, thin, if necessary, with drying oil.

METHOD OF PROTECTING WATER PIPES FROM FREEZING

To properly protect pipes is perhaps a little expensive, but the extra expense will save greater expense in the long run, says the Rural New Yorker.

Make a 4-in. pipe of heavy galvanized iron in sections like stove pipe, each section made to slip over the next. In every second section run four copper wires through holes in the pipe on four sides and opposite to each other. Solder the wire on the outside and solder the holes up tight. As each section is put on over the water pipe fasten the wires so that the water pipe is in the middle of the galvanized pipe. If it is not possible to disconnect the water pipe in order to slip the protection pipe over it, crimp and fasten at the top and bottom with small short stove bolts, having the screw heads on the outside. Put the boards on as shown in the diagram. Be sure to always break the joints. Leave the pipes bare.

In the diagram, A, is water pipe, W, wires for holding pipe in the center, the circle represents the 4-in. galvanized iron pipe, and the rest are 1-in. boards carefully trued. Put two thicknesses of paper under each



Protecting Water Pipes


joint to act as an air-tight washer. X represents dead air spaces and Y inner dead air space.

Do not let the water run in the hope of preventing freezing, unless the supply is from a windmill. On very cold nights set a lamp in the box to heat the air. Have the chimney of the lamp of tin 8 or 10 in. long, and fit it tightly through a hole in a piece of tin under the box. Use a 1/2-in. wick.

This plan was tried on a 60-ft. standpipe under a tank and a 32 ft. pipe each 1½-in. diameter, and was found to work to perfection

SIMPLE HIGH AND LOW WATER ALARM

A high and low water alarm that is exceedingly simple and wholly dependable is designed for use at the top of the boiler. The bell is installed and connected up as shown



High and Low Water Alarm

In the illustration. Contact is provided for by a rod of very small diameter attached to a float. The packing, says the Engineer's Review, is soaked in oil and ground graphite so there is the minimum of friction on the rod.

HOW TO WIND A SINGLE CYLINDER MOTOR

To wind a single cylinder motor, using three and four terminal coils, connect the primary wires to the end binding posts, and always have the secondary on top of the coil. The Motor Age gives a number of diagrams showing the arrangement for several numbers of terminal coils.


Fig. 1 represents a five-terminal coil, with two sets of batteries and but one secondary terminal. A wire is shown connected to the circuit breaker cam, but in making the connections this wire is always grounded on the engine. Fig. 2 shows a six-terminal coil, the primary being connected as in Fig. 1, and the extra secondary is grounded to the motor. Fig. 3 is a three-terminal coil, Fig. 4 a four-terminal coil, and Fig. 5 is another way to connect the coil of Fig. 4. These diagrams represent the usual methods of connecting coils with terminals from three to six.

MATCHES FOR CUTTING GAGE GLASSES

The easiest method of cutting gage glasses is with red-headed matches. Measure off the glass, wet the head of a match thoroughly, and with it mark a circle on the inside of the glass at the point where it is to be cut. Strike another match, hold it on the outside of the glass under the marked circle and the glass will break off with smooth edges at the point marked. The trick can be done with but one match, says a correspondent of Power, and is so simple and easy that a gage cutter is wholly unnecessary. If you cannot reach far enough into the glass the first time, make a second cut.

GRADE THE STEAM PIPE


The steam pipe should be graded from the boiler towards the engine, says the Practical Engineer, because the water of condensation can move in no direction save along with the steam. Provision for catching or disposing of this water should be made at the engine.



Winding a Single Cylinder Motor

SUBSTITUTE FOR AUTO STARTER

We recently had an auto starter for a 50-hp. three-phase induction motor burn out and were badly in need of motor, but could not use same on account of large starting



Auto Starter Substitute

current and our small generating capacity, writes H. H. Cloyd, of Trenton, Mo.

The transformers for this motor were located close by and with the use of two D. P. D. T. switches I made the transformers take the place of the starter by cutting the starting voltage from 200 to 100 volts at transformers' terminals. With this voltage the motor started with very little jerk on our line and with about 60 per cent of its

rated load. The enclosed rough sketch will show use of switches.

One 4-pole D. T. switch would be much better, as with the two D. P. D. T. switches both must be thrown at the same time. This will also apply to any two-phase motor, also three-phase and three transformers, provided another switch is added.

Referring to sketch, when the switches are thrown downward the secondary coils of the transformers are in multiple, giving the motor 100 volts starting current. Throwing switches upward simply short circuits two middle transformers' leads, throwing secondary coils in series, giving motor 200 volts, or its rated voltage. The upper switch terminals act simply as single pole switches.


This idea, though not always practical, might be of some good if any one were caught as we were without immediate means of repairs.

SIMPLE BABBITT LADLE

When rebabbitting stern bearings, or any time I need a ladle, I take a piece of 2-in. gas pipe, 18 in. long and put an elbow on one end and the ladle is made. To make the metal run readily take a good chisel and dig a trench through the threads on the elbow.—Contributed by E. S. Stout (marine engineer), San Pedro, Cal.

HEATING SYSTEM

The system of piping shown in the illustration used in connection with a small laundry or tank heater is suitable for heating a stable, small conservatory or a chicken house. The system is cheap and simple to rig up, says Domestic Engineering. The illustration explains the connections and most of the materials can be picked up at home.



Heating System for a Stable or Greenhouse

CHEMISTRY FOR MECHANICS

By M. G. KOPF

This is the second of a series of short lessons on practical chemistry, particularly adapted to the mechanic. The professional chemist is now considered indispensable in the larger manufacturing industries. We have the iron smelter sending samples of iron to the chemist, to be analyzed, so that he will be able to grade it as regards strength and purity. We have the food chemist, constantly in watch of our health. There is the agricultural chemist transforming arid deserts and wastes into productive farms and fields. In the shops we wonder why one tool breaks sooner than another, why some oils are better than others. We cannot all be chemists, but every one may easily obtain some knowledge of the science in its immediate relation to the things which are closely connected with his every-day work. These articles will all be written in plain simple language "so you can understand it."—Editor's Note.


PART II.

The following articles will be needed: A fish tail burner (25 cents); a few feet of $\frac{1}{8}$ -in. soft glass tubing (about 2 cents per ft.); a few inches of copper wire; a pound of nitric acid (6 cents); a few ounces of copper sulphate (blue vitriol, 5 cents); a $1\frac{1}{2}$ to 2-in. glass funnel (10 cents); a package of 9 c. m. filter papers (10 cents); a wire gauze (10 cents); and a ring stand with three rings (65 cents).

HOW TO BEND GLASS TUBING.

Cut two pieces of tubing 6 in. long, and three pieces 12 in. in length. Place the fish tail burner on the bunsen burner and turn

withdraw it quickly from the flame and bend it just as one would bend a small copper wire. There are several things to be observed when bending glass tubing and these are, that the tube is hot enough; that it is evenly heated; that it is constantly rotated, so as to heat it evenly; that about one to two inches of the tubing is heated; that, after hot enough, the tube be bent quickly, and finally that the bend be allowed to cool slowly. To procure a slow cooling the bends should be held in the upper part of the luminous flame until a black deposit of soot covers it. This deposit will protect the tubing from the cold air and allow it to cool slowly and thus obtain good anneal-



Bending Glass Tubes

the draft to give a luminous flame. Tubing having thin walls should be bent with a luminous flame, but tubing of hard glass and having heavy walls should be bent with the non-luminous flame. Take one of the 6-in. pieces of tubing and hold it in the flame, rotating constantly, so that the central portion is heated. When the tubing becomes soft and has a tendency to bend,

ing. If the tubing were not heated evenly or if it were heated in one spot (as would be the case with the ordinary flame of the bunsen burner) a kinked bend would result (See Fig. 1). Heating the tube evenly and bending rapidly gives a bend as shown in Fig. 2. Observing the various points above and practising a little will bring success in glass tube working. Having bent a tube

as shown in Fig. 2, bend the remaining pieces according to the Figs. 3, 4, 5 and 6. Preserve these tubes for future use.

ELEMENTS.

Chemists have agreed to adopt certain symbols denoting the atoms or particles of the various elementary forms of matter. These elementary forms of matter are called "Elements," and they are substances that cannot be decomposed, i. e., they cannot be separated into any simpler substances. The elementary substances were given names denoting, in a number of cases, a peculiar property of that element; and in other cases they were named from the city in which they were discovered, or from the discoverer, and so on. The symbols are taken from the first or initial letter of the ordinary name of the element. For example, Boron, B; Carbon, C; Iodine, I; etc., etc. In a number of cases the symbol comes from the initial letter of the Latin name for the element. For example, Antimony, Sb, from Stibium; Iron, Fe, from Ferrum; etc., etc. When only one element is known, whose name begins with a certain letter, that letter is used as the symbol, but when two or more are known, the names of which begin with the same letter, that one best known or first discovered is generally designated by the letter, while the others are designated by the first two letters or by the first and third letters and so on, e. g., Carbon, C; Chlorine, Cl; Calcium, Ca; etc. In the table shown, the name of the element, its symbol, its discoverer, date of discovery and physical state is given. These elements, with their symbols, should be memorized as they are used.

COMPOUNDS AND MIXTURES.

A compound is a combination of two or more elements chemically united in *definite* proportions.

A mixture is a combination of two or more elements in any proportions, the resulting substance still retaining the properties of its constituents.

In a chemical combination the substance resulting from the combination has properties entirely different from the original constituents.

Powder a piece of marble and put a little in a test tube. Add enough water to half fill the test tube. Heat with the bunsen burner for a moment or two and then filter into a test tube. The heating should be done carefully and the test tube shaken so as to slowly and thoroughly heat the liquid. To filter take one of the filter papers and fold

ELEMENTS AND SYMBOLS.

Element	Symbol	Discovery	State
Aluminum	Al. ⁱⁱⁱ	Wohler, 1828	Solid
Antimony	Sb. ⁱⁱⁱ	Valentine, 1460	Solid
Arsenic	As. ⁱⁱⁱ	Schroeder, 1694	Solid
Barium	Ba. ⁱⁱ	Davy, 1808	Solid
Bismuth	Bi. ⁱⁱⁱ	Agricola, 1529	Solid
Boron	B. ⁱⁱⁱ	Davy, 1807	Solid
Bromine	Br. ⁱ	Balard, 1826	Liquid
Cadmium	Cd. ⁱⁱ	Stromeyer, 1817	Solid
Calcium	Ca. ⁱⁱ	Davy, 1808	Solid
Carbon	C. ^{iv}	Ancients	Solid
Chlorine	Cl. ⁱ	Scheele, 1774	Gas
Chromium	Cr. ^{iv}	Vanquelin, 1797	Solid
Cobalt	Co. ^{ii, iv}	Brant, 1733	Solid
Copper	Cu. ⁱⁱ	Ancients	Solid
Fluorine	F. ⁱ	Knox, 1836	Gas
Gold	Au. ^{i, iii}	Ancients	Solid
HYDROGEN	H. ⁱ	Cavendish, 1766	Gas
Iodine	I. ⁱ	Courtois, 1811	Solid
Iron	Fe. ^{ii, iv}	Ancients	Solid
Lead	Pb. ⁱⁱ	Ancients	Solid
Lithium	Li. ⁱ	Davy, 1818	Solid
Magnesium	Mg. ⁱⁱ	Bussy, 1830	Solid
Manganese	Mn. ⁱⁱ	Galm, 1774	Solid
Mercury	Hg. ⁱⁱ	Ancients	Liquid
Nickel	Ni. ⁱⁱ	Cronstadt, 1751	Solid
Nitrogen	N. ⁱⁱⁱ	Rutherford, 1772	Gas
OXYGEN	O. ⁱⁱ	Priestly, 1774	Gas
Phosphorus	P. ^{i, iii}	Brand, 1669	Solid
Platinum	Pt. ^{ii, iv}	Wood, 1741	Solid
Potassium	K. ⁱ	Davy, 1807	Solid
Selenium	Se. ⁱⁱ	Berzelius, 1817	Solid
Silicon	Si. ^{iv}	Berzelius, 1823	Solid
Silver	Ag. ⁱ	Ancients	Solid
Sodium	Na. ⁱ	Davy, 1807	Solid
Strontium	Sr. ⁱⁱ	Davy, 1807	Solid
Sulphur	S. ⁱⁱ	Ancients	Solid
Tin	Sn. ⁱⁱ	Ancients	Solid
Zinc	Zn. ⁱⁱ	Paracelsus, 16—	Solid

it through the center; then fold again at right angles to the first, which leaves the paper in the form of a section of a circle; now, by inserting the apex of the section into the glass funnel, the paper may be opened out in the form of a cone that will closely fit the funnel. It is best to wet the paper before filtering. After filtering the solution above you will have a white substance remaining on the paper and a clear liquid in the test tube. The white substance is known as the *residue* and the clear liquid as the *filtrate*. Taste the filtrate. Put a small amount in an evaporating dish and evaporate to dryness. To evaporate place the wire gauze on a medium ring and fix the ring on the ring stand high enough to allow the bunsen burner to be put under it. Place the evaporating dish on the

gauze and heat. On evaporating nothing is left. On tasting the filtrate it does not taste much different than ordinary water. These then show that there is no change and that marble and water form a simple mixture and do not combine to form a compound. Next add some salt and marble to a test tube half full of water and repeat the above operation. The taste of the liquid is salty and on evaporating we have a substance left which, on tasting, is found to be salt. This shows that salt is soluble in water and that a mixture has formed since the liquid has the property of its constituents, and also since no new substance has formed. Is this last experiment a chemical or physical change?

Add next, to a small piece of copper foil or wire in a test tube, a few drops of nitric acid (HNO_3). Warm a little and when you have a solution, evaporate it just to dryness. A bluish green substance is obtained. When the copper is acted upon by the HNO_3 a green solution results and reddish brown fumes are given off. The residue in the evaporating dish is different than copper (Cu), it is copper nitrate [$\text{Cu}(\text{NO}_3)_2$]. This then is a substance entirely different than Cu or HNO_3 and therefore a compound of HNO_3 and Cu has formed. Chemical or physical change? Is blue vitriol a mixture or a compound? Blue vitriol (CuSO_4) is a

compound because it is made from definite proportions of Cu and SO_4 , and because it has different properties than either Cu , S , or O .


THREE STATES OF MATTER.

Matter exists in three forms; viz., Solid, Liquids, and Gases.

Fill a test tube $\frac{1}{3}$ full of sulphur and gently apply heat, noticing the change in appearance of the sulphur as the temperature increases. Increase the heat until the sulphur boils. When we begin we have a solid; after heating, a liquid, and we find that on the sides, near the top, sulphur condenses in yellow drops. There must then be something besides a solid and liquid and this must be a gas. We have then the three states of matter illustrated in this simple experiment. Repeat the above experiment, using a small piece of camphor instead of sulphur.

Solids do not readily change their form. Liquids do readily change their form. Gases always tend to expand and change their form.

In the next part we will take up Distillation, Crystallization and Oxygen, with a study of the flame of a bunsen burner and the changes that take place in a coal stove, introducing how to write formulas and equations.



French Flag-Ship "Jaureguiberry"

The flagship of the French squadron, the "Jaureguiberry," was launched in 1893 and is of 11,324 tons. Her armament consists


of two 12-in. guns, two 8-in. guns and twenty-four quick-firers of various calibres. Her maximum speed is 18.10 knots.

MECHANICS FOR YOUNG AMERICA

HOW TO BUILD AN ELECTRIC ENGINE

This engine, if carefully made, presents a neat appearance and is capable of running toy machinery on very low current strength—the one I made ran satisfactorily on 1½ amperes.

The coils may be those of an old electric bell, mounted on a light piece of angle-iron, at a height of not more than one inch from the baseboard. The fly-wheel standard,



Simple Electric Engine

crank-rod and armature may be made out of galvanized iron, No. 16 being most suitable. A small valve-wheel makes a very good fly-wheel, but care must be taken in mounting it upon the shaft, for if the shaft is not in the center the engine will not run smoothly.

Make the shaft to extend on each side of the two bearings, so that the commutator may be attached to one side and so the other side may be bent into the form of a crank. On the commutator side place a brush in such position that during every revolution the circuit will be alternately opened and closed. Arrange the commutator so that the circuit will be closed either when the handle is at the top or when it is at the bottom, which makes no difference, except for the direction in which the engine will run.

Let us suppose that the crank is pointed downward. The circuit is now closed by the commutator and the armature is attracted by the electro-magnet, but, as it approaches the magnet, the circuit is broken and the fly-wheel pulls it back again, only to be attracted when the circuit is again closed.

By adjusting the commutator, several different speeds may be obtained, as well as reversing the engine accomplished, which is done by placing the crank so that it points


upward, then twisting the commutator around so that the circuit is closed.—Contributed by Warren B. Weyrick, 4 Russell Ave., Akron, O.

NOVEL ELECTRIC MOTOR

The materials necessary to make this motor are an old electric bell of the "buzzer" type and a cog-wheel from an old clock.

Remove the hammer-head and gong from the bell, then bend the end of the hammer into a loop, as in Fig. 1. Now make a little wire catch like Fig. 2, and fasten its loop into the loop of the hammer. Mount the bell on a small board as in Fig. 3 and fasten the cog-wheel almost on a line with it. Now press down the hammer and place a nail in the position shown in the diagram so that the catch touches one of the teeth.

Fasten the board in an upright position and attach two dry batteries to the binding



Novel Electric Motor

posts. If properly connected, the fly-wheel will turn quite rapidly and with amazing force for so small a machine. The machine, however, has a fixed direction as shown by the arrow, but the belting can be arranged so as to send the models in a reversed direction if required. The materials for the motor should not cost more than 25c for the bell and if you have an old bell it will cost next to nothing.—Contributed by Fred C. Curry, Brockville, Ontario.

HOW TO MAKE A SAILOMOBILE

By Frank Mulford, Shiloh, N. J.

I had read of the beach automobiles used on the Florida coast; they were like an ice boat with a sail, except they had wheels instead of runners. So I set to work to make something to take me over the country roads.

I found and used seven fence pickets for the frame work, and other things as they were needed. I spliced two rake handles together for the mast, winding



Photograph by Mrs. C. J. Lupton, Shiloh, N. J.

Sailomobile Built by Frank Mulford

the ends where they came together with wire. A single piece would be better if you can get one long enough. The gaff, which is the stick to which the upper end of the sail is fastened, is a broomstick. The boom, the stick at the bottom of the sail, was made of a rake handle with a broomstick spliced to make it long enough. Mother let me have a sheet, which I put down on the floor and cut in the shape of a main-sail. The wind was the cheapest power to be found, thus it was utilized; the three wheels were cast-off bicycle wheels.


I steer with the front wheel, which was the front wheel of an old bicycle with the fork left on. The axle between the rear wheels is an iron bar which cost me 15 cents, and the pulley which raises and lowers the sail cost 5 cents. Twenty cents was all I spent, all the rest I found.

A saw, hammer, and brace and bit were the tools used. Slats made the seat and a cushion from the house made it comfortable, and in a week everything was ready for sailing.

Once it was started with only my little cousin in it and I had to run fast to catch up.

HOW TO MAKE A NOVEL BURGLAR ALARM

The only materials required for this device are a small block of wood, two screws, some copper wire, an old spring, an electric bell, a dry battery and a one-point switch.



The illustrations show how these parts are put together and the letters used indicate as follows:

A and G, screws; B, old mouse trap spring; C, anchor for spring; D, wire to hold F back at night, or when alarm is set; E, copper wire running from G to bell; F, straight part of spring which, when released from D, completes the circuit; H, same as E, but connected at G; I, electric bell; J, dry battery; K, a one-point switch to be set on only when burglar alarm is set, otherwise bell will ring all the time; L, base for the alarm.


Fig. 1 shows the screws and spring arranged on the base; Fig. 2 shows the position of the wooden base above the door, and shows a complete plan of the wiring.—Contributed by Harry A. Peshon, 333 Cherry St., San Francisco, Cal.

SIMPLE X-RAY EXPERIMENT

The outlines of the bones of the hand may be seen by holding a piece of rice paper before the eyes and placing the spare hand about 12 in. back of the rice paper and before a bright light. The bony structure will be clearly distinguishable.—Contributed by G. J. Tress, 126 Centre Ave., Emsworth, Pa.

TO BUILD A MERRY-GO-ROUND

This is a very simple device, but one that will afford any amount of amusement. The center post rests in an auger hole bored in an old stump or in a post set in the ground. The stump makes the best support. The



Home-Made Merry-Go-Round

center pole should be 10 ft. high. An old wheel is mounted at the top of the pole, and the pole works in the wheel as an axle, says the American Boy. The wheel is anchored out by several guy wires. The seat arms may be any length desired. A passenger rides in each seat and the motor-man takes his station at the middle.

BOOKS OF TABLES. BOOKS OF RECEIPTS

ROPP'S NEW CALCULATOR. 200 pages. Actual size, 5½x9½ inches. Cloth. Price, \$1.50. Pocket size, \$1.00. Sustains the same relation to the commercial world that the new Century Dictionary does to the literary world. Fully abreast with



the age of air ships, submarine boats and wireless telegraphy. Designed for and adapted to the particular wants of bankers, accountants, mechanics, farmers, manufacturers, merchants, miners, etc., etc., and must prove of incalculable value to them—unless the book itself can calculate its own worth—for it calculates almost everything that is calculable.

QUESTIONS AND ANSWERS. Based upon the Standard Code of Train Rules. By G. E. Collingwood, Ed. Revised edition. 80 pages. Diagrams. Cloth. Price, \$1. Intended for use in the examination of trainmen. The general rules, train rules, train orders, and the whole handling of trains is set forth in so simple and at the same time comprehensive manner that a careful reading of the book will fit any one with sufficient knowledge to meet any contingency that may arise in the conduct of a train. Endorsed by high railway officials from all sections of the country. Every transportation man should have a copy.

FERRIC AND HELIOGRAPHIC PROCESS: A Handbook for Photographers, Draughtsmen and Sun Printers. By George E. Brown. 149 pages. Diagrams. Cloth. Price, \$1. For architects, surveyors, draughtsmen, engineers and others who find the reproduction of tracings a matter of everyday necessity. It embraces: The ferro-prussiate process, toning blue prints, uses of blue prints; ferro-prussiate in tri-color work; the kallitype process; the Oberretter process; the wranotype process; prints on fabrics, prints in dyes; heliographic processes compared; preparation of heliographic papers, making tracings for sun-copying; outfit for heliographic printing; ferro-prussiate or white line on blue ground; pellet or blue line on white ground; ferro-gallie, or black line on white ground; brown line on white ground; minor heliographic processes. A comprehensive little bibliography at the end of the volume and an index add greatly to its value and interest.

THE LOCOMOTIVE UP TO DATE. By Charles McShane. 736 pages. 380 illustrations. Cloth. Price, \$2.50. Covers the whole range of locomotive construction and management down to the present day, including its latest development and all modern appliances, together with a classification and comparison of all kinds of locomotives, both simple and compound. It is a book culled from the mechanical books and papers of the world and so contains all the really valuable information to be found in a complete mechanical library. Every subject is fully illustrated and the descriptions given of all new devices were prepared by the inventors themselves. The contents include: Compound locomotives; combustion; air brake; breakdowns; locating blows and pounds; incrustation; injectors; inspirators and boiler checks; slide valves; valve gears; errors by the link motion; locomotive valve setting; steam indicator; modern locomotives; extraordinary fast runs; lubricators; metallic packings; general information; locomotive construction-erecting department; machine work; metric system; steam and air gauges; compressed air; modern counter-balancing and the history of the locomotive.

ONE THOUSAND POINTERS for Machinists and Engineers. By Charles McShane. 342 pages. 187 illustrations. Cloth. Price, \$1.50. Includes articles from the best authorities on each subject.

Embraces the most modern and approved practice in the construction, care and economical management of the locomotive. Written in plain language and condensed form, no mathematical demonstrations being given or required.

JOHNSON'S HANDY MANUAL. Price, \$1. An authority on steam, hot-water heating and ventilating, plumbing and gas fitting. A valuable reference book for architects, those in pipe trades, engineers, janitors and those intending to install or alter heating or plumbing systems. All kinds of measurements arranged in tables. Fully illustrated with cuts and complete working plans.

FIFTY-CENT SERIES

HANDICRAFT SERIES—A Series of Practical Manuals. Edited by Paul N. Hasluck. Price, each, 50c.

BOOT-MAKING AND MENDING Including repairing, lasting and finishing. Illustrated. 179 engravings and diagrams. Price, 50c. Contents: Repairing heels and half-soleing; patching boots and shoes; re-welting and re-soleing; boot-making; lasting the upper; sewing and stitching; making the heel; knitting and finishing; making riveted boots and shoes.

Others of the set are:

HOUSE DECORATION. Price, 50c.

HOW TO WRITE SIGNS, TICKETS AND POSTERS. Price, 50c.

WOOD FINISHING. Price 50c.

DYNAMOS AND ELECTRIC MOTORS. Price, 50c.

CYCLE BUILDING AND REPAIRING. Price, 50c.

DECORATIVE DESIGNS OF ALL AGES FOR ALL PURPOSES. Price, 50c.

MOUNTING AND FRAMING PICTURES. Price, 50c.

SMITH'S WORK. Price, 50c.

GLASS WORKING BY HEAT AND ABRASION. Price, 50c.

BUILDING MODEL BOATS. Price, 50c.

ELECTRIC BELLS: HOW TO MAKE AND FIT THEM. Price, 50c.

BAMBOO WORK. Price, 50c.

TAXIDERM. Price, 50c.

TAILORING. Price, 50c.

PHOTOGRAPHIC CAMERAS AND ACCESSORIES. Price, 50c.

OPTICAL LANTERNS. Price, 50c.

ENGRAVING METALS. Price, 50c.

BASKET WORK. Price, 50c.

BOOKBINDING. Price, 50c.

BENT IRON WORK. Price, 50c.

PHOTOGRAPHY. Price, 50c.

UPHOLSTERY. Price, 50c.

READY SHORTLY.

LEATHER WORKING. Price, 50c.

HARNESS MAKING. Price, 50c.

SADDLERY. Price, 50c.

TECHNICAL INSTRUCTION. Important new series. Edited by Paul N. Hasluck. With numerous illustrations of the text. Each book contains about 160 pages. Crown 8vo. Cloth. Each, \$1.

PRACTICAL DRAUGHTSMAN'S WORK. Price, \$1.

PRACTICAL GASFITTING. Price, \$1.

PRACTICAL STAIRCASE JOINERY. Price, \$1.

PRACTICAL METAL PLATE WORK. Price, \$1.

PRACTICAL GRAINING AND MARBLING. Price, \$1.

OTHER VOLUMES IN PREPARATION.

SPON'S MECHANICS' OWN BOOK. 702 pages. 1420 illustrations. Half leather. Price, \$2.50. General method of treatment of each subject is first, the raw materials worked upon, its characteristics, variations and suitability; secondly, the tools used, the sharpening and use; thirdly, devoted to typical examples of work to be done, materials and how to do similar work. Nearly all of the mechanical trades are here included and some of the professions.



Cartoon in Motor Age Offered as Remedy for Dangers of Automobiling in Suburbs of Chicago, Where Policemen Stop Fast Riding by Shooting Holes in the Tires.

KNOTS AND MILES

There is a growing practice, says the Yachtsman's Guide, of making an improper use of the word knot, not only with landmen, engineers and shipbuilders, but also with those who should know better. The prevailing idea appears to be that a knot is the same as the geographical, nautical or sea mile, and the word knot is used to prevent any possible confusion with the statute land mile. But this is quite wrong. The knot is the cosmopolitan unit of speed, employed at sea by sailors of all civilized nations. One knot is a speed of one nautical mile

the word knot as the equivalent of a length is in tracing the knots on the log line, and then, by a familiar tendency in language, the "distance between two knots" is abbreviated in speech to the "length of knots." By a curious perversity and straining after precision, the incorrect expression "knot an hour," to express the speed of a ship, is creeping into general use, with the effect of displacing the word mile by knot. No real sailor would say that a rock on the land was half a knot, one knot, etc., away. It is too often urged that the expression "knots an hour" is so much clearer and definite; but we might just as well measure pressure in "atmospheres per square inch."

A NEW SECONDARY WINDING OFFER

ONE INCH SPARK, Secondary Winding, FIVE DOLLARS
including sufficient core and magnet wire for the Primary. The spark is fat and vigorous, and suitable for Wireless Telegraphy. This is absolutely the best Coil bargain we have ever offered. We invite correspondence.
NEW ENGLAND COIL WINDING CO., Atlantic, Mass.

an hour, the nautical being the mean sexagesimal minute of latitude on the earth's surface, so that it is 90 x 60—5,400 miles from the equator to the pole, and this is the only mile the sailor knows or uses. The nautical mile is a little over 6,080 feet, the Admiralty measured mile (we do not say the Admiralty knot), so that one knot is a speed of a little more than 100 feet in a minute, more nearly 101 to 102 feet a minute; thus, on a log line, with a half minute glass or interval of time, the distance between the knots should be 50 feet or a little over, say 51 feet.

The word knot is derived from knots on the log line, the number of knots that pass over the ship's taffrail during a half minute or other interval of time, giving the speed of the ship in knots. The only occasion then, on which it is permissible to use

BURGLARS

"James," cried Mrs. Timmid, "there are burglars downstairs."

"Oh, no, there ain't, my dear," replied Mr. Timmid.

"I'm sure there are."

"I'm sure there ain't."

"I tell you there are."

"I tell you there ain't."

"Your husband is right, mum," interposed a low-browed individual who thrust his head into the room at this juncture. "We're upstairs."

And as he started down he was heard to say to his pal, "I always believe in helping a husband out whenever I kin. I'm a married man myself."—Pittsburg Post.



THE IDEAL SIGHT RESTORER

Is Your Sight Failing ?

All refractive errors, muscular trouble and chronic diseases of the Eye successfully treated by scientific MASSAGE.

"I am in my seventy-ninth year, and have the Sight Restorer and yourselves to thank for renewed eye-sight." (Testimonial 177)

"I wish I could impress every one afflicted so they would give the Restorer a trial." (Testimonial 244)

English, German or Spanish pamphlet mailed free. Address
THE IDEAL COMPANY, 239 M Broadway, New York.

THE LATEST—THE BEST

No. 602 "NAPANOCH" POCKET KNIFE TOOL KIT

BEST AMERICAN MAKE.

- No. 1. Leather Pocket Book.
- No. 2. Pocket Knife, length, 3 7-8 in.
- No. 3. Reamer, 3 1-8 in.
- No. 4. File, 4 in.
- No. 5. Saw, 4 in.

PRICE,
COMPLETE,
\$2.25



- No. 6. Chisel, 3 5-8 in.
- No. 7. Screw Driver, 3 3-4 in.

Any tool attached to knife in one second by simple backward wrist movement, and as quickly released.

Price, complete, \$2.25

Ask Dealer or write.

U. J. ULERY, 7 Warren Street, New York City.

WANTED

Engl. eers and all persons running belts, to write on their firm's letter head for liberal free sample prepaid of

"Pulle-Y-Grasp"

for Belts. State kind of belts.

THE CARDINAL MFG. CO.,
Cleveland, Ohio.

The "HANDLE" Rule



FOR TOOL AND DIE WORK.

35 cents each, \$1.00 per set of 4.
Send for circulars.

J. L. LUCAS, 3 Fox St., Bridgeport, Conn.



THE CLIMAX
BLOW TORCH

An improvement over every good quality of the soldering iron. Carries its own heat supply, and burns alcohol, benzine or gasoline. Used extensively by professional and amateur workers. 55 cents, postpaid. Our gas blow torch (bunsen burner with blow pipe attachment) at the same price.
CLIMAX MFG. CO., - 1 Hartford St., Boston

A CUREALL.

[From the Catholic Standard and Times.]

Feelin' pretty blue, you say?

Ha! ha! ha!

Things went wrong with you today?

Ha! ha! ha!

One would think, to see you frown,

All the troubles in the town

Clung to you and weighed you down.

Ha! ha! ha!

Come now, mister, don't get mad.

Ha! ha! ha!

I ain't laughin' cause you're sad,

Ha! ha! ha!

I've had troubles, too, today—

Bad as yours, I'll bet—but, say,

I'm a-drivin' 'em away.

Ha! ha! ha!

Grandest tonic on this earth—

Ha! ha! ha!

Is a steady dose o' mirth.

Ha! ha! ha!

Just you get a strangle hold

On your cares an' knock 'em cold

With a hearty, merry, old

Ha! ha! ha!

Please mention Popular Mechanics when writing Advertisers.

FARMERS--


Protect Your
Stock From

LIGHTNING

SHARP'S

Metal Fence Post

THE BEST INSURANCE
ABSOLUTE PROTECTION



High-Speed Fence Construction—No Staples Required.—No Post Holes to Dig.—Fire-Proof.—Holds any Make of Wire.—Artistic—Strongest Construction.—Low First Cost.—First in Solid Ground Engagement.—Animal and Insect Proof.—Best Proof.—Minimum Shipping and Storing Space.—Adapted for Trolley Poles, Telegraph Poles, Railroad and Farm Fences, Mail Box Sustainers, Government Requirements.—Driven by Hand.—One Tool Only Required for Setting.—Good Stock for Implement Dealers, Lumber Yards, Hardware Stores, etc.—No Depreciation of Stock.

AMERICAN METAL POST

606-612 So. 10th St., OMAHA, NEB.

ESSENTIAL QUALITIES OF A SUCCESSFUL LOCOMOTIVE ENGINEER.

"Three qualities are most essential for an engineer to possess in order to make a success of running an engine: First, a fairly good education; second, a reasonable amount of practical experience as a fireman, three years at least; and third, good judgment." So writes W. J. Hill in an article from which the following is condensed:

Probably the third is the most necessary of the three, as many men who have had the education and the experience, have failed to make a success of running because they lacked good judgment. A fireman frequently has chances of measuring his capacity along this line, by watching the outcome of things which his engineer does, and which at the moment he thinks is wrong or unnecessary. The engineer applies his brake some distance from a fixed signal, or before rounding a curve, or when entering a yard when everything is apparently clear. If he watches the case to the end, he will likely find that the engineer's past experience has taught him the signal is liable to be changed at the last moment; find someone's tail end just around the curve, or a yard engine working down in the yard which may run out in front of him at



Running Water for Irrigation

(Pumps Water by Water Power.)

RIFE AUTOMATIC HYDRAULIC ENGINE

NO ATTENTION.

NO EXPENSE.

RUNS CONTINUOUSLY.

Complete System Extending to Stable, Greenhouse, Lawn, Fountains and Formal Gardens.

Operates under 18 inches to 50 feet fall. Elevates water 30 feet for every foot fall used. Eighty per cent efficiency developed. Over 5,000 plants in successful operation. Large plants for towns, institutions, railroad tanks and irrigation. Catalogue and Estimates Free.

RIFE ENGINE COMPANY

Trinity Building, New York City.

This Shows Our
"Vim"

Butt Spark Magneto


We make other Types for

Butt and
Jump Spark
Ignition

Also

COILS

of all kinds. Write
for prices and full
information



THE TRITT ELECTRIC CO. South Bend, Indiana

any moment. The man with good judgment realizes how many of our wrecks are caused by the failure of yard engines and others to be in to clear, or by tail ends not protected, and he takes precaution accordingly. Frequently men take long chances in order to make the time, but generally the man who does, sooner or later gets caught. Again, good judgment is required in case of a breakdown. A man must think quickly whether the engine can be readily repaired and take in the train, or whether another engine must be sent for, also what must be disconnected or can be left as it is, until the engine is off the main line into a siding.


Read books on mechanical or scientific subjects. Acquire habits of study, and instead of regretting that you did not get a good education when you were young, embrace some of the opportunities which every man has today, through correspondence schools, night schools, or other technical schools. Start at once, so that five years from now you will not still be regretting that you did not enlist in 1905. Get busy, and remember you are never too old to learn if you persevere.

It is not the engineer who makes a successful trip with a good engine, good coal and weather conditions in his favor who displays his ability as an engineer. Any kind of an engineman could do that, but it is the man who can go out on the road and successfully take a train from terminal to terminal with a leaky engine, poor coal and other adverse conditions which are common today, who shows that he is an engineer "of the first water" and entitled to his company's confidence.

Some time ago a magazine sent letters to a number of high railway officials asking them if they gave preference to college graduates in filling vacancies in the various departments. Nearly all the men thus written to replied that they preferred men who had at least a thorough public school training, or, better still, a technical education, owing to the fact that these men had been trained to study; their minds were more active, thus being better fitted for an emergency.

Popular Mechanics for the balance of your life for \$10, or a five year subscription for \$3. Changes in address made upon notification.

IT WILL PAY YOU! THE BOWSER



Handles
All
Grades
and
Kinds
of
Lubricating
Oils

SINGLE SQUARE CABINET

NO WASTE, NO OIL - SOAKED FLOORS

The "OILER" is exactly filled
AT ONE STROKE; there is no
overflow.

Fifty Different Styles. Send for Catalog XII.

S. F. BOWSER & CO., Ft. Wayne, Ind.

CHAIN TOOL

35c


THE HUSKY KIND

SENT PREPAID FOR 45c

THE MOTOR CAR SUPPLY CO.

1427 MICHIGAN AVENUE CHICAGO, ILL.

NEW, READY



"DIVINE" WATER MOTOR

CONNECTS TO ANY FAUCET

GRINDS, POLISHES, BUFFS ANYTHING

Furnishes Power for
Sewing Machines
Small Lathes
Scroll Saws
Dental Lathes and
other small machines

Price, complete, including Emery
Wheel, Pulley Wheel, Buffing or
Polishing Wheel and
Polishing Composition, etc., - - - - - **\$3.50**

1-8 Horse Power or 80 lbs. Pressure

Send us Check, Money Order or C. O. D.

SMITH & HEMENWAY CO., - - 296 Broadway, NEW YORK

IF

you are in the market for any kind of machinery
and don't know where to get it, write : : : : :

POPULAR MECHANICS



Anybody Can Use It

Those cement patches
are constantly coming off
this hot weather. Our
Vulcanizers not only make
patches stay, but will
mend cuts and holes in
outer casings of auto tires
good as new.

GUARANTEED

Let us tell you. Ask for
circular "R."

"STITCH-IN-TIME"
VULCANIZER CO.
TOPEKA, KAN., U. S. A.



To Gas Engine Operators
Dynamo Ignition.
Motzinger Auto-Sparker

No battery to start or run. The original
speed-controlled friction-drive Dynamo.
Driven parallel with engine shaft. No
belts. No beveled pulley or beveled
fly wheel necessary. For make and
break and jump-spark system. Water
and dust proof. FULLY GUARANTEED.
MOTSINGER DEVICE MFG. CO.,
128 Main Street, Pendleton, Ind., U.S.A.

Write
for
32-page
catalog,
FREE.

Faster than an Auto Cheaper than a Horse




GET A MANSON

It is speedy and reliable, adapted
to all roads, and maintained at a
moderate expense. Attachments
designed for leisure and utility

Write us

**Fowler - Manson - Sherman
Cycle Mfg. Co.,**


Clinton and Fulton Sts., Chicago, Ill.



HASTINGS COMPOUND

Guaranteed to stop Sparking. Money refunded if it
don't. Put up in convenient form, 3 3/4 in. long x 1 3/16 in. diam.
We have enough confidence in Hastings Compound, to mail a full
size sample stick, upon receipt of six cents to cover postage.

JAS. L. NEEFUS, Sole Agent
54 DEY STREET, N. Y.




SIMPLE BUT SAFE THE LANCASTER

High and low water and high pressure alarm for steam boilers. Whistles when water is
too high, too low or for high pressure. The floats are made of terra cotta, will not collapse
or fill with water. Will work at any boiler pressure. Sent on approval. You can try it
before you purchase. Mechanical agents wanted everywhere. For full particulars and
descriptive circulars, address

GEORGE LANCASTER, - 541 Lexington Ave. - NEW YORK CITY

Please mention Popular Mechanics when writing Advertisers.

1060



\$100 The New Pierce Gasoline Motor IS A WONDER

It will develop more power on less fuel
than any other make in the world....

Built on modern lines and up to the very latest practice; made from the best material, and with ordinary care will last a life-time.

We have been building Gasoline Motors for over twenty years. More than 12,000 PIERCE MOTORS are in use in all parts of the world. We know how to, and do, build them right, in fact, we


Guarantee Them to Give Satisfaction.
If they do not, send them back and we
will refund your money in full. . . .

The PIERCE MOTORS are the best in the world and cost less than the poorest. We guarantee them against defective material for life. If you want power for any purpose, write for our printed matter, stating your needs. We also build other sizes up to 100 H. P., also Marine Motors, Launches and Auto Boats. Be sure and address

PIERCE ENGINE COMPANY, - Dept. 2, Racine, Wis.
3 1-2 Actual Horse Power

Gasoline Engines and CASTINGS

AUTO, MARINE and STATIONARY



ARE you in the market for Gasoline Engines or Accessories? We conduct a real Bargain Place on these lines. Write us.

Booklet on Request.

L. W. GILLESPIE & COMPANY, MARION, IND.

Gasoline Motors and Castings



A complete line from 1 1/4 to 10 h. p., for Bicycle, Automobile, Marine or Stationary. Also attachable motor outfits and complete MOTOR-CYCLES. Send stamp for catalogue.

STEFFEY MFG. CO.,

2941 Girard Avenue,

Philadelphia, Pa.



TOGO THE MODEST.

A nation called a fighting man,
He didn't say a word.
He listened close to aim and plan,
He didn't say a word.
"Togo," they said, "within your hand
Is held the future of our land."
His nod replied, "I understand."
He didn't say a word.


He climbed aboard his battleship
And didn't say a word,
He found the foes he went to whelp,
And didn't say a word,
But plugged them full of smoking lead
And hammered till the sea turned red,
And when they all were sunk or fled
He didn't say a word.

The battle won, the country saved,
He doesn't say a word.
In lasting fame his name engraved,
He doesn't say a word.
His glorious health the whole world drinks,
He smiles a little, nods and winks,
And, like that wise old bird, the Sphinx,
He doesn't say a word.

—Newark News.

"COLUMBUS"

Gas and Gasoline
Engines



Observe its Simplicity

The cut shows all of the working parts and no complicated mechanism is concealed on the back side or within the bed. Send for

Catalogue No. 65

Columbus Machine Co.
Columbus, Ohio.

Shop Notes for 1906 will be ready December 1st. No workman's library complete without this helpful book. Many illustrations. Price, 50 cents.



Box No. 30


Jump Spark Coils

FOR ALL PURPOSES

Single, Double, Triple and Quadruple for Stationary Engines and Automobiles. Guaranteed in every particular. Fine Vibrator.

SEND FOR CATALOGUE D.


THE KNOBLOCK HEIDEMAN MFG. COMPANY
SOUTH BEND, IND.



"Quick Action"
IGNITING DYNAMOS and
MAGNETOS

The most Reliable Sparkers on the Market.

Take the Place of Batteries.



Please mention Popular Mechanics when writing Advertisers.

OTTO ENGINES

LESS REPAIRS and LESS FUEL

It is what an engine costs to *keep it running* that cuts the big figure and not the *first cost*. The St. Anthony & Dakota Elevator Co., Minneapolis, Minn., writes: "In April, '02, we had 92 'Otto' engines running, all of which gave better satisfaction, cost less for repairs and consumed much less fuel than any others we had tried. During the season of 1902 we bought 35 more 'Otto's' and now have 127 of them." A splendid testimonial to the merits of the "Otto" from people who have tried many others.

OTTO GAS ENGINE WORKS, Phila., Pa.

STANDARD OF THE WORLD




WONDER GASOLINE ENGINES

THE ENGINE OF FEW PARTS.

HAS only one-third the parts found in other engines. The strongest engine on earth for the money, in fact, so simple a child can operate them. Two cycle, jump spark, no valves, gears, etc.

The testimonial attached is a remarkable showing. You can use the "Wonder" with the same result. We manufacture engines for any purpose, both marine and stationary up to 5 H. P. Send for catalogue. Prices and terms will surprise you. A fine agency proposition for you.


The R. M. CORNWELL CO., 408 So. Salina St., Syracuse, N. Y.



The R. M. Cornwell Co., Syracuse, N. Y.

Gentlemen:—The 1 1/2 H. P. Engine purchased of you, called "The Little Wonder," is appropriately named. I am using it to pump water with complete success. I am able to fill a tank containing 750 gallons at an average of 45 feet in 45 minutes, at an expense of less than two cents for fuel. I cheerfully recommend the "Little Wonder" to all that want cheap, effective and economical power.

Yours very truly,
J. W. T.



SIMPLICITY

GASOLINE ENGINES

Vertical and Horizontal, 1 1/4 to 15 h. p. Stationaries, Portables, Pumping Outfits and Sawing Rigs.

GET OUR PROPOSITION
and 1905 catalogue.

Western Malleable & Grey Iron Mfg. Co.
134 Chase Street, Milwaukee, Wis.



Gasoline Engines

Three Styles—All Sizes.

Feed Mills, Saw Machines, etc.

LOWEST PRICES

Write for descriptive circulars and price list. Agents Wanted.

GILSON MFG. CO.



26 Park St., Port Washington, Wis.

BUY A CAPITAL GAS ENGINE

And you will not sit up nights worrying about expensive power.

Our engines are beyond the standard set by older gas engine builders and no one who is looking for the best and most economical power should buy any engine without first investigating the merits of the Capital Engine. Write for Catalog P.

CAPITAL GAS ENGINE CO., - Indianapolis, Ind.



Fairbanks-Morse Jack-of-all-Trades

Gasoline Engine will saw more wood than any other 2 H. P. Gasoline Engine.

It is sent all set up and ready to run.

Awarded Gold Medals at World's Fair, 1904

Cut out complete advertisement and send to

FAIRBANKS, MORSE & CO., Monroe St., Chicago, Ill.


Please send me illustrated Catalogue No. H449 Gasoline Engines. I may want..... H. P.

Engine to run.....

Name..... Street No.....

Town..... State.....

Please mention Popular Mechanics when writing Advertisers.




SPECIAL GAS ENGINE GENERATOR

Steady light from an ordinary Gas or Gasoline Engine. Write for Bulletin.

Rochester Electric Motor Co.

23 FRANK STREET

ROCHESTER, N. Y., U. S. A.




15 Days' Trial on this Engine

No cash payment required. We pay freight to any point within 1,000 miles of Chicago. Spark Plugs guaranteed for 365 days, \$1.50 each.

Second-Hand Engines all Sizes
McDONALD & ERICKSON,

36 West Randolph St., Chicago.



ECONOMY HOT AIR PUMP

Will pump water from wells, cisterns, lakes, etc., to any desired place. Does away with the uncertain windmill and the unreliable gasoline engine. Runs equally well in winter and summer. No explosion; so simple that a child can operate it.

TEN DAYS FREE TRIAL.

Send for illustrated catalogue.

THOMAS & SMITH, Dept. G.

19-21 So. Carpenter St., Chicago.
288 Hudson St., New York.


The MIETZ & WEISS

OIL ENGINE, Stationary and Marine

1 to 75 H. P.

128-138 Mott St. - New York

Convert Your Bicycle Into a Motorcycle



We have a 1 1/4 H. P. Bike Motor. We sell the set of castings & drawings for \$7.50

We also have a 2 1/4 H. P. set of castings. Send stamp for catalogue and full particulars.

EUREKA MFG. & SUPPLY CO.,

ST. PAUL - MINN.

KEROSENE OIL ENGINES

MARINE. STATIONARY. PORTABLE.

No Danger, Maximum Power, Lightest Weight, Simple, Reliable, Economical. No Batteries, Self-ignition by compression. Fully Guaranteed. Write for Catalogue P. M.

International Power Vehicle Company

253 Broadway, NEW YORK.



Peerless Electric Co.

**Dynamo and
Motor Repairing**

Send us a trial order

122-124 So. Green St.

Phone Monroe 1362. Chicago, Ill.

Please mention Popular Mechanics when writing Advertisers.

NEW MECHANICAL DEVICES.

ROPE CLIMBER.—This device will be best understood from the illustration. When the rope is grasped by the hands and the feet raised, the jaws of the climber open, allowing it to slip up the rope freely. The moment the feet are pressed down the



jaws close, gripping the rope and affording a secure support to the operator. A very long rope may be climbed in this way, as the climber can stop for rest as long and often as desired; or having reached the elevation sought can use the hands for other work while standing in the climber.

STEAM WALL-PAPER REMOVER.—Steam generated in a boiler by means of a gasoline burner is applied to the wall by a hood in the hands of the workman. The hood is connected to the boiler by rubber tubing. When the hood has been held to the



wall a short time the old paper readily peels off by the use of a plow. The outfit is portable and the gasoline tank is of capacity for a half day's work. The water tank holds four gallons, sufficient for the same period. The steam kills any germs or vermin that may be in the wall, also.

Cyclopedia of Drawing

A new enlarged edition, constituting a complete encyclopedia of information on Drawing, has just been issued for the library, the shop, drafting room; teacher, student and all others interested in this fascinating subject.

The set is published in two handsome volumes, bound in $\frac{1}{2}$ red morocco. It contains over 1200 pages (8 x 10 inches), completely indexed and beautifully illustrated with 1500 illustrations, line drawings, half tone engravings, full page and folding plates, tables, etc.

Both volumes sent

FREE

for examination

No more comprehensive treatise on drawing has ever been published than this new enlarged edition of the Cyclopedia. Twenty-five dollars would not buy separate volumes covering the subjects. The chief object in offering the books at a reduced price is to show the character of our instruction in drawing and to interest the public in the work of our school.

R. FRITSCH, New Orleans, La., says: "I cannot say half enough in praise of the 'Cyclopedia of Drawing.' I was greatly surprised to receive such fine books, containing so much valuable information, at so low a price."

SPECIAL OFFER

To Readers of Popular Mechanics

Not Good After November 30th


BOTH VOLUMES sent free on approval (express prepaid). Keep them five days. If satisfactory send \$1.00 and \$1.00 per month for six months thereafter. Otherwise notify us and we will transfer them absolutely free. They have a permanent utility that makes them a desirable acquisition to every library.

LIST OF AUTHORS AND SUBJECTS

PROF. H. E. EVERETT, University of Pennsylvania	Freehand Drawing
PROF. E. KENISON, Massachusetts Institute of Technology	Mechanical Drawing
PROF. H. W. GARDNER, " "	Shades and Shadows
PROF. D. A. GREGG, " "	Rendering in Pen and Ink
PROF. W. H. LAWRENCE, " "	Perspective Drawing
FRANK CHOUTEAU BROWN, Architect, Boston	Architectural Lettering
H. V. VON HOLST, Architect, Chicago	Rendering in Wash and Color,
" " " " " "	Water Color hints for Draftsman
PROF. W. H. JAMES, Mass. Inst. of Technology	Working Drawing
PROF. C. L. GRIFFIN, formerly Pa. State College	Machine Design
WM. NEUBECKER, N. Y. Trade School	Sheet Metal Pattern Drafting
" " " " " "	Tinsmithing
" " " " " "	Practical Problems in Mensuration


American School of Correspondence

CHICAGO, ILL., U. S. A.




Size 8x10 inches

CUT OFF HERE
 American School of Correspondence, Chicago:
 Please send me free, on approval (express prepaid,) one
 Cyclopedia of Drawing, as advertised in Popular Me-
 chanics, Oct. '05.
 Name.....
 St. and No.....
 City.....
 State.....



CATALOGUE FREE **PRICES RIGHT**
Telegraph Instruments, Telephones
 Burglar Alarms, Bells, Push Buttons, Batteries, Electric
 Clocks, Medical Apparatus, Motors, Etc., Etc.
MANHATTAN ELECTRICAL SUPPLY CO.
 32 Cortland St., New York 188 Fifth Ave., Chicago



Robert Battery Volt-Ammeter
Guaranteed
 Forwarded prepaid, including case,
 upon receipt of \$4.50
3 VOLTS **SEND FOR**
30 AMPERES **CATALOGUE**
THE ROBERT INSTRUMENT CO.
 50 Shelby St. Detroit, Mich.

Xmas Tree Lights With Battery \$3 up

WE ARE SELLING

Toy Electric Railways	\$3.00 to \$	60.00
Passenger and Freight Trains.....	5.00	50.00
Electrical Books.....	10c to	5.00
Neckties and Cap Lights.....	75c to	5.00
Battery Table Lamps.....	3.00 to	10.00
Carriage and Bicycle Lights.....	3.00 to	6.00
Lanterns and Pocket Lights.....	75c to	3.00
Battery Motors and Fans.....	1.00 to	12.00
Electric Door Bells Complete.....	75c to	1.50
Telephones Complete.....	2.50 and	5.95
Telegraph Outfits Complete.....	1.75 to	2.50
\$8.00 Medical Batteries.....		3.95
\$12.00 Electric Bed with Suspensory.....		2.50
Dynamos and Motors.....	1.00 to	1,000.00
Gas and Gasoline Engines.....	3.00 to	1,400.00

OHIO ELECTRIC WORKS, CLEVELAND


We Undersell All. Want Agents.
Catalogue Free
OHIO ELECTRIC WORKS,
Cleveland, Ohio.

Eldredge Battery Volt-Meter

Reading 0 to 3 Volts in $\frac{1}{10}$ Divisions

A convenient and practical instrument for those who use Primary and Storage Batteries. Its range will cover two cells of primary or one cell of Storage Battery, is Dead Beat in its readings. Non-removable scale on strong contact posts. **Price \$4.**


ELDREDGE ELECTRIC MFG. CO., Springfield, Mass.



ELECTRIC BELLS THAT RING

Our first grade standard make, complete outfit \$1.25. Also telegraph instruments. (Standard "Morse" quality is your guarantee.) Write for catalog.

MORSE ELECTRIC INSTRUMENT CO.,
 Factory Grand Crossing, Chicago.



DYNAMO CASTINGS

Sets of Material or Finished Parts for the
FRANKLIN MODEL DYNAMO
PRICE \$3.50 AND UP
 Will light six 6 c. p. lamps
 Write for illustrated booklet 8


PARSELL & WEED,
 129-131 West 31st Street, • NEW YORK CITY

Please mention Popular Mechanics when writing Advertisers.

MOTORS

$\frac{1}{2}$ H. P. BATTERY MOTOR
A PRACTICAL MACHINE—NOT A TOY
\$5.00 each
 SEND FOR PARTICULARS
WALSH'S SONS & CO., Newark, N. J.

Mitre-Cutting Tool.—A combined mitre-cutting block and corner cramp, especially for making pic-



ture frames and similar work. A recent English invention. Will hold mouldings up to $4\frac{1}{2}$ in. wide.

SEARCHLIGHT CLUB.—A new electrical device is a policeman's club with an electric searchlight in the end which can be made to flash by pressing a button in the handle. One would naturally expect a blow from such a club to be light, but the contrary is true, as it contains a battery, and altogether is quite a shocking affair.

HEAT AND LIGHT GAS BURNER.—Attaches to chandelier, wall bracket or portable gas stand.



Easy to adjust. When lighted produces both heat and light at one cost. Clean and odorless.

Expansion Drill for Iron.—A new English device which cuts holes up to 3 in. diameter. Intended specially for plumbers and hot water engi-



neers. Obviates the cutting of a circle of small holes; only one small hole—the center—is required to use the drill. The claim is that a $1\frac{1}{2}$ -in. hole can be drilled through $\frac{3}{8}$ -in. iron in five minutes.



FOOT AND HAND POWER

Wood Working Machinery

For Carpenters, Cabinet Makers, Wagon Builders and Wood Workers Generally

Machines for Scroll and Band Sawing, Ripping, Cutting Off, Mitering, Rabbeting, Grooving, Gaining, Dadoing, Beading, Edge Moulding, Boring, Mortising, Tenoning, Turning, Etc., for Working Wood in any manner.

ENTERPRISING MERCHANTS ARE QUICK TO SEE
THE SUPERIOR MERIT OF OUR MACHINES : : :

Machines Sent on Trial. Send for Catalogue "A."

The Seneca Falls Mfg. Co. 102 Water St.
Seneca Falls, N. Y.



**WE MANUFACTURE TO ORDER
DIES, TOOLS AND
AUTOMATIC MACHINES**

**ALSO HARDWARE SPECIALTIES
AND PATENTED NOVELTIES**


ESTIMATES FURNISHED ON EXPERT
MODEL WORK. SEND DRAWING OR
SAMPLE.

BOOKLET FREE. WRITE TODAY.

Stamping & Tool Co.

DEP. C

LA CROSSE, WIS.



**B. F. BARNES'
ELEVEN-INCH SCREW
CUTTING LATHE**

For foot or power as wanted. Has
power cross feed and compound
rest. A strictly high-grade mod-
ern tool. We also build a 9-inch
lathe. Descriptive circulars of
each lathe upon request.


B. F. BARNES CO., Rockford, Ill.

FOOT and POWER

**AND TURRET LATHES, PLANERS
SHAPERS AND DRILL PRESSES : : :**

SHEPARD LATHE CO.

A131 W. 2d St., Cincinnati, Ohio



**9 to 15 in. Swing.
New Features.**

If It's a Sebastian, It's a Good Lathe

BUILT UPON HONOR—ACCURACY, EFFICIENCY, MODERATE PRICES.

Foot and Power Lathes, all sizes. Send for Catalogue.

Sebastian Lathe Company,


Covington, Ky.

**MECHANICAL ENGINEER—SPECIAL MANUFACTURER
WILLIAM G. CURTIS**

LIGHT MACHINERY, TOOL MAKING AND DIE SINKING

Estimates furnished for Special and Expert Metal Work
Jewelers' Novelties, Die and Tool Making, Jigs and Fixtures
for fine interchangeable Work, Electrical Work, Screw Ma-
chine Work, Pattern making, Models Redesigned and Per-
fected, Etc., Etc.

**541 THE ROOKERY,
Telephone Harrison 1946. CHICAGO, ILL**



LATHES

9 to 13 inch Swing

List price, \$85.00 and up accord-
ing to size. When ready to buy
send for Lathe Catalog and prices

W. F. & John Barnes Co.
100 Ruby St., : : Rockford, Ill.

SPECIAL MANUFACTURING

**Dies and Stamping
-- TO ORDER --**

**SPECIAL MACHINERY, MODELS
EXPERIMENTAL WORK**

DROP FORGING DIES AND DROP FORGINGS

Hardware Specialties, etc., Man'd to
Order. Send Samples or Drawings for
Estimates. Write for Our Booklet.

THE GLOBE MACHINE & STAMPING CO.
973 Hamilton St., - Cleveland, Ohio

Please mention Popular Mechanics when writing Advertisers.

TELEGRAPHY

The **OMNIGRAPH** is automatic and takes the place of an expert operator. It will send you perfect Morse by the hour or by the day. Many are holding positions they owe to our invention. Five styles from \$2.00 up. Circulars free.

OMNIGRAPH MANUFACTURING COMPANY
Dept. J., 39 Cortlandt Street, NEW YORK CITY.

LEARN TELEGRAPHY AND R. R. ACCOUNTING

Operators Always in Great Demand

\$50 to \$100 per month salary assured our graduates under bond. Our schools are endorsed by every railway official in the U.S. Ladies also admitted. Write for catalogue.

MORSE SCHOOL OF TELEGRAPHY

Cincinnati, O. Buffalo, N. Y. Atlanta, Ga. La Crosse, Wis.
Texarkana, Tex. San Francisco, Cal.

WIRELESS TELEGRAPH CCHERER PARTS

All the difficult parts mounted on base board; price, postpaid, \$1. Certain parts of the set sold separately. Send for illustrated price-list.

NEW ENGLAND COIL WINDING COMPANY, Atlantic, Mass.

Send three one-cent stamps for 5-color
PICTURE OF LINCOLN PARK BRIDGE

W. L. STEBBINGS

Civil and Consulting Engineer
LICENSED ARCHITECT

Monadnock Block, - - - Chicago

Tel. Harrison 1104 Cable Address "Stebbing" Directory Code

WE WILL SEND YOU One Vise,
One Set **GENUINE**
Armstrong Stocks
and Dies.

One Pipe Cutter,
One Wrench. All for handling pipe from 1/4 to 1 inch.

ON RECEIPT OF \$10.50

Send for Catalogue of Complete Line,
ARMSTRONG MFG. CO., Bridgeport, Conn.

GET MONEY- I DID- GOT \$301²⁷

In 2 weeks doing plating, writes M. L. Smith of Pa. (used small outfit). Start as Smith did—that's easy—hundreds already started—new ones daily—money coming in—goods going out. People everywhere have tableware, watches, jewelry, etc., for the "Gray Plating Man." Practical outfit, all sizes, heavy plate, guaranteed, pure gold, silver, nickel metal plating, equal to new goods, latest process, taught free quickly, experience unnecessary, all easy, secrets exposed. Own and Boss a business at home or travelling all or part time that pays \$15 to \$50 weekly. Write today for new offer, sample, and hundreds letters from successful agents—free. M. Gray & Co., Plating Works, 102 Miami Bldg Cincinnati, O.

"SHOP NOTES"

200 Pages


386 Illustrations

PRICE - - - 50 CENTS

POPULAR MECHANICS

Please mention Popular Mechanics when writing Advertisers.

New Bench Vise.—An English device specially intended for use in manual training schools. Contains in addition to the ordinary vise, a drawing



table, seat, rack for files and compartments for tools, and drawer for drawing instruments.

"Next Street" Indicator.—A mechanical device for announcing the next street or station in street or passenger cars. Consists of a box 8 in.



high by 24 in. long, operated by a bell cord and illuminated at night by an electric lamp inside the box.

Automobile Rules.—Grab der veel vich is in front of you firmly mit both hands and put one foot on der accelerator. Now put der udder on der rheostat und let der elbow chently touch der de-odizer. Keep der blow pipe connecting mit der automatic fog vissle closely between der teeth, und let der right elbow be in touch mit der quadruplex while der apex of der left knee was pressed against der spark coil. Keep both eyes on der road in front of you und der rest of your face in der vaggon. Start der driving wheels, repeat slowly der name of your favorite coroner, und leave der rest to fate.—Whitewater (Wis.) Register.

Glass Churns for Home Use.—

The glass churn comes in small sizes and is intended for converting the small quantities of milk and cream that may not be used and will sour if left over into wholesome butter. The churn has a small wooden paddle that is easily rotated and seven or eight minutes of churning suffices.

The churn can be operated by an inexperienced child, and the little pats of home-made butter amply repay for the extra trouble.



STARRETT TOOLS

are the recognized standard for accuracy, workmanship, design and finish. Whether you use tools to earn your daily bread or for amusement and relaxation from a different vocation, it pays to use GOOD tools. You get a better quality of bread and a good deal more pleasure.




L. S. STARRETT

USE STARRETT TOOLS

We make hundreds of different tools. Ours is the largest plant in the world where nothing but fine mechanical tools are made. All these tools are fully described and illustrated in our Catalogue No. 17AP, which you may have by sending us your address. There is a good deal of valuable information in its 176 pages which it will pay anyone who uses tools to have.

THE L. S. STARRETT COMPANY
ATHOL, MASS., U. S. A.



Earn from \$80 to \$125 Per Month

WE WANT YOUNG MEN for Firemen and Brakemen, experience unnecessary. High Wages, Promotion. Positions secured as soon as competent. Instructions by mail. Cut out Coupon and send with stamp for full particulars to-day . . .

**National Railway Training
School, 224 Boston Blk.
MINNEAPOLIS, MINN.**

Name _____
Town _____
State _____
R.F.D.No. _____
Age _____

HEIGHT AND SPEED OF WAVES

The subject of the height and velocity of the waves of the ocean is always an interesting one, and frequently comes up for discussion by landmen as well as seamen. It has been calculated that waves rarely exceed a height of 40 feet, while the speed at which they travel depends largely upon the wind and depth of the water. Airy calculates that a wave 100 feet in breadth and in water 100 feet deep travels at the rate of about 15 miles an hour; one 1,000 feet broad and in water 1,000 feet deep at the rate of 48 miles; one of 10,000 feet in breadth and in water 10,000 feet deep will sweep forward with the velocity of not less than 154 miles an hour. An earthquake on the Island of Nippon, Japan,

caused a wave to travel 4,800 miles across the Pacific to San Francisco in 12 hours and 16 minutes, or at the rate of $6\frac{1}{4}$ miles a minute. Waves of the Atlantic have been calculated to move at the rate of 32.67 English miles an hour.

THE MAN WHO'S AFRAID

I've paid close heed to the ways of men,
I've observed what the world calls luck,
I have silently marveled, now and then,
At the potent power of pluck;
And this as a bit of truth I hail,
A sentence that's worth one's heed;
The man who is always afraid he'll fail
Doesn't stand much show to succeed!

—Dividends.

1068

4 SMOOTH PERFECT EASY SHAVES for 1c

BY THE
USE
OF THE

MORTON

SAFETY RAZOR



ONE PIECE
HANDLE and
BLADE

FULL SIZE

TRIPLE
SILVER
PLATED

There are twelve double-edged blades or twenty-four cutting edges of the finest, smoothest, hardest steel, ground by our own process to a lasting, perfect edge. They are tempered so hard they will cut glass, and each one of these blades will give 20 to 40 smooth, perfect, easy shaves, no matter how harsh the beard, with

NO HONING OR STROPPING

A set of new blades will cost \$1.00—so you can see how you can get 300 to 500 shaves for \$1.00, or an average of about four shaves for a cent.

The safety razor has become popular, and self-shaving is now a part of every gentleman's education. It has remained for the **MORTON** to develop to the highest point, where others have experimented. Its construction is so simple that it cannot get out of order, and any one can use it. There are only two pieces—handle and blade. The blade slips into the handle without screws, clasps, hinges, or other movable parts. **With the MORTON cutting the face is impossible.**

PROVE ALL THIS BY A TRIAL AT OUR EXPENSE

Use the **MORTON** thirty days and if for any reason you want your money back, just return the razor and we will return your money without question. We pay express charges both ways. We authorize all dealers to make this offer. If yours don't handle the **MORTON** write us for our interesting booklet, but be sure he doesn't induce you to try "some other" kind. There is no other razor "just as good."



Exact Size of Blade.

MORTON
SAFETY RAZOR CO.

1192 Tacoma Building, Chicago, Ill., U. S. A.

Home Benches



THE NO. 42 BENCH; ALSO MADE WITHOUT CABINET

Write for Catalog and Prices

**GRAND RAPIDS HAND
SCREW CO.**

146 South Ionia Street

Grand Rapids - - Michigan

Largest Manufacturers of Manual Training and Home
Benches in the World.

We
Manufacture
and Market

Patented
Specialties

We have had
Experience

You probably
Have not

Send us
Description of
Your Invention

It will have care-
ful consideration

Should we think
it unsuitable for
our purposes,
all papers will
be returned

POWER SPECIALTY CO.

513½ WASHINGTON ARCADE
Detroit, Michigan

Manufacturers of Various Styles and Sizes of Draughting Tables, Drawing Boards, Blue Print Filing Cabinets, Blue Print Frames, Etc. Send for Illustrated Catalogue or ask your jobber.



FRITZ & GOEDEL MFG. CO.,
99 Alabama Street, Grand Rapids, Mich.

\$13 SAVE YOUR STENOGRAPHER'S TIME Dearborn Jr. Typewriter Cabinet \$13

42 in. long
24 in. deep
38 in. high




Guaranteed the most complete and perfect desk ever sold at any where near the price. We ship on approval. \$13.00. Freight Prepaid East of Rocky Mountains. Without roll curtain to paper cabinet, price \$12.00. Made of solid golden oak, beautifully finished. Invaluable note book holder free with Cabinet. Write for FREE catalog of this and other styles.

DEARBORN DESK CO
ALEXANDER A. SAMUEL

Gen. Mgr.

304 Fisher Building
CHICAGO, U. S. A.

IF YOU WANT A DESK ASK "DEARBORN"



STEEL SHOP BARRELS

For Foundries, Factories, Machine Shops, etc. Intended for carting and storing heavy fittings, castings, parts of valves, etc.

SIZE—18 inches diameter, depth 28 inches. Shell made from single sheet of No. 16 gauge steel, having only one riveted side seam. Bottom stamped from a single plate of No. 8 gauge steel, to form flange 1 inch deep, which is riveted to the shell and with a 1 inch corrugation 6 inches from the center, barrel bound at top with $1\frac{1}{4} \times \frac{3}{4}$ inch steel. Painted black outside. Weight 60 pounds each. Open at top; not water tight. Other sizes made to order.

Write for prices and information to

The Kilbourne & Jacobs Mfg. Co.

Lock Box G

Columbus, Ohio.



Platinum, Gold, Silver Etc., without the use of solder or acids. Solderene solders anything and everything that the old method of using bar or wire solder, acids, rosin and paste accomplished.


AGENTS WANTED. SEND TEN CENTS FOR A SAMPLE STICK.

THE CHAS. A. THOMPSON CO.,

41 Cortlandt Street, New York, N. Y.

SOLDERENE

A new rapid flux and tin combined for soldering and mending Iron, Copper, Brass, Lead, Zinc, Tin. Solderene solders anything and everything that the



Big Catalogue Free

The popular Ward Catalogue, very latest edition. 1200 pages, a new book from cover to cover. The catalogue that is known everywhere and liked by everybody. It has been in use for a third of a century and has made friends in all parts of the world.

Don't bother with unreliable, incomplete catalogues, when you can get the genuine Ward book for the mere asking. This is the catalogue for wide awake buyers. It's reliable, brand new, complete in every department, honest in descriptions, and quotes the very lowest price for really good merchandise. No cheap goods at Ward's. Catalogue No. 74 will prove a money-saver for you.

No Charge

The complete 1200-page catalogue, very latest edition, will be sent free, postpaid, to every grown man or woman who will cut out this coupon and send to us with his or her name and address plainly written. We don't ask you to write a line—only your name and address. Cut out coupon and mail to Montgomery Ward & Co., Chicago.

Cut here, fill in carefully.

COUPON

Send me FREE and prepaid one copy of your New No. 74 Catalogue for 1905-6. I saw your ad in Oct. Popular Mechanics.

Name _____ B. F. D. No. _____

Post Office _____ County _____ State _____

MONTGOMERY WARD & CO., Michigan Ave., Madison and Washington Sts., Chicago.

Please mention Popular Mechanics when writing Advertisers.

FIRST WATER

Diamonds on Credit



JUST THE SIZE THAT SATISFIES

1/2 CARAT QUALITY-A-1 \$72.50

OTHER GRADES OF SAME SIZE AS LOW AS \$50.00

TERMS \$12. CASH \$5. PER MONTH

AMONGST our customers are many who buy on credit by choice—not because they can't afford to pay cash. Ask them "why" and they will tell you that gradually paying for an article makes the cost seem as nothing. Of course, everybody must know that there is a difference between credit prices and lowest prevailing cash prices—but with us the difference is hardly worth mentioning. It's a mere fraction.

We will send you on approval, express prepaid, a half carat diamond with mounting like illustration, or any standard 14-kt. solid gold mounting. If ring is as represented, pay express agent \$12.00. Balance monthly. If you'd like to have goods sent by registered mail, send first payment with order. Your reputation for honesty is our security.

Catalog No. G71 shows a wealth of diamond rings ranging in price from \$12.50 to \$743. If interested in Watches, ask for Special Catalog. Both free.

Herbert L. Joseph & Co. High-Class Jewelry Credit House
213 (G71) STATE STREET, CHICAGO
Established 1882 Responsibility, \$250,000.00

WINTER CLOTHING OFFER

FREE SAMPLE and TRIAL PROPOSITION.


If you would have any use for a heavy or medium weight all wool Suit, Overcoat or Ulster, then **DON'T BUY ELSEWHERE** at any price, under any circumstances, until you cut this advertisement out and mail it to us. You will then receive by return mail, free, postpaid, the **Greatest Clothing Offer ever heard of**. You will get **FREE** a big book of cloth samples of Men's Clothing, **FREE** an extra quality cloth tape measure (yard measure), **FREE** a book of latest fashions, descriptions and illustrations of all kinds of clothing for men. We will explain why we can sell at prices so much lower than were ever before known, a mere fraction of what others charge. We will explain our simple rules so you can take your own measure and how we guarantee a perfect fit. You will get our **Free Trial Offer**, our **Pay After Received Proposition**. With the free outfit goes a special sample order blank for ordering, return envelopes, etc. You can get a whole suit, an extra pair of Pants and an Overcoat under our offer for about **ONE-HALF** what some Chicago tailors would charge for one single pair of pants. The offer you will get will astonish and please you. Prices on the best clothes made reduced to next to nothing compared with what you have been paying. **DON'T BUY CLOTHES** until you cut this ad. out and send to us, and see what you get by return mail, free, postpaid.

Address **SEARS, ROEBUCK & CO., Chicago.**

—BE THE BOSS—

Make \$100 per month. Others do it. You have same chance. Start a mail order business at home. Write for our "Starter" and free particulars.
Mgr. W. C. Co., 956 E. 23rd St., Los Angeles, Cal.

BURN AIR-IT'S CHEAP LIKE IT!




Consumes 395 Barrels of Air to one gallon of Kerosene. Penny fuel, burns like gas, hottest fire, won't explode, saves work and fuel bills. No coal, wood, dirt, ashes—no wick, no valves, easy operated, handsome, durable. Grand cooker, baker, quick work, cool kitchens. 13000 Harrison Wickless, Valveless Oil-Gas and Air Burners sold 1 month. **AGENTS WANTED**—\$40 Weekly. Greatest **MONEY MAKER**. Guaranteed, all sizes, sent anywhere, \$8 up. Write, **FREE** proposition, 30 day trial offer.

World Mfg. Co., 5909 World Bldg, Cincinnati, Ohio,

Please mention Popular Mechanics when writing Advertisers.

\$20 to \$50 Weekly made selling this new invention, the STANDARD Self-Filling Self-Cleaning FOUNTAIN PEN

No ink dropper. No smeared fingers. No twisted rubber No Complication



\$178.90 earned in 32 days by retired business man in Ala.
\$48.00 earned in first four weeks by Rev. B. F. Gehring of N. Y. Spare time only.

\$35.80 for a month's odd hours by G. Jos. Lovett of Mass.

\$5.40 made in First Two Hours by Mrs. Mary M. Lennon of Mich.

Our free lessons in successful salesmanship make experience unnecessary. We send all particulars and figures to prove above and many other records. Write today. Energetic Agents and District Managers Wanted.
STANDARD PEN CO., 1056 Baker Bldg., TOLEDO, O.

QUICK HANDLING OF MAILS ON THE ROCK ISLAND ROAD

A satisfactory device for discharging mails from high-speed trains, for which postoffice officials have been searching for more than seven years, has at last been discovered and following repeated tests, is now in daily use on one of the Rock Island's fast mail trains in Iowa.

Captain E. L. West, superintendent of the railway mail service, Chicago, and other postoffice officials who have witnessed the workings of the new device, are enthusiastic over the results accomplished. Equally good performance is shown on trains running at from fifteen to as high as seventy-two miles per hour.

The operation of the mail crane for picking up mails is familiar but the problem of discharging mails safely from the same trains, without hazard to the mails, trains and bystanders, has been a difficult one. A special commission appointed by the postmaster general, in 1902, to examine the various devices offered the department, made thorough tests of eighteen different devices and reported, in May, 1902, rejecting all of them as having one or more points of impracticability.

The Burr delivering device was among those examined, but the objections entered against it have been overcome. The device is entirely automatic and is operated by air from the brakes of the train and the instantaneous action necessary, is thus secured.

The device consists of a platform arranged in the car door, on which the sacks of mail to be delivered are placed. Contact between the crane on the station platform and a trigger on the mail-catching arm on the car, puts the mechanism in operation, which ejects the mail sacks into a receiving box placed at the side of the track, so constructed that the air is forced into either end by the momentum of the pouch and thus acts as a cushion, preventing damage to the pouch or its contents. The Burr device, combined with the standard crane, can be operated either to catch or deliver mail.

The Rock Island has done much in the past few years to facilitate western mail service and in affording opportunity for development of the Burr mail-catching and delivering device, has given valuable aid to the postoffice department and the commercial interests of the country.



TIZ-IT

Trade Mark
(Cut 1/2 Size)

SEE THAT BALL?

This New All-Metal-Ball-and-Socket-Swivel-Joint HORN CONNECTION will positively improve your PHONOGRAPH or GRAPHOPHONE. Fits all Edisons and new Columbias. Price 50 C's Postpaid.
—KREILING & COMPANY—
—Inventors and Sole M't'rs.—
855 N. 40th Ave., CHICAGO.

Nature's Coffee Pot

'Makes Coffee Harmless.'

We have at last discovered the active principles of separating the pure Coffee extract from the bitter and poisonous matter of the Coffee Bean.

Like all great inventions—it is simple; so simple indeed that it seems impossible that it was not thought of before. We want to tell you more about this Coffee Pot—it's wonderful workings and the clever way it transposes Coffee into a drink—as healthy and harmless—as a glass of water.

Try This Coffee Pot at Our Expense

Talk is cheap—let us show you the proof by sending you a Nature's Coffee Pot. We want you to test it for yourself in your own home. Send us no money until you are satisfied—then mail us a dollar or send us back the Pot. This is our way of doing business.

THE POILLON POTTERIES, Branch No. 3, Woodridge, N.J.



Catalog Free.

The season is here to

MAKE MONEY

Get started early.

**\$40 to \$75
A WEEK**

Can be made with one of these

**Steam Peanut Roasters
and Corn Poppers**

S. DUNBAR & CO.

16-18 No. Desplaines St.
CHICAGO.

MANUFACTURERS

Why not locate where intelligent labor, raw material and demand

for your product obtains. All these and more found on the **BURLINGTON ROUTE.** For information write to

**Burlington
Route**

W. H. MANSS, Industrial Commissioner

209 Adams Street - - - - - Chicago

3 MONTHS FREE

If you are interested in any kind of investment—Oil, Mining, Plantation, Industrial, Lands, Stocks, Bonds, Mortgages, etc., send us your name and address and we will send you *The Investor's Review* for 3 months free of charge. A journal of advice for investors. Gives latest and most reliable information concerning new enterprises. Knowledge is power. Great opportunities come and go. Great fakes likewise. Get posted before investing. Write to-day.

INVESTOR'S REVIEW, 1461 Gaff Bldg., CHICAGO, ILL.



A COLORED VIEW FREE.

WRITE FOR THE
FREE COLORED
VIEW NOW.

Send me your name and address and I will send you by return mail, postpaid, free (nothing for you to pay) one of my latest new secret process, beautiful colored stereoscopic views. I will also send you my new price list of stereoscopes and views of all kinds, war views, scenery, famous places, St. Louis Fair views, Bible scenes, comic views, funny scenes, etc., all wonderful offers that will delight you.

ROBERTS SPECIALTY COMPANY, BOYCE BUILDING, CHICAGO, ILL.

GASOLINE SOLDERING IRON AND BLOW TORCH



Furnished with two coppers drop forged from bar, one for regular work and one for heavy work. Nothing complicated. No pump to get out of order. No platinum coil to burn out. Never too hot and never too cold. No wind will blow it out. Can be changed to blow torch instantly. Can be carried in any tool kit, or linemen's belt. Will last for years. Used by tinner, plumbers, painters and electricians. Guaranteed to give satisfaction. If your jobber does not handle them, write us for illustrated booklet and price.

EMMELMANN BROS. MFG. COMPANY, Indianapolis, Ind., U. S. A.

COUNTRY HOME LIGHTING

Made effective, easy and 50 to 75 per cent cheaper than kerosene, gas or electric lights by using our


BRILLIANT

OR

Head Light Gasoline Lamps

They can be used anywhere by anyone for any purpose, business or house use, in or out door. Over 100,000 in daily use during the last 8 years. Every lamp guaranteed. Write for P. M. catalog, it tells all about them and our Gasoline Systems.

BRILLIANT GAS LAMP CO.
42 State St. Chicago, Ill.



\$5.00 a month to one bright man in each good-sized shop. Does not interfere with regular work in the least. Address "Opportunity," Room 510—160 Washington St., Chicago.

\$15.00 — \$6.21 LIST REFRIGERATORS



Factory Closing Out SALE

Price less than cost
to manufacture

White Enamel Lined, Zinc Lined
Galvanized Steel Lined
Charcoal, Granite Rock Filling
Cold Air Space

Our prices \$5.00 to \$8.00 Less than Department Stores

SENT ANYWHERE C. O. D. SUBJECT
TO APPROVAL

Tolman Steel Range Co.
66 Lake Street, Chicago

Spon's Mechanic's Own Book

Is the most useful and handy book ever published for anyone interested in mechanics or who likes to use tools, because it contains real practical information on almost every mechanical subject including

Mechanical Drawing
Mechanical Movements
Casting & Founding
Forging
Soldering
Turning & Turning Lathes

Carpentry
Log Huts, Building, Etc.
Cabinet-Making
Carving & Fretwork
Picture Frame Making

Painting
Staining
Polishing
Paper Hanging
Electric Bell & Bell Hanging

OVER 700 PAGES. 1420 ILLUSTRATIONS. PRICE CARRIAGE PAID \$2.50.

An 8-page circular giving full contents sent free on application.

SPON & CHAMBERLAIN, - 123 P. M., Liberty St., New York

HENRY & HORA'S
Modern Electricity



Explains X-Rays, Wireless Telegraphy, Radium, Transmission & Distribution, Power Stations, Wiring, etc. Written in plain English.

All Problems Solved

Practical—Accurate—Scientific
150 illustrations.
355 pages. Cross index.

"A practical handbook for students, apprentices, and electrical engineers."—*Scientific American*.

Silk Cloth, decorative cover, silver stamping, . . \$1.50
Seal Leather, marbled edges, gold stamping, . . 1.00

LAIRD & LEE, PUBLISHERS CHICAGO
263 Wabash Ave.

AGENTS WANTED Sell \$1 bottle Sarsaparilla for 35c;
best seller; 200 per cent profit.
Write today for terms. F. R. Greene, 115 Lake St., Chicago

WHEN IN SAN FRANCISCO
— YOU CAN ALWAYS GET —

Popular Mechanics

and its books, as well as back numbers,
and any other book or periodical you want.

ROBERT C. ROSS, 1203 Market Street, 'Frisco

Send **THE MONTHLY "CONCRETE"**
for **JOURNAL**

One Dollar a Year. Sample Copy Free

Concrete Publishing Co., - 20 Congress St. DETROIT, MICH.

**Write for Our
Great Offer**

**To One Man
In Every Shop**

..Popular Mechanics..

Please mention Popular Mechanics when writing Advertisers.

SMALLEST COMPLETE FARM IN THE WORLD.

California can truthfully boast of having the smallest complete and most profitable (for its size) farm in the world. It is located in the great valley of the Sacramento, near the little town of Orland. This farm consists of just one square acre. It belongs to Samuel C. Cleek, who, assisted by his wife, has continuously cultivated this diminutive ranch for 27 years. Originally, the acre was part of a wheat field, and was dry and semi-barren, having no running water. Cleek sunk two wells from which he obtained an abundant supply of water. He has converted the arid farm into a perfect gem of beauty, fragrance, and profit. Not only has this acre supported the couple, in comfort and even luxury, but has yielded an income, and \$4,000 has been placed in the bank—derived from the profits of production.

Mr. Cleek first settled on the wee sterile tract, when he and his good wife were very poor. Through patience and judicious toil, the couple have made the land literally "to bloom and blossom as the rose." This farm contains: Cottage and porch, 30 by 30 ft.; barn and corral space, including chicken coops, etc., 75 by 75 ft.; two windmill towers, 16 by 16 ft. each; garden, 46 by 94 ft.; strawberries, 65 by 90 ft.; citrus nursery, 90 by 98 ft.; in which there are 400 budded orange trees; a row of dewberries along the fence, 100 by 2 ft.; four apricot, two oak trees, three peach trees; seven eucalyptus trees; six fig trees; ten locust trees; one paradise tree, four bearing bread trees; thirty rose bushes; twenty geraniums; twelve lemon trees; a large lime tree from which was sold the present year 160 dozen limes; eight bearing orange trees; five pomegranate trees; six beds of violets, 6 by 2 ft. each; one patch of Japanese bamboo; one bed of calla lilies; four prune trees; six cyprus trees; fourteen stands of bees; four huge grapevines; one bed of sage; one large garden and flower seed bed, besides honeysuckle, and a great many other rare and beautiful exotic plants and shrubs. In some of the little spare corners and angles, vegetables are cultivated with much success; so that with the exception of flour for bread, and a few groceries, this little "One Acre Farm," produces all that Cleek and his wife can consume, and a great deal more—leaving a considerable surplus that is marketed to profit every season. This demonstrates what may be produced on just one acre of even rather poor land when it is industriously cultivated.

The "1906 Shop Notes" will be ready December 1st. Price 50c.

Drawing Instruments and Materials

**MOST COMPLETE ASSORTMENT
ALL GOODS WARRANTED**

Richter Instruments of Precision

None better. Their mechanical
merits challenge criticism.

Blue Print Papers, Vandyke Solar Paper

Write for Catalogue "P," 416 pages

EUGENE DIETZGEN CO.

181 Monroe St.,
Chicago

14 First Street,
San Francisco



119-121 W. 23d St
New York

145 Baronne St.
New Orleans

Raise Your Salary

We have built up the largest educational institution in the world, with an invested capital of 5 million dollars and with $\frac{1}{2}$ of a million students, by helping people to increase their earnings. This remarkable growth means that we have made a remarkable success of enabling people to earn more money. It is because we have helped so many thousands of others under all circumstances that we state positively that we can help YOU. Do you want to raise your salary? It puts you under no obligation to find out how you can do so. Simply write us, stating the occupation you wish to rise in. **DO IT NOW.**

International Correspondence Schools

Box 872,
Scranton, Pa.

**DRAWING STUDENTS NEED
THE DRAFTSMAN**
25c for 4 months—Cleveland, Ohio

Grand Rapids School of Mechanical Drawing

361-362-363 Houseman Bldg., Grand Rapids, Mich.

INSTRUCTIONS BY MAIL

In MECHANICAL DRAWING, NAVAL or MARINE ARCHITECTURE,
BOAT DESIGNING, LANDSCAPE GARDENING.

SEND FOR OUR CATALOGUE OF FULL INFORMATION.


Please mention Popular Mechanics when writing Advertisers

ROGERS' Machinists' Library

—LIST—

The Progressive Machinist . . . \$2
The Advanced Machinist . . . 2
Mechanical Drawing and Design . . 3

SEND POSTAL FOR MACHINISTS' LIBRARY.



Each of the Books in the Library is a complete treatise in itself and can be purchased separately at price above named.

—PLAN OF WORK—

The three volumes composing the "Machinists' Library" have been issued just long enough to receive the most hearty approval of the best representatives of the Engineering and Mechanical world.

The books composing the library are intended to be: educational, and progressing from the simple to the more complex subjects; plain books for those already engaged, or soon to be in the practical application of the theory of mechanics; each volume is complete in itself, while progressive in the series. The books are each supplied with a ready reference index, which enables the quick use of their contents.

The volumes are strongly and handsomely bound in black cloth, with titles and edges in gold; they contain 1,204 pages, 1,244 illustrations, many of which are full pages, with 3,000 ready references; they are printed on fine surface paper with large, clear type. Each book stands 8½ inches in height, and the three packed for shipment weigh over 7½ lbs. No works of equal value have ever been offered to the machinists' and allied trades, and no one, from the Superintendent and Owner to the Apprentice, can afford, considering the price and terms, to be without them.

—MONTHLY PAYMENT PLAN—

Rogers' Library is supplied whenever desired on easy terms. Upon receipt of one dollar, and agreement to remit the same amount each month for six months, and accompanied by the name of one or two persons of whom inquiry could be made if desired, regarding subscriber's reputation for keeping business promises, the set will be shipped to any part of the world with all transportation charges prepaid.

CUT OUT AND MAIL TO-DAY

I accept your offer to supply me with ROGERS' MACHINISTS' LIBRARY, 3 vols., for \$7. Enclosed find \$1 as first payment; the balance I agree to remit in \$1 monthly installments.

Name _____

Occupation _____

Address _____

You are at Liberty to consult the person named below as to my reputation for keeping business promises.


Name _____

Address _____

Pop. Mech. Oct.

THEO. AUDEL & CO.

Educational Book Publishers,
63 Fifth Avenue NEW YORK.



Learn Furniture Designing

DO you know that the Furniture business is one of the most rapidly growing trades in this country? Those who will enter this line now will have a splendid future before themselves. The public demands new ideas at all times, and there is a great field for practical and original people who may wish to become

Furniture Designers

We always have an opportunity to place our graduates in good paying positions. Some of them are now earning between \$1200.00 and \$2500.00 per year with plenty of chances for further advancement. Write for full particulars and testimonials.

COLLEGE OF FURNITURE DESIGNING
Porter Block, Dept. M, Grand Rapids, Mich.

Engineering

**MECHANICAL,
ELECTRICAL,
STEAM,
CIVIL.**

Complete and short courses. Thoroughly equipped engineering shops. Shop work from the beginning. Short courses in Steam and Electrical Engineering. Expenses low. Accommodations the best. School all year. Students may enter any time. Correspondence steam and electrical courses. Send for catalogue. Mention course in which interested.
HIGHLAND PARK COLLEGE, Des Moines, Ia.

STUDY LAW

**Leading Law School
In Correspondence
Instruction.**

Thirteenth Year.

Prepares for the bar of any state. Improved method of instruction, combining the Text-Book, Lecture and Case Book methods. Approved by the bench and bar. Three Courses: College, Post-Graduate and Business Law. The One-Price School. Write today for Catalogue.

Chicago Correspondence School of Law,
Reaper Block, Chicago.



WHY NOT LEARN SIGN PAINTING?



SHOW-CARD WRITING OR LETTERING.

Only field not overworked. Separate courses. Ours is the only practical, thorough and personal instruction. We teach by mail and guarantee success. Easy terms. Write for large interesting FREE Catalog. **THE DETROIT SCHOOL OF LETTERING,** Dept. P M, Detroit, Mich.
"Oldest and largest School of its kind."

Be Your Own Taxidermist

WE can teach you BY MAIL to stuff and mount Birds, Animals, Fishes, etc. The most fascinating of arts. Easily learned by men, women and boys. **BIG PROFITS.** Save your fine trophies. Decorate home and den. **STANDARD METHODS** only and **GUARANTEE SUCCESS.** If you hunt, fish, love or enjoy nature in any way you should know Taxidermy. Investigate today. Write for particulars. New Catalog and Taxidermy Magazine, ALL FREE. **N. W. SCHOOL OF TAXIDERMY, Inc.,** 53 T St., Omaha, Neb.



WANTED

men to post signs, advertise, and distribute samples. Salary \$18.00 weekly, \$3.00 per day for expenses. State age and present employment.

KUHLMAN CO., Dept. B. . . . ATLAS BLOCK, CHICAGO

STEEL FENCE, WHY NOT STEEL POST?

Argument in Favor of Steel Fence Post—Protects Against Lightning

By L. C. Sharp

Being considerably interested in fence post construction, I note with interest an article in your July issue by T. H. Pottinger, of Peru, Ill., relative to the various good points inherent in cement construction for fence posts. I have given this matter considerable thought and have arrived at a different conclusion, and think that the coming post for farmers will be made of metal. It is conceded by all observers in this line that the old wooden post must go, and the reasons are plentiful why this should be so. While the advantages of cement posts, as enumerated by your correspondent, are evident, they are not enough to warrant the assumption that concrete has sufficient advantages to make it the coming post.

In regard to cement construction, it is not every farmer who cares to bother with or comprehends the mixing of cements and casting in moulds; then again, the constituents of a perfect cement mixture are not easily obtainable in all localities. On the other hand, if the posts are factory-made, the excessive weight and their fragile nature brings them into a classification in shipment which makes a prohibitive price on them; furthermore the stringing of wires and stay plates in the interior introduces additional expense and weakness in the posts.

As to the cement being a protection against lightning, I do not see how this can be, as seasoned cement is a non-conductor, as much so as wood. It is now well understood that it is of the highest importance that all fence wires be grounded with the earth, in order that stock may be protected from this dangerous source of loss. The electric discharge will escape always through the path of least resistance, which is often through the bodies of stock and animals which invariably drift up against the fences during storms. How often do we hear of whole herds being stricken down in this manner! I have noted but recently the event of

(Continued on page 1076.)

KEUFFEL & ESSER COMPANY OF NEW YORK


111 East Madison Street

Chicago

DRAWING MATERIALS

SURVEYING INSTRUMENTS

Write for particulars about our new Mechanics Steel Tape Rule.



TECHNIC OF Mechanical Drafting

BY CHAS. W. REINHARDT

Chief Draftsman, Engineering News

Author of "Lettering for Draftsmen, Engineers and Students."

"SHOWS HOW TO DO IT"

Contains chapters on outlining, lettering, outline shading, section lining, curved surface shading, shading of inclined surfaces, topographical drawing, character and finish, etc. Boards 11x8 ins. 42 pp. 50 text illustrations and 11 full page plates. Plates I to IV contain 69 distinct conventions for section lining.

Prof. Jacoby of Cornell, says: "Each of the chapters on 'outline shading' and on 'section lining' are alone worth the price of the book."

Most Popular Book on Mechanical Drafting Ever Published

Adopted as Standard in many Technical Schools

PRICE, \$1.00

MECHANICS

PROBLEMS FOR ENGINEERING STUDENTS

By Prof. Frank B. Sanborn

500 problems, many being examples in engineering practice.

Contents: I, Work (Problems 1 to 172). II, Force (Problems 173 to 406). III, Motion (Problems 406 to 500) answers and complete index. A practical, elementary book of problems for the use of practicing mechanics, engineers and students.

PRICE, \$1.50

Send for descriptive catalog M. P. and a sample copy of Engineering News

THE ENGINEERING NEWS PUBLISHING CO.

220 BROADWAY, NEW YORK

ARE YOU LOOKING For a Better Position?



Are you looking for that chance, that opportunity to improve your position? Then let us help you. If you follow our advice, our instructions, we will enable you to better your position, to increase your salary, to make a more satisfactory and better living throughout your entire life. No training whatsoever means poor salary, no possible chance for advancement—that is sure. We can give you a thorough training by mail in your spare time to qualify you for a high salaried position as an Electrical, Steam or Mechanical Engineer, Mechanical Draftsman, Machine Design, Electric Lighting, Motorman, Dynamo Tender, Telegraphy, Short Electrical Course, Arithmetic, Algebra. Complete course in Engineering \$15, and up.

**Let Us Prove to You
What We Can Do.**

Thousands have succeeded; you have just as good a chance. Write for our free 80-page book and testimonials; convince yourself.

SPECIAL OFFER: New students enrolling now will be provided free of charge with our Reference Library and a set of Electrical Apparatus.

Electrical Engineer Institute of Correspondence Instruction, Dept. 6, 240-242 W. 23d St., New York.

Spangenberg's Steam and Electrical Engineering

Some of the Authors

This book is really a text-book of the St. Louis School of Engineering, the entire mechanical portion, except that pertaining to the locomotive, having been written by Prof. E. Spangenberg, C. E., the Superintendent of that institution, a graduate of the shop and work bench as well as of the University. Mr. Spangenberg has been eminently successful as a teacher, having enabled hundreds of men to pass satisfactory examinations for stationary and marine engineers' licenses.

Mr. E. W. Pratt, author of the portion on Locomotive Engineering, is master mechanic of one of the large railroads, and has made the locomotive his life-study.

Mr. Albert Uhl, A. I. E. E., Instructor in Practical Electrical Engineering at the St. Louis School of Engineering, is a successful electrical contractor who has risen from the ranks, having worked as dynamo tender and wireman's helper in his younger days.

695 Pages—648 Illustrations

Written so You can Understand It. A practical book for practical men. Intended especially for the use of Stationary, Steam and Locomotive Engineers and Firemen, Electrical Workers and others interested in Engineering. The work is written in the form of **1,035 QUESTIONS and ANSWERS** and gives a complete course in Engineering, Stationary and Locomotive, Compressed Air, Refrigeration, Gas and Gasoline Engines, Elevators, Repairs and Electrical Engineering.

When Ordering use Attached Coupon

Price \$3.50

\$3.50 is the price, and it is sold with the understanding that it may be returned if not satisfactory, and your money will be refunded immediately. Out of 10,000 books sold only one has been returned. This fact speaks for itself.

COUPON—CUT OUT AND MAIL TO-DAY

GEO. A. ZELLER BOOK CO., 7 So. 4th Street, St. Louis, Mo.

DEAR SIR: I accept your offer to send me express prepaid, one of Spangenberg's Steam and Electrical Engineering, a complete library in one volume: 695 pages, 648 illustrations, price \$3.50, and enclose \$2.00 as first payment. The balance, \$1.50. I agree to remit in 60 cent monthly installments, money or express order, or stamps.

NAME

Street or Box No. City and State

Please mention Popular Mechanics when writing Advertisers.

10/6

Dynamo and Motor Bargains

We carry in stock over 600 machines in all sizes from $\frac{1}{8}$ to 100 horse power, both new and second hand, *all guaranteed*. Small factory equipments our specialty.

NO ONE

Can sell you a first-class machine for less money. We repair all makes. Send us your inquiries.

Guarantee Electric Co.

CHAS. E. GREGORY, Pres.

153 to 159 S. Clinton St.,

CHICAGO

The New Popular Mechanics PREMIUM LIST

**Fully Illustrated
Is Now Ready**

**BOOKS FOR MECHANICS,
ELECTRICIANS, ENGINEERS
SHOP TOOLS OF ALL KINDS
SPORTING GOODS, WATCHES, ETC.**

Something for everybody given for
one or more new subscribers.

ADDRESS

**Popular Mechanics
JOURNAL BUILDING, & CHICAGO**

Please mention Popular Mechanics when writing Advertisers.

SEND FOR IT

MY revised list of machinery and contractors' equipment July issue, is now ready, and covers eleven printed pages with location and prices. I will be very pleased to send a copy to you if you will let me have your address.

Willis Shaw, Machinery

171 La Salle St.

CHICAGO, ILL.

100 horses being killed by lightning at Rapid City, S. D., on account of a non-protected wire fence, and of 40 head of cattle killed by lightning in Iowa, and so on more or less, all over the country. This point alone is worthy of the most careful consideration and is something which can only be prevented by thorough grounding of the wires, only to be accomplished by giving each wire a metal path to the earth.


Aside from the deficiencies mentioned in the concrete post, there is the additional expense and time involved in the digging of post holes, tamping, and the annoyance of long staples for each fastening. It would seem to the writer, viewing the relative merits of each, that the selection should largely preponderate in favor of the rust-proofed iron and of such a form as shown in the advertising pages of this magazine. In this construction lies the greatest strength with the least amount of material; there is no post holes to dig, nor staples used. It would seem to the undersigned that there is as much consistency in using metal for the post as metal for the wires. One should last as long as the other, and the posts, when past their stage of usefulness, are still valuable as scrap. I therefore believe that the metal post is the proper thing, being, as it is, rustless, lightning-proof, fire-proof, frost-proof, requiring no staples to use, nor holes to dig, and giving absolute uniformity and at low cost.

Omaha, Neb.

TIN PLATE PROCESS 400 YEARS OLD

Making tin plates, or the process of coating iron with tin, was invented in Germany about 400 years ago. The people of that country kept the process a secret for over a century, but after a long and diligent search English manufacturers, near the end of the seventeenth century, discovered the secret. In England, soon after this discovery was made, the process of rolling iron sheets was invented, the tin plate industry growing rapidly, and for nearly two centuries England maintained its supremacy in the industry, until about ten years ago, when our country became a strong rival.

TELEPHONE CLOCK.—To be placed over or near a telephone. When commencing conversation



on a toll line you press the button and at the expiration of the three minutes an alarm bell sounds.

MANUFACTURERS FOR INVENTORS

We have the best equipped plant in the United States for EXPERIMENTAL WORK, MODELS, METAL SPECIALTIES of all kinds.

Our line of work is essentially special, as we

MANUFACTURE TO ORDER FOR OTHERS

Shipments made direct to customers of our clients. Use of sales department lent, if desired. All facilities for boxing, shipping, etc.

SEND FOR BOOKLET containing full information of our method of doing business.

The AMERICAN SPECIALTY CO., Harvard, Ill.

"We Analyze Everything"

At Reasonable Rates. We Devise New and Original

Address **Formulæ**

The Ellsworth Laboratories

MAX D. SLIMMER, Ph. D.

857 Dearborn Street. - - - Chicago

UNPARALLELED FACILITIES FOR MANUFACTURING

Metal Specialties

OF ALL KINDS PROMPTLY AND REASONABLY
WILL MANUFACTURE DIRECT OR ON ROYALTY

Crescent Mfg. Co., Valparaiso, Ind.

The Largest Factory in the United States for Manufacturing Metal Specialties IS AT YOUR SERVICE
Write us for estimate on any article you want manufactured. Prompt and careful attention given all correspondence

FORT DEARBORN MFG. CO.

Manufacturers of

Incorporated 1895.

SPECIAL MACHINERY DIES, TOOLS, Etc.

Also Blanking, Forming and Drawing of Sheet Metal

63-65 Crossing Street - CHICAGO

Gear and Cam Cutting

Surface and Circular Grinding

Screw Machine Work

CRANE VALVES

ESTABLISHED 1855

Going to Put It on the Market?

You have the article; we have the brains and the equipment for making it at the lowest cost.
We manufacture and ship all kinds of Special machinery on contract.

LET US ACT AS YOUR FACTORY

JOHN WISHART MACHINE WORKS, Engineers and Machinery Mfrs. (Inc.) 43 to 45 S. Canal Street, Chicago.
LONG DISTANCE 'PHONE, MAIN 839.

YOUR INTERESTS AND OURS ARE IDENTICAL.




Fig. 31

Please mention Popular Mechanics when writing Advertisers.

You Want Practical

WELL DRILLING MACHINERY

to develop that

Mineral, Oil or Water

proposition; we have it. Guarantee it to work satisfactorily.

Tell us about the formations, depth, diameter holes; will send printed matter and can save you money.

THE AMERICAN WELL WORKS,

AURORA, ILL., U. S. A.

CHICAGO, ILL. DALLAS, TEX. S.

POPULAR MECHANICS

PATENT BUREAU

invites the co-operation of Inventors, Mechanical Engineers, Draftsmen, Machinists, Superintendents and Foremen of Shops and Mills, and Skilled Mechanics in all trades, everywhere, in building up a Patent Bureau that will give honest advice to inventors, protect their interests by good patents and strong contracts; assist inventors in perfecting their inventions, and in selling their patents when obtained; and in all matters to render careful service and give full value for money paid.

We have a Patent Bureau of which it can be said: "Conducted So You Can Trust It;" just as this magazine is "Written So You Can Understand It."

We have been getting patents for the past twenty-five years, and hope to be in the same business for another quarter of a century.

We want the business of practical, hard-headed inventors—not the perpetual motion cranks. We charge moderate fees for services rendered, and do not care for the business of those who expect something for nothing.

Our booklet about Patents contains much information in small compass, and you can depend on it. Send for a copy.

POPULAR MECHANICS
PATENT BUREAU,
Journal Building, : Chicago, Ill.

Have You An Idea?

PATENT IT. Send for Particulars.

LEWIS & COMPANY, Box 132, Washington, D. C.

NEW BOOKS.

PRACTICAL PLUMBERS' WORK. Edited by Paul N. Hasluck. Numerous illustrations; 160 pages; crown 8vo.; cloth, \$1.00. David McKay, Philadelphia.

This practical volume treats first the materials and tools used by plumbers, and then, step by step, in a manner readily understood, carries the subject through its several practical applications. The text is elucidated by illustrations. Among other subjects treated are sheet lead working, pipe bending, pipe jointing, lead burning and lead work on roofs.

CLAY MODELING AND PLASTER CASTING. Edited by Paul N. Hasluck. Illustrated; 160 pages; cloth, 50 cents. David McKay, Philadelphia.

This little book is intended for the use of the beginner and its text and illustrations are purely adapted to his requirements. It treats of drawing for modelers, tools and materials for clay modeling, clay modeling, modeling ornaments, modeling the human figure, casting in plaster from nature, finishing casts, etc.

WANTED

We want the names and addresses of parties who have small factories and who are looking for new things to make in their lines. Anyone sending us the names and addresses of such parties will be compensated for their trouble. Popular Mechanics Patent Bureau, Journal Bldg., Chicago.

TO OUR FRIENDS

If you have an acquaintance who has an invention and wants to know:—

1. Whether he can get a patent.
2. How much it will cost him to get a patent.
3. Whether it will pay him to get a patent.
4. How he can sell the patent after he gets it.
5. How he can get the most money out of his invention.

Tell him to write to Popular Mechanics Patent Bureau, Journal Bldg., Chicago, Ill., for free advice and information. Then write to the Bureau, and give the name and address of the inventor. You will be pleased with the results.

When You Want Anything

And Don't Know Where to Find It

Write Popular Mechanics

Your Ideas Developed

PATENTS PERFECTED EXPERIMENTAL WORK
EXPERT MODEL AND DIE MAKING

METAL SPECIALTIES MANUFACTURED

Punch, Press and Screw Machine Work, Brass Finishing, Oxidizing, Nickel Plating, Enameling. Thirty years' experience.

JOHN OLDFIELD, 937 North 41st Court, CHICAGO

Please mention Popular Mechanics when writing Advertisers.

PATENTS

SECURED PROMPTLY and with special regard to the Legal Protection of the Invention.

HAND BOOK FOR INVENTORS AND MANUFACTURERS SENT FREE UPON REQUEST.
Consultation Free. No charge for opinion as to the patentability and Commercial Value of Inventors' Ideas.

HIGHEST REFERENCES FROM PROMINENT MANUFACTURERS.

SHEPHERD & PARKER, PATENT LAWYERS

Patents, Caveats, Trade Marks, Copyrights, Validity Reports, Infringement Contests.

REFERENCES: American Water Motor Co., Blum Shoe Co., International Fence and Fire Proofing Co., Winget Concrete Machine Co., Century Chemical Co., By-Products Co., Columbus Pharmaceutical Co., Richmond Electric Co., M. C. Lilly & Co., N. L. Hayden Mfg. Co., Murray Engineering Co.

"During the past 10 years Mr. Shepherd, of Shepherd & Parker, has obtained for us a great many important patents. We have no hesitation in heartily recommending him to any one having need of the services of a patent attorney".

HALLWOOD CASH REGISTER CO.

Mr. Parker on November 1, 1903, resigned his position as an Examiner in the U. S. Patent Office to enter this firm.

Address, 210 Dietz Bldg., WASHINGTON, D. C.



PATENT YOUR IDEAS

\$100,000 offered for one invention; \$8,500 for another. Book "How to Obtain a Patent" and "What to Invent" sent free. Send rough sketch for free report as to patentability. We advertise your patent for sale at our expense. Chandler & Chandler, Patent Attorneys, 959 F. Street, Washington, D. C.

MODELS

CHICAGO MODEL WORKS
175-181 E. MADISON ST., CHICAGO, ILL.

ESTABLISHED 1867

WRITE FOR CATALOGUE
OF MODEL SUPPLIES

Wanted Toys and Novelties

We want Small Novelties and Toys to manufacture and sell on royalty. If you have Small, Useful Novelty, Toy or Advertising Article, send us sample or model and we will make you an offer. We have ample means and well equipped factory.

KUBEC MANUFACTURING CO.

666 W. Lake Street, - - - Chicago

PATENTS

SECURED OR FEE RETURNED

FREE opinion as to patentability. Send for Guide Book and What To Invent, finest publication issued for free distribution. Patents secured by us advertised free.

EVANS, WILKENS & Co.,

No. 717 F Street N. W. Washington, D. C.
New York Offices, 132 Nassau Street, N. Y. City

WE MANUFACTURE

Metal Specialties, Dies, Tools, Metal Stampings of all kinds, Screw Machine Work, Novelties, etc. Estimates cheerfully given. Send drawing or models.

Metal Specialty Mfg. Co.,

18-24 W. Randolph St., Chicago

PATENTS

Careful attention given to the prosecution of business before the patent office. Patents procured and no attorney fee called for until patent is allowed. (23 years experience.) Write for "Inventor's Guide." Address

Franklin H. Hough

Atlantic Building, Washington, D. C.

EXPERIMENTAL AND MODEL WORK

Inventors' Ideas Developed. Circulars Free.

WM. GARDAM & SON, (Inc.)
45-51 Rose St. New York

PATENTS

Save time and money by employing a Washington attorney.

WATSON E. COLEMAN,
Registered Patent Attorney

COLUMBIAN BUILDING, WASHINGTON, D. C.

Advice Free; Terms Low; Highest References; Best Service

PATENTS

Valuable Book on Patents FREE. Tells how to secure them at low cost. How to sell a Patent and What to Invent for Profit. Gives Mechanical Movements invaluable to Inventors. Full of Money-Making Patent Information. NEW BOOK FREE to all who write.

O'MEARA & BROCK, Patent Attys., 918 F. Street, Washington, D. C.
NEW YORK OFFICE, 288 Broadway, New York City



I SELL PATENTS

If you wish to buy or lease on royalty, patents on hardware or mail order specialties, machinery, in fact anything, write me.

INVENTORS desirous of selling their patents quickly and to the best advantage should register with me. I can save you time and money.

Charles A. Scott

796 Mutual Life Bldg.
Buffalo, N. Y.



Typewriters all makes

All the Standard Machines SOLD or RENTED ANYWHERE at HALF MANUFACTURERS' PRICES allowing rental to apply on price. Shipped with privilege of examination. Write for Catalogue TYPEWRITER EMPORIUM, 202 LaSalle St. Chicago

Cement Fence Posts

Cheap as wood, and will last forever. Made with simple and inexpensive tools. Fire proof, frost proof, wind proof.

Material used: Cement & Sand or Gravel. Will supplant Wood and Iron entirely. For part 1's write with stamp

A. D. MACKAY & CO.

Chamber of Commerce, Chicago



GOVERNMENT POSITIONS

Opportunity to prepare for U. S. Civil Service Examinations by mail. Salary to start \$600.00 to \$2500.00 per year; 50,000 appointments last year; many more next year. Manual of information and sample questions, 160 pages 50 cts. Catalogue FREE. Dept. 30.

AMERICAN COLLEGE OF CIVIL SERVICE, Valparaiso, Ind.

LOW PLUMBING BILLS

Get them by paying right prices for supplies. We sell

SUPPLIES AT WHOLESALE

You save 20% to 40% on every article. Highest grade goods and line complete. Free illustrated catalog gives all particulars. Write for it.

B. P. KAROL,

229 W. Harrison St., Chicago, Ill.



You Can Make

BIG MONEY

With My New PRIZE VENDING MACHINES

Best Novelty and Money Maker ever placed on the market. Operated with nickels. Also six other new style Vending Machines now ready. Write to Manufacturer for full particulars and prices.

THOS. H. SHERBORNE, 29 South 3rd Street, PHILA, PA

Andrews Office Desks



Have a name to their credit and are a CREDIT to their name, for they are made by

Specialists who know how.

STEEL TYPEWRITER

CHAIRS \$4. DELIVERED

The A. H. Andrews Co.

174 Wabash Ave., Chicago



BE YOUR OWN BOSS

MANY MAKE \$2,000 A YEAR

You have the same chance. Start a Mail Order Business at home. We tell you how. Money coming in daily. Enormous profits. Everything furnished. Write at once for our "Starter" and FREE particulars.

P. M. Krueger Co., 155 Washington St., Chicago, Ill

Great is Texas!

The Eyes of the World Are Upon Her

THE HOME-SEEKER wants to know about her "Matchless" Climate and Her Cheap Lands.

THE INVESTOR wants to know about not only Her Cheap Land and Low Taxes, but as well, Her Wealth of Mine and Forest, and this is to let you know that

The International & Great Northern Texas' Greatest Railroad

traverses more than a thousand miles of the Cream of Texas' Resources, latent and developed, and that you may learn more about the GREAT I. & G. N. COUNTRY by sending a 2-cent stamp for a copy of the ILLUSTRATOR AND GENERAL NARRATOR, or 25 cents for a year's file of same, or by writing

D. J. PRICE, G. P. & T. A., I. & G. N. R. R. Palestine, Texas

NEW CATALOGS.

OLDSMOBILE is the title of an attractive catalog issued by the Olds Motor Works of Detroit, Mich. The book illustrates the various machines of the company's make, stating the merits and particular adaptations of each and its price. There is a good deal of information on autos, incidentally.

DUMP CARS were invented in 1866. In their recent catalog under this title the Kilgore-Peteler Company of Minneapolis, Minn., illustrate and describe the dump cars of 1905, up-to-date in every respect.

MECHANICAL DRAWING.—Samples of the instruction plates used by the Grand Rapids School of Mechanical Drawing, Grand Rapids, Mich., illustrate in handsome manner the practicability of this system and likewise its simplicity. The student passes from one lesson to another without difficulty, so carefully has their sequence been arranged. Definitions and propositions appear in as brief form as possible and in all respects the task before the pupil has been greatly simplified.

ELECTRIC MOTORS AND DYNAMOS is the subject treated of in Bulletin No. 4 of the Barriett Electric Company. Several types of Barriett motors and dynamos are illustrated and described in detail. A portrait of S. L. Barriett, the inventor of the self-rolling bearing and the automatic release starting rheostat, is one of the features of the book.

How To Make Mirrors

We have for years sold our renowned Mirror Formulas, and hundreds of them at \$1.00, and a large number at \$2.00, and they are worth the money.

For a short time will make a SPECIAL PRICE of 25 cents and give you exactly the identical formulas sold at \$1.00 to \$2.00, provided you cut out and return this adv. with your order. We also tell you FREE OF CHARGE how to Emboss, Etch, Grind, Foil, Gold Leaf, Frost, Chip, and make Imitation Stained Glass. How to transfer Photos onto Glass. How to Bore Holes in Glass and Cut Sky Lights. All the above and more for the small sum of 25 cents. Money back if you are not pleased.

G. L. PATTERSON & CO.,

Chicago, Ill.

What Is Daus' Tip-Top?



TO PROVE that Daus' "Tip Top" is the best and simplest device for making 100 copies from pen-written and 50 copies from typewritten original, we will ship complete duplicator, cap size, without deposit on ten (10) days' trial.

Price \$7.50 less trade discount of 33 1/3%, or

\$5 net

THE FELIX S. K. DAUS DUPLICATOR CO. Daus Building, 111 John St., New York City

Please mention Popular Mechanics when writing Advertisers.

Iron Mountain Route

Has Territory Along Its Lines Which Offer

Rare Opportunities

For the Investor and Homeseeker

The Railroad That Carries
You Through the Heart of

Arkansas and Louisiana,

The Two Great Agricultural and
Timber States,

Where the Soil Is Rich, Deep
and Productive.

Prices Reasonable

Low Settlers' Rates

For full information and descriptive literature,

Address **H. C. TOWNSEND,**

General Passenger and Ticket Agent, - ST. LOUIS, MO.

ELLIS FARNSWORTH, D. P. A., 186 Clark St., Chicago, Ill.

500 BOOKS

Our new catalog of latest mechanical and technical books, now ready. Write for a copy.

Want a

Typewriter Free?

It takes no money and very little effort to earn A FINE TYPEWRITER. This is certainly the greatest offer we have ever made. Write at once for "How To Get It."

Popular Mechanics,
JOURNAL BUILDING, CHICAGO

HOW ONE MAN MADE MONEY

A STORY OF SUCCESS



GEORGE W. HOMAN

One year ago George W. Homan, of 221 South Linden Street, Carthage, Ohio, was situated like thousands of young men who have no particular employment. He earned little, spent it all, and made no progress toward that success which all young men crave. He was more than half-way satisfied with himself because he did not appreciate the value of the time he was wasting. An idle hour meant no appreciable loss to him.

One day he picked up a paper and discovered that he could learn bookkeeping at his own home at a small cost and have someone outside of himself interested in getting a position for him. This made him think. The result was that he wrote to the Commercial Correspondence Schools, Rochester, N. Y., for full information. After considering it carefully, he took up their course.

This is an extract from a letter written eight months afterwards: "Through the knowledge I received from your course, I was offered three fine positions. I took the one I now have. My wages have been increased, and I am earning more than twice as much money as at first. I am now married and have money to spare, and have a nice home. I owe it to you. I do not keep books at present, and I tell this because one of the arguments against my taking bookkeeping was 'Once a bookkeeper, always one.' I said it was not so, and I have proved it. Bookkeeping is the stepping stone to a higher position in the business world. If it were not for the knowledge I received from your course, I would not be where I am now in business."

The Commercial Correspondence Schools will send you its free book, "How to Succeed in Business." This is the book that started Mr. Homan on the road to success. It tells you how you can learn bookkeeping and pay your tuition after you have been placed in a profitable and permanent position. It tells about the best system of accounting ever devised. It is full of valuable information that will help you succeed in life and push your way forward in business.

A limited number of these books will at present be sent absolutely free to any ambitious person who sincerely desires to better his position in life. Write to Commercial Correspondence Schools, 19 A, Commercial Bldg., Rochester, N. Y. All you need to do is to send your name and address on a postal card. You will receive the book by return mail.

Please mention Popular Mechanics when writing Advertisers.

The National Lines of Mexico

NATIONAL RAILROAD OF MEXICO
MEXICAN INTERNATIONAL RAILROAD
INTEROCEANIC RAILWAY OF MEXICO

MEXICO'S GREATEST RAILWAY SYSTEM

All Year Tourist Rates
and Homeseekers'
Excursion Rates

Daily Pullman Service
between St. Louis, Mo.
and City of Mexico

VIA

LAREDO ROUTE

578 Miles Shortest 22 Hours Quickest

—Affording—

The Only Through Pullman Service

The Republic of Mexico abounds in attractions for
Tourist, Prospector and Investor, and the Capital

MEXICO CITY

The Paris of America

is an all-year resort unsurpassed.

Average temperature:

Summer 63 deg., winter 53 deg. Fahr.

Only line affording diverse route without extra charge.

For illustrated descriptive literature, rates, sleeping car
reservations, etc., call on or address

GEO. W. HIBBARD,
General Passenger Agent,
Apartado No. 322
Mexico City, Mexico

G. R. HACKLEY,
General Western Agent,
Suite 230-240 Quincy Bldg.,
Chicago, Ill.



**"FOLLOW
THE FLAG"**

WABASH Summer Tours

Write today for a Free copy
of **WABASH Summer Tour
Book—1905**, outlining many
very attractive summer vaca-
tion trips, with rates, etc.

Write us about any tour you
may have in contemplation.
We shall be glad to assist you.

C. S. CRANE,
G. P. & T. Agent,
ST. LOUIS.

F. A. PALMER,
A. G. P. Agent,
CHICAGO.

INDUSTRIES

ARE

OFFERED

LOCATIONS

WITH

**Satisfactory Inducements
Favorable Freight Rates
Good Labor Conditions
Healthful Communities**

ON THE LINES OF

THE ILLINOIS CENTRAL R. R.

AND THE

YAZOO & MISSISSIPPI VALLEY R. R.

For full information and descriptive pamphlet, address

J. C. CLAIR

Industrial Commissioner

1 Park Row, - - - Chicago, Ill.

The Overland Limited California

the most luxurious train in the world,
leaves Chicago 8:00 p. m. daily. Less
than three days to San Francisco.
Magnificent equipment. Electric lighted
throughout.

THE BEST of EVERYTHING

Two other fast trains leave Chicago 10
a. m. and 11:35 p. m. daily, with through
service to San Francisco, Los Angeles
and Portland via the

**Chicago & North-Western,
Union Pacific and
Southern Pacific Railways**

All agents sell tickets via
this route.

Illustrated booklets on
application to
W. B. KNISKERN,
CHICAGO, ILL.
or **E. L. LOMAX,**
OMAHA, NEB.

OL16

25 Cents **BOOK** **25 Cents**
— FOR —
BOYS

**"Mechanics for
Young America"**

Tells How to Make Things

Reprinted from the Boys' Department of Popular Mechanics. Fully Illustrated. Instructions are "Written so you can understand it."

CONTENTS

How to Make a Paper Boat.....
How to Make a Barrel Boat.....
How to Make a Water Wheel.....
How to Make Your Own Fishing Tackle.....
Temporary Camps and How to Build Them.....
Permanent Camps and How to Build Them.....
How to Build an Imitation Street Car Line.....
How to Make a Water Bicycle.....
How to Make a Miniature Windmill.....
How to Build an Ice Boat.....
A Novel Burglar Alarm.....
A Mechanical Ventriloquist and How to Make It.....
How to Make a Boot-Blackening Cabinet.....
Renewing Dry Batteries.....
How to Make Water Motors.....
How to Make "Antique" Clocks from Up-to-Date Materials.....
Lettering a Clock Dial.....
How to Make a Windmill of One or Two Horse-power.....
How to Make a Trap for Rabbits, Rats and Mice.....
How to Make a Small Searchlight.....
Kites of Many Kinds and How to Make Them—Jug Fishing.....
How to Do Ornamental Iron Work.....
Ornamental Metal Guards for Open Fireplaces.....
How to Make a Propelling Vehicle.....
How to Make a Water Telescope.....
How to Make Paper Balloons.....
How to Make a Hectograph.....
Useful Articles and Ornaments Made of Old Bicycle Parts.....
Devices for Winter Sports—How to Make and Use Them.....
Coasting Sleds, Chair Sleighs, Toboggan Slides and Skis.....
How to Make Rubber Stamps.....
How to Make a Baggage Carrier for Bicycles.....
A Water Candlestick.....
Boys' Hand-Power Auto—How Made.....
How to Make a Pair of Dumb-Bells.....
How to Rid Your Yard of Cats.....
How to Make an Easel.....
To Light a Gaslight Without Matches.....
Things a Boy Can Make Out of old Bicycle Parts.....
How to Make a Wind Propeller.....
Photographing from a Captive Balloon.....
How to Make a Simple Burglar Alarm.....

Sent postpaid on receipt of 25 cents, or order from your newsdealer.

Popular Mechanics,
Journal Building. . . Chicago

**EVERY BOY
His Own Toy-Maker**



It tells you how to make a Steam Engine, a Photographic Camera, a Windmill, a Microscope, an Electrical machine, a Galvanic Battery, an Electric Telegraph, an Electrotyping Apparatus, a Telephone, a Kaleidoscope, a Magic Lantern, an Aeolian Harp, Boats of every kind, from a little rowboat to a full-rigged schooner; how to make Kites, Balloons, Paper Toys, Masks, Card Racks, Wagons, Carts, Toy Houses, Bows and Arrows, Pop Guns, Slings, Stilts, Fishing Tackle, Rabbit and Bird Traps, and many other things, and all is made so plain and simple that any boy can easily make anything described. The whole is illustrated with more than 200 handsome illustrations. This is a great book and you should not be without it. Price only 10 cents, postpaid, 3 for 25 cents. Address WESTERN SPECIALTY CO., 336 Jackson Street, St. Paul, Minn.

ELECTRIC RAILWAYS

Dynamos : Motors : Gas Engines




Complete Working Models, also Castings and Parts. Everything for the Amateur Electrician. Send for Catalogue B

The CARLISLE & FINCH CO.,

262 E. Clifton Ave.

Cincinnati, Ohio

ELECTRIC MOTOR, 75c.



An entirely new design. Runs with a wet or dry battery. Has 2-inch armature, wrought iron field magnet, pulley, etc. 75 cents; packing and postage, 15 cents. Catalogue Free.

Electro magnets for experimenting, 15 cents each.

Send 10 cents for 20 feet of magnet wire for experimenting and making small magnets.

ARTESIAN ELECTRIC CO., 744 Artesian Ave., Chicago

FIGHTING ROOSTERS

Mytify and amuse your friends. These are two genuine game roosters with feathers. They fight to a finish, and are always ready to fight. The secret of their movements is only known to the operator. Will last a lifetime. 10c per pair, 3 for 25c.



Postpaid and one big bargain catalogue free.

ADDRESS

**W. H. MILLER & CO., - 739 E. 4th St.,
ST. PAUL, MINN.**

HUNTING
CASE
GENTS
OR
LADIES
SIZE



This ELEGANT Watch \$3.75

Before you buy a watch out this out and send to us with your name and address, and we will send you by express for examination a handsome **WATCH AND CHAIN C. O. D. \$3.75.** Double hunting case beautifully engraved, stem wind and stem set, fitted with richly jeweled movement and guaranteed a correct timekeeper; with long Gold plated chain for Ladies or vest chain for Gents. If you consider it equal to any \$25.00 GOLD FILLED WATCH Warranted 20 YEARS pay the express agent \$3.75 and it is yours. Our 20 year guarantee sent with each watch. Mention if you want Gents' or Ladies' size. Address **J. FARRER & CO., 331, 28 Quincy St., CHICAGO.**

EVERY INVENTOR

Who Wants to know

1. What are the most profitable inventions,
2. How to perfect inventions,
3. The first step to take in getting a patent,
4. How to protect himself from parties who might steal his invention before he can get a patent,
5. How to find out what patents have been granted on inventions like his, or intended for the same purpose,
6. How much it costs to get a patent,
7. How long it takes to get a patent,
8. What protection a patent is,
9. How he can sell his patent after he obtains it,
10. How to handle his patent to get the most money out of it,
11. Where and at what expense he can have working drawings made of his invention,
12. Where and at what expense he can have models or experimental machines made,

should send his questions to

**POPULAR MECHANICS PATENT
BUREAU,**

Journal Bldg. - - Chicago, Ill.

RHEUMATISM

ABSORBED FROM THE BLOOD

The Capillaries now reached through the large foot pores and forced to yield down their acid impurities. New treatment discovered which is sent to anyone

FREE TO TRY

If you have rheumatism, send us your name to-day. You will get by return mail a pair of Magic Foot Drafts, the celebrated discovery which is accomplishing such marvelous results in all the rheumatic countries of the world. Try the Drafts thoroughly, then if you are fully satisfied with the benefit received, send us One Dollar. If not, keep your money. You are the sole judge. We can afford to make this offer only because the Drafts *do* cure, and people are willing and glad to pay for them.

Magic Foot Drafts are worn as shown and cure by reaching the capillaries through the large foot pores and absorbing acid impurities directly from the blood, without which purification rheumatism cannot be cured. Thousands all over the world are already rejoicing over their safe and inexpensive cure without medicine, and we have their grateful letters to show. Don't you want to try this treatment free? Write to-day to Magic Foot Draft Co., 1051 Oliver Bldg., Jackson, Mich. Our valuable book (in colors) on rheumatism comes free with the trial Drafts. Send no money—only your name and address.



HYDRAULIC DRAIN JOINTER.

This drain jointer which is an English device is described in the London Plumber as consisting of a pair of rubber discs mounted on a sliding piston connected to a cylinder, into which water is pumped under pressure, and by which pressure the two discs are brought close together. The appliance is placed in the entrance or opening of a drain, the space between the discs then filled with Portland cement wet to a plastic condition, and then dragged into the drain by means of a rope and a special hauling lever.

As soon as the jointer has traveled a foot or two inside the drain, a hydraulic pump, with a pressure gauge attached, and a flexible steel hose connection to the traveling appliance, is put into action. During the time the appliance is being dragged through the drain, the pressure gauge is closely watched, and the pump is kept working until the gauge again shows a pressure of about 100 lbs. to the square inch. The cause of the loss of pressure is a defect in the drain into which the plastic cement is forced until it is filled up and made perfect. The hauling lever is then again brought into action and the jointer dragged forward until another defect has been discovered.

POPULAR MECHANICS SHOP NOTES FOR 1905

Second 10,000 Edition

Easy ways to do hard things.
Of daily use to every mechanic.

"Worth it's weight in gold,"

—writes one

"Best book I ever had,"

—says another.

REVISED AND ENLARGED
FOR 1905

Compiled from the "Shop Notes"
Department of Popular Mechanics
up to and including Volume VI.

200 Pages--385 Illust's

"INDEXED SO YOU CAN FIND IT"

For Sale by all Newsdealers

Price Postpaid 50 cents

POPULAR MECHANICS
JOURNAL BUILDING
CHICAGO

Please mention Popular Mechanics when writing Advertisers.

FREE

HAIR
FOOD



FALLING HAIR AND BALDNESS ABSOLUTELY CURED

There is but one way to tell the reason of baldness and falling hair, and that is by a microscopic examination of the hair itself. The particular disease with which your scalp is afflicted must be known before it can be intelligently treated. The use of dandruff cures and hair tonics, without knowing the specific cause of your disease, is like taking medicine without knowing what you are trying to cure. Send a few fallen hairs from your combings, to Prof. J. H. Austin, the celebrated Bacteriologist, who will send you absolutely free a diagnosis of your case, a booklet on care of the hair and scalp, and a sample box of the remedy which he will prepare specially for you. Enclose 2c postage and write to-day.

PROF. J. H. AUSTIN
456 McVicker's Theatre Bldg., Chicago.



Write for free Booklet *Illustrated from Life* "Cure yourself by ELECTRICITY"

This wonderful book is compiled from the best authorities in the world. Explains how electricity, nature's greatest gift to man, the mysterious "Life Force" as supplied by inexpensive Batteries cures Rheumatism, Dyspepsia, Insomnia, Liver and Kidney Trouble and all nerve affections and diseases due to poor circulation. Explains fully how to enjoy the famous Electric baths, beauty and health massage at home.

Write today for this valuable book, it will be sent free, postage prepaid.

DETROIT MEDICAL BATTERY CO.
1062 Majestic Bldg. Detroit, Mich.

"Want" and "For Sale" Ads. 2 cents per word, payable in advance. Replies may be sent to a number, care Popular Mechanics, and will be forwarded promptly without extra charge.

"SHOP NOTES"—Paper covers 50 cents. Popular Mechanics.

AUTOMOBILES.

AUTOMOBILE SCHOOL.—Chicago School of Motoring; the original automobile school in Chicago. One hundred and eighty graduates the past year, to whom we refer upon request. Automobile owners, prospective buyers and young men wanting to become expert chauffeurs will save a great deal of money and a lot of worry by studying the mechanism, care and repair of gasoline automobiles, in our shop, where all parts are open so you can see how they are made, and how they operate. We give thorough and practical instruction. Competent chauffeurs supplied. Address, Chicago School of Motoring, Dept. B., 264 Michigan Ave., Chicago, Ill.

FOR SALE.—Complete set 1½ h. p. motorcycle castings with blue prints, \$6.00. Also a good Kingston carburetter, \$10.00. Several pairs new automobile baskets at interesting prices. Address Jesse C. Pope, Huntingdon, Pa.

FOR EXCHANGE.—One light automobile. Running gears ready for the power. Will exchange for 4 h. p. air cooled motor. Address H. C. Hiatt, Neoga, Ill.

FOR SALE.—One new motorcycle engine 1½ h. p. with accessories, \$25.00. Write Ardene Goodenow, Albion, Mich.

FOR SALE.—Big bargain, Marr auto car, strong, sturdy runabout in pink of condition. Run only about 600 miles. Will sell for less than one-half cost price. Don't miss this opportunity. The Starin Co., North Tonawanda, N. Y.

WANTED.—Small Runabout, must be cheap and in good condition. Write William Lezatte, Walshville, N. Y.

FOR SALE OR EXCHANGE.—Two sets automobile gasoline engine castings; one nearly finished. Want small lathe. B. Sprinkel, Springfield, Ill.

FOR SALE.—Michigan runabout, gasoline, little used, everything first-class, \$300. Address A. W., care Popular Mechanics.

FOR SALE OR EXCHANGE.—Automobile gear. Address C. C. H., 18 North Front St., Columbus, O.

FOR SALE OR EXCHANGE.—4 h. p. automobile or boat 4 cycle gasoline engine. Address A. P. C., 18 North Front St., Columbus, O.

BUSINESS CHANCES.

FOR SALE.—Eleven hundred and fifty acres pine timber. Double circular saw mill, twenty thousand capacity; cable feed, live rolls, gang edger, log turner and log haul, steel head blocks, shingle mill and planer. Good buildings, all new and modern. Big Bargain. For particulars apply to J. J. Patterson, Eagleville, Modoc Co., California.

FOR SALE.—A well equipped machine shop in southern Michigan, doing a good business. Price, \$3,000. Splendid opportunity for a good business mechanic. Address No. 987, care Popular Mechanics.

Six Thousand acres of fine timber land in Idaho (deeded) for sale cheap if taken soon. Address W. J. Ramey, Nezperce, Idaho.

FOR SALE.—Small Machine Shop. Established trade—in Southwestern Michigan. Only exclusive jobbing shop here. Population, 5,000. Address 898, care Popular Mechanics.

ATTENTION.—Mechanics, Salesmen, etc. We have an unusual and original plan and not at all one-sided, which we ask to present to you if you desire to begin a most profitable manufacturing business at your home or business place without other expense than materials from \$25 to \$50. Write Dept. M., The Cardinal Mfg. Co., Cleveland, O.

FOR SALE.—Well equipped machine shop in state capital; a money maker; \$2,500. Other business reason for selling. Schaefer Bros., Holmes St., Frankfort, Ky.

FOR SALE.—General repair shop and second-hand store. Town of 3,000. No competition. Will sell all or part. S. Blosser, Council Grove, Kan.

FOR SALE.—75 cents on the dollar buys almost new stock of jewelry tools and fixtures. Value about \$1,800. Other business demands attention. Write at once. W. H. Y., care Popular Mechanics.

BLACKSMITHS.

GOOD BLACKSMITHS ARE SCARCE AND BUT FEW LEARNING THE TRADE.

And the smith comes first of all professions or trades. The smith must make the tools first for all from the surgeon to the safe blower, by using Toy's Treatise on new steels explaining how to work them with 75 new methods for working all difficult jobs. Ten receipts for making your own compounds for welding different kinds of steel solid. Thermite welding fully explained; also two colored tool tempering charts; chart A explains all annealing and hardening; Chart B explains both scientific and plain tempering to a standard. All the above for \$1.00. Valuable samples free. W. M. Toy, Sidney, Ohio.

EDUCATIONAL.

FOR SALE.—Complete course in the International Correspondence School on Electrical Mechanical Engineering, with 6 volume library and electrical outfit, \$60.00 cash, or \$65.00 on installments. Write Mr. E. H. Hansen, 175 N. 51st Ct., Chicago, Ill.

FOR SALE.—A General Illustrating course in the International Correspondence Schools. Address N 11, Popular Mechanics.

FOR SALE OR EXCHANGE.—Complete Sheet Metal and Drafting course in the International Correspondence School. Address No. 935, Popular Mechanics.

TECHNICAL AND CATALOG translation into Spanish, Portuguese, French, Italian and German. Work guaranteed correct. L. G. Prieto, 614 185 Dearborn St., Chicago, Ill.

IF THERE'S a book you need, and can't locate it, Popular Mechanics can.

P. A. Westerwald, of 154 S. Maple St., Akron, O., wishes to correspond with anybody having "Pops" for January, February, March and April, 1905, to dispose of.

A PRACTICAL BOOK, "Dies and Diemaking." Postpaid \$1. J. L. Lucas, Bridgeport, Conn.

ANYONE WISHING TO SELL missing numbers of Horseless Age, 1905; Popular Mechanics, 1905; Power, 1903; Automobile, 1903; Motor World, 1904; Motor Age, 1903. Mrs. C. F. MacDermot, Hotel Wentworth, New Castle, N. H.

FOR SALE

FOR SALE OR EXCHANGE.—Barnes No. 4 lathe, in good condition, dirt cheap. What have you? W. L. Howland, Monmouth, Ill.

FOR SALE.—Sixteen foot steam launch, burns gasoline or coal. Will exchange for small steam runabout. William Lezatte, Walshville, N. Y.

FOR SALE.—Small dynamo-motor; a great bargain. Write Denton, 12th St., Newark, N. J.

FOR SALE.—8x8 Air Compressor; 8 h. p. Electric motor; 2 h. p. Gasoline engine; 2 Emery stands. Also a full set of patterns, and a lot of castings for 2 h. p. up-to-date Gasoline Engine. Will sell cheap; going out of business. J. F. Schulz, North Chicago, Ill., Box. 176.

FOR SALE OR EXCHANGE.—Rug and carpet loom in good condition. Address O. Bashford, Poplar Grove, Ill.

FOR SALE.—\$7.00 Gasoline Study Lamp, in fine condition, \$3.00; \$5.00 Telegraph Instrument, \$2.50. Edward Jaekel, 1100 S. 6th Av., LaCrosse, Wis.

FOR SALE.—Automobiles; two hundred and up; send 3 cents for cuts. Also castings. Wm. Riggs, Wing, Ill.

FOR SALE.—Cheap, 4x6in. Vertical Engine; 2 Steam Pumps; 1 Circulating Pump; 1 8-h. p. Gasoline Auto Engine. Perry Bros., 467 W. Madison St., Chicago.

FOR SALE—Castings or emery grinder head and countershaft that you can build on a 9-in. lathe. Small steam engine and sewing machine motor castings. We make patterns from drawings. Blue prints of grinder and countershaft, 25 cents. Salineville Model & Machine Works, Salineville, O.

FOR SALE—The following gasoline engines:
 Beebe, 3½ H. P. Marine Engine.....\$50.00
 Wipern, 2½ H. P. Auto Engine..... 50.00
 Fox, 2 H. P. Marine Engine..... 45.00
 Fleming, 1¼ H. P. Bicycle Engine..... 25.00
 Hummer, 1¼ H. P. Stationary Engine..... 50.00
 Tuttle, 2 H. P. Stationary Engine..... 50.00
 "We need the room." Lenox Machinery Co., 10 S. Clinton St., Chicago.

HELP WANTED.

WANTED SALESMEN—The Tropical Oil Company, Cleveland, O., will arrange on salaried basis with lubricating oil salesmen for territory not covered; can also use on attractive commission proposition few good salesmen without previous experience in this line, which is easily learned. Communicate with us.

ELECTRIC BELL AND INSTRUMENT makers wanted at once. Address Morse Electric Instrument Co., Grand Crossing, Ill.

WANTED.

AGENTS WANTED for Farmers Stand-by. Eight tools in one. Fastest seller ever put on the market. Write for descriptive circular and agents' terms to B. W. Tucker, Chickasha, Indian Territory.

AGENTS TO SELL my Callipers and Levels; good pay. Ernst G. Smith, Columbia, Pa.

WANTED—Motor-Cycle in A 1 condition; must be cheap. J. Hall, Waterville, Kans.

MECHANICS, SALESMEN, CLERKS, ETC.—We will start and instruct you free in manufacturing various grades of Elastic Carbon Graphite paints at your home. No further expense than \$25.00 to \$50.00 in materials which we make. If a beginner follows our plan and does not succeed in manufacturing, it will cost him nothing. This unusual offer is made to establish new manufacturers at once. Write Dept. M., The Cardinal Mfg. Co., Cleveland, O.

WANTED—Second hand, 20 to 30 horsepower saw mill engine and boiler. Address Nathan C. Dudley, R. F. D. No. 2, Guilford, Conn.

WANTED—Position as electrician in Shop, Mine or Factory. Twelve years' practical experience. Competent to assume full charge of plant. All references. D. M. Rhoades, 248 S. Main St., Canandaigua, N. Y.

WANTED—TO ACT as manufacturer's agent for good paying line. Address F. C. Erkel, Minneapolis, Minn.

MISCELLANEOUS.

BRAINS FOR SALE—Do you want a prospectus written and illustrated for your new company or syndicate? Do you want one that will command attention and sell shares? Do you need a catalogue or booklet that will not be thrown in the waste basket? If so write to Expert, care of Popular Mechanics, Journal building, Chicago.

WHEN YOU WANT anything and don't know where to get it, write Popular Mechanics.

WANTED—If you have anything in light metal manufacturing, job or experimental work, write me. Lowest prices. Schwabe & Son, 55 W. Washington St., Chicago.

A PRACTICAL BOOK, "Dies and Diemaking." Postpaid \$1. J. L. Lucas, Bridgeport, Conn.

WANTED—If you want a gas or gasoline engine designed for any purpose, address "G. E. Designer," care Popular Mechanics.

WILL MANUFACTURE and place on the market any machine or device. Machinery, etc., to be designed or developed will receive my prompt and careful consideration. Let us figure on your work. Edward Lindmueller, Williamson Bldg., Cleveland, O.

DON'T FORGET to get our price on our medical batteries this month; all sizes and prices. Get our price first. Smith Electric Supply House, 207 and 213 E. Van Buren St., Chicago, Ill.

SOMETHING NEW!—Our Magic Engraving Fluid is used with a rubber stamp. Marks all tools and metal articles permanently. Best seller on earth. Sample package and agent's terms, 25 cents. Address Gem Specialty Co., Box 262, St. Cloud, Minn.

WANTED—Small metal specialties to manufacture. Expert die making. Press and screw machine work. Plating of all kinds. Prices right for quantities. John Oldfield, 937 W. 41st Court, Chicago.

MECHANICS, SHOPMEN, ETC., can have a regular, or side line manufacturing business at their home, or shop without other expense than materials which we furnish to manufacture Elastic Carbon Graphite paints. We instruct beginners free with first order for materials. Sales to merchants and consumers afford unusual profits. We want manufacturers where we have none, hence this unusual offer. Write Dept. M., The Cardinal Mfg. Co., Cleveland, O.

STEEL, BRASS, WOOD STAMP—Ten cents a letter; seals, doorplates, embossing wood cuts, 75 cents. Stationery embossing dies, \$1.50. Presses, \$3.00. Postal brings price circular. J. Kiola, engraver, 155 W. Madison St., Chicago, Ill.

ELECTRIC SCIENCE LIBRARY, 6 vol., new, \$12; cost \$18. 3½ K. W. D. C. 110 V. Dynamo, Columbia Graphophone and 42 records. Enclose a stamp. J. Homer Boals, Salineville, O.

MECHANICS SEND ten cents for blueprint chart of Standard Nuts and Bolts. Also list of many others. Big inducements to agents. E. J. Milo, 14 Bridge St., Newark, N. J.

BICYCLE POWER—Crank attached to any grindstone by bolts; no shaft; bearings on each crank. Applied to any pulley for driving machinery, best foot power. One dollar per pair. Patents for sale. Agents wanted. J. H. Norrell, 1402 Gwinnett St., Augusta, Ga.

FOR SALE—LATEST TRICK—How to remove a man's shirt without removing his coat. Send 10 cents for full particulars. Wm. Kirsch, Magician, 170 Belmont Ave., Newark, N. J.

STRICT ORDERS

The following notice was observed posted in the engine dispatcher's office at the roundhouse in a neighboring town on one of the railroads running out of Albany: "Trainmen on passenger trains must not go through the coaches with overalls on, without first taking them off."—Albany Journal.

TELEPHONE TROUBLES AND HOW TO FIND THEM

This little book is strictly up-to-date on all matters pertaining to telephone troubles and their remedies on both Magneto and Central Energy Systems; contains diagrams on the following subjects:

"Low and High Wound Frequency System" for four party lines,
 "How to Test and Repair Toll Lines,"
 "New Specifications for Inside Wiring,"
 "The Use of Condensers for Rural Lines,"
 etc.,

making the book much more complete than previous editions.

Price postpaid 25 cents a copy, by Popular Mechanics.


VENTRILOQUISM

Learned by anyone at home. Small cost. Send 2-cent stamp for particulars and proof.
 O. A. SMITH, - Box 5, 2040 Knoxville, Ave., - Peoria, Ill.

WONDERFUL

EDISON OFFER

If you love music, if you enjoy entertainment, if you want to make your home more cheerful, **BE SURE** to read every word of this great offer



Read What Mr. Edison Says:

"I want to see a phonograph in every American home."

For the phonograph has become this great inventor's hobby. It has given more pleasure and happiness to mankind than any other of his products and today Mr. Edison has dropped his financial interest in practically all his other patents, concentrating his efforts on the phonograph, which he has now brought to perfection. Mr. Edison personally owns almost every share of stock in the phonograph company. It is his pride and pleasure. He wants to see a phonograph in every home.

Now is your opportunity—we want every honest, responsible and reliable person to read this

GREAT FREE TRIAL OFFER

While this offer lasts—every responsible person can get on **free trial** A GENUINE EDISON phonograph direct from us to your home without deposit, without guarantee from third parties, without formality of any kind.

Try it in your home, play the stirring waltzes, marches, two-steps, concert pieces, minstrel dialogues, beautiful vocal solos and other beautiful Edison gold moulded records: play all these, and if then you don't care to keep the outfit, send it back at our expense. We charge you nothing for the trial.

But Mr. Edison knows you will be glad to keep his phonograph, for you may keep it now by sending only a small sum after free trial, balance in monthly payments.

\$2.00 A MONTH now pays for a genuine Edison Gem phonograph (larger installments for larger instruments). A nickel to a dime saved a day will buy a genuine Edison without interest on payments and at exactly the lowest net cash prices.

THE PURCHASE OF A PHONOGRAPH is the most generous of gifts for any member of the family to make. The purchaser not alone enjoys it, but the entire household and friends. There are none too old or none too young to take pleasure in the phonograph.

Can you imagine a more enjoyable winter's evening than spent in your comfortable sitting room by the fire and listening to the realistic reproduction of an endless variety of musical selections, comic recitation and minstrel records?

One of the distinctive Edison features is that you can make records in your own home, and that this can be done so conveniently. For parties and entertainment the making of records will prove one of the most enjoyable features.

THE EDISON PHONOGRAPH plays in perfect dance time waltzes, two-steps, lancers, quadrilles, and all other of the popular dances. The records are amply loud for large halls.

You cannot realize how many other pleasures you will derive from an Edison phonograph until after you have it in your home.

Don't delay. If you are a responsible person and want this great offer, write at once for free illustrated catalog of Edison Gem, Edison Standard, Edison Home and Edison Triumph phonographs, also free catalog of 1,500 Edison gold moulded records. Address

MR. BABSON, Manager

302 Wabash Avenue, Dept. 126A.

Chicago, Ill.

FREE

Our new style Camel's hair clip brush for automatically cleaning records, thus greatly improving the sound, will be sent absolutely free to owners of Edison phonographs who send number and letter of their machine.

We accept old machines in exchange for new phonographs.



DON'T SPECULATE • • TAKE A CERTAINTY

Would you be open for an investment which will yield, with reasonable assurance, from 50 to 100 per cent each year?

An investment that will enable your surplus earnings to work with you and shorten the road to wealth. Not a get-rich-quick scheme, but a get-rich-sure investment, that is sure as the seasons, and increases as they roll by.

Study it out for yourself: A rubber plantation in the finest rubber zone in the tropics: 200 to 250 trees per acre; two pounds of rubber and upwards to the tree, worth now \$1.40 per pound, gold. No speculation in that. Rubber is worth the money, and we have the rubber.

Our rubber plantation consists of 6,000 acres; enough developed to insure its success, making a certainty of an enterprise that is within the reach of any prudent working man that can save from \$2.50 to \$12.50 per month from his earnings.

The contract protects you in misfortune, sickness or death.

Send today for our prospectus and further detailed information.

MONTEZUMA AGENCY

1107 Ashland Block, - - - Chicago



THE NEW DEPARTURE RAZOR,

The razor that holds its edge.

Unlimited Guarantee.

Has the thought ever struck you to shave yourself?
That it is really the only clean way to do?
That you can do it better than your barber?
Why not send for one of our booklets, (Free) "Hints to Shavers." Also our "Booklet of Illustrations." You will find it interesting.

Our New Departure, with "the only perfect edge"	-	Price, \$2.50
Our Magnetic Razor,	-	Price, \$1.00

The only dollar razor made of Clauss steel
Try it and be convinced.

Will send on trial, upon request.

Those who are not accustomed to shaving will be furnished with a guard, without extra charge.

The only genuine way of shaving, with safety.

Ask your dealer for the above

All leading dealers sell Clauss Razors, but if yours does not, order direct from the cutler.

"Clauss,"

9 First St., Fremont, Ohio.

Make Your Money Earn A Big Income



Small Investment Quick Profit

Your opportunity is just as good as that of Joseph Orsi, Elkins, West Virginia, who says: "The Elk Machine is all right. It is a good money maker. I have run it just 14 days and it sold me \$80 worth of cigars."

O. R. Terry, Meadville, Pennsylvania, wrote us: "The Elk Machine you sent me is a dandy. It took in \$42.29 the first twenty-four hours."

THIS WONDERFUL MACHINE that makes so much money is the Mills Elk, a Fortune Teller with a card and check paying feature.

After three weeks use, Mr. J. R. Kelly, Charleston, South Carolina, wrote: "The Elk Machine has now been in operation three weeks and has had a pay of \$400." The Elk requires very little attention. Max and Billy of Wheeling, West Virginia, say: "The Elk certainly is the best machine we have ever had, as it needs no attention as most machines do, which is a saving of much time when one is busy."

Increase Your Business

This is one of 200 different coin operated Mills machines daily earning big money for their owners. It does not matter whether you live in a small town or a big city, Mills machines will earn you a large income without much work or worry. You just count the profits. If you have any sum of money—\$15 or more—to invest in a sure money maker, don't fail to write today for our booklet N. 58, about trade stimulators and say that you want to know more about the Mills Elk.

Mills Novelty Co.

11 to 23 South Jefferson Street, Chicago, Ill.

The WARNER "LITTLE WONDER" WATER MOTOR



A Complete Grinding and Polishing Outfit

Indispensable for home and general use. Saves hours of time and makes silverware and cutlery shine like new. Sharpens edged tools of every description, shears, knives, hatchets, etc. Will run a small dynamo, sewing machine or other light machinery. In every home this motor will fill a long felt want. Dentists, doctors, butchers, cooks, jewelers, carpenters, plumbers and mechanics generally will find this machine of immense value.

Price complete, including emery wheel, pulley wheel for power transmission, 2 buffing and polishing wheels, and sticks of silver and steel polishing composition.....\$4.00

Motor attaches directly to standard threaded faucet or by means of our "universal connection" to any smooth faucet. Absolutely practical. Universally successful. This is not a toy and we will cheerfully refund your money if unsatisfactory, so you take no chances. Booklet giving full description sent free. Correspondence with dealers solicited. Send check, money order or C. O. D. order to

WARNER MOTOR CO., Flatiron Bldg.
Dept. 14 New York City

Davison's Miniatures

Beautiful Watch Charms

CARTRIDGE



Smallest Pistol in the world. Shoots real cartridges, makes loud report. Sent, postage paid, including cartridges and ramrod, for..... 50c



ACTUAL SIZE NO. 1683

Perfect working model Wrench. Exact reproduction of the standard tool, beautifully finished, sent, postage paid, for..... 25c

DAVISON MFG. CO.,
296 Broadway, New York City.

BUILD YOUR OWN BOAT

By the Brooks System

IF you can drive a nail and cut out a piece of material from a full-sized pattern—you can build a canoe—row-boat—sail-boat—or launch—in your leisure time—at home—and the building will be a source of profit and pleasure.

All you need is the patterns, costing from \$2.50 up, and materials, from \$5.00 up. The tools are common in every household. Patterns of over 40 styles and sizes—all lengths from 12 to 55 feet.

The Brooks System consists of exact-size printed paper patterns of every part of the boat—with detailed instructions and working illustrations showing each step of the work—an itemized bill of material required and how to secure it.

Over six thousand amateurs successfully built boats by the Brooks System last year. Fifty per cent. of them have built their second boat. Many have established themselves in the boat manufacturing business.

Catalogue and particulars free. For 25 cents 100-page catalogue containing valuable information for the amateur yachtsman, showing several working illustrations of each boat, and a full set for one boat. Full line of knock-down and completed boats. When so ordered, patterns are expressed, charges prepaid C. O. D. to allow examination.

Brooks Boat Mfg. Co.

Originators of the Pattern
System of Boat Building

3710 Ship St. Bay City, Mich., U. S. A.